



HWREN15

HI-GAIN™ WIRELESS-150N Mini Range Extender

website www.hawkingtech.com
e-mail techsupport@hawkingtech.com

USER'S MANUAL ►►

COPYRIGHT

Copyright ©2011 by Hawking Technologies. All rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual or otherwise, without the prior written permission of this company

Hawking Technologies makes no representations or warranties, either expressed or implied, with respect to the contents hereof and specifically disclaims any warranties, merchantability or fitness for any particular purpose. Any software described in this manual is sold or licensed "as is". Should the programs prove defective following their purchase, the buyer (and not Hawking Technologies, its distributor, or its dealer) assumes the entire cost of all necessary servicing, repair, and any incidental or consequential damages resulting from any defect in the software. Further, this company reserves the right to revise this publication and to make changes from time to time in the contents thereof without obligation to notify any person of such revision or changes.

Federal Communication Commission

Interference Statement

FCC Part 15

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio technician for help.

FCC Caution

This equipment must be installed and operated in accordance with provided instructions and a minimum 20 cm spacing must be provided between computer mounted antenna and person's body (excluding extremities of hands, wrist and feet) during wireless modes of operation.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

Federal Communication Commission (FCC) Radiation Exposure Statement

This equipment complies with FCC radiation exposure set forth for an uncontrolled environment. In order to avoid the possibility of exceeding the FCC radio frequency exposure limits, human proximity to the antenna shall not be less than 20cm (8 inches) during normal operation.

The antenna(s) used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

R&TTE Compliance Statement

This equipment complies with all the requirements of DIRECTIVE 1999/5/EC OF THE EUROPEAN PARLIAMENT AND THE COUNCIL of March 9, 1999 on radio equipment and telecommunication terminal Equipment and the mutual recognition of their conformity (R&TTE).

The R&TTE Directive repeals and replaces in the directive 98/13/EEC (Telecommunications Terminal Equipment and Satellite Earth Station Equipment) As of April 8, 2000.

Safety

This equipment is designed with the utmost care for the safety of those who install and use it. However, special attention must be paid to the dangers of electric shock and static electricity when working with electrical equipment. All guidelines of this and of the computer manufacture must therefore be allowed at all times to ensure the safe use of the equipment.

EU Countries Intended for Use

The ETSI version of this device is intended for home and office use in Austria, Belgium, Denmark, Finland, France, Germany, Greece, Ireland, Italy, Luxembourg, the Netherlands, Portugal, Spain, Sweden, and the United Kingdom.

The ETSI version of this device is also authorized for use in EFTA member states: Iceland, Liechtenstein, Norway, and Switzerland.

EU Countries Not intended for use

None.

CONTENTS

Chapter I: Product Information	1
1-1 Product Introduction	1
1-2 Safety Information	2
1-3 System Requirements	3
1-4 Package Contents	4
1-5 Product Overview	5
Chapter II: Quick Setup and Basic Settings	7
2-1 Installing the 150N Mini Range Extender to your Network	7
2-2 Connecting to the Range Extender by Web Browser	8
2-2-1 Windows 95/98/Me IP Address Setup	9
2-2-2 Windows 2000 IP Address Setup	10
2-2-3 Windows XP IP Address Setup	11
2-2-4 Windows Vista/7 IP Address Setup	13
2-2-5 Mac OS X IP Address Setup	15
2-2-6 Connecting to Web Management Interface	16
2-3 Quick Setup	18
2-4 Status	20
2-5 Wireless Security	21
2-5-1 Disable Security	23
2-5-2 WEP	24
2-5-3 WPA Pre-shared Key	26
2-6 WPS Setting	28
2-7 MAC Filtering	31
Chapter III: Advanced Settings	33
3-1 Advanced Wireless Settings	33
3-2 System Utilities	36
3-2-1 Change Password	36
3-2-2 IP Address of the Wireless Range extender	37
3-2-3 DHCP Server	39
Chapter IV: Advanced Configuration	41
4-1 Configuration Backup and Restore	41
4-2 Firmware Upgrade	43
4-3 System Reset	44
Chapter V Setup Wizard	45
Chapter VI: Appendix	47
6-1 Hardware Specification	47

6-2 Troubleshooting	48
6-3 Glossary	51

Chapter I: Product Information

1-1 Product Introduction

Thank you for purchasing the Hawking HWREN15 Hi-Gain™ Wireless -150N Mini Range Extender!

Easy installation procedures allow any computer user to setup a network in very short time - within minutes, even inexperienced users. Just follow the instructions given in this user manual, you can complete the setup procedure and unleash the power of this range extender all by yourself!

Other features of the 150N Mini Range Extender include:

- Compatibility with IEEE 802.11b/g/Draft-N wireless network standard - works with other 802.11b/g/Draft-N wireless devices.
- High speed wireless network, three times faster than conventional 802.11g wireless network (up to 150Mbps).
- Supports DHCP server function.
- Supports 64/128-bit WEP, WPA, and WPA2 wireless data encryption.
- Supports MAC address filtering (Only allow specific wireless device of your choice to connect to this range extender).
- Supports WPS (Wi-Fi Protected Setup), simplifies wireless client setup procedures. Even inexperienced users can setup wireless network without a network technician's help!
- Easy to use web-based GUI (Graphical User Interface) for network configuration and management purposes.

1-2 Safety Information

In order to keep the safety of users and your properties, please follow the following safety instructions:

1. This range extender is designed for indoor use only; **DO NOT** place this range extender outdoors.
2. **DO NOT** put this range extender near hot or humid places, like a kitchen or bathroom. Also, do not leave this range extender in the car.
3. **DO NOT** pull any connected cable with force; disconnect it from the range extender first.
4. If you want to place this range extender at high places or hang on the wall, please make sure the range extender is firmly secured. Falling from high places would damage the range extender and its accessories, and void the warranty.
5. Accessories of this range extender, like the antenna and power supply, are dangerous to small children under 3 years old. They may put the small parts in their nose or mouth and it could cause serious damage to them. **KEEP THIS RANGE EXTENDER OUT THE REACH OF CHILDREN!**
6. The range extender will become hot when being used for a long time (***This is normal and is not a malfunction***). **DO NOT** put this range extender on paper, cloth, or other flammable materials.
7. There's no user-serviceable part inside the range extender. If you found that the range extender is not working properly, please contact your dealer of purchase and ask for help. **DO NOT** disassemble the range extender, or the warranty will be void.
8. If the range extender falls into water when it's powered, **DO NOT** use your hand to pick it up. Switch the electrical power off before you do anything, or contact an experienced electrical technician for help.
9. If you smell something strange or even see some smoke coming out from the range extender or power supply, remove the power supply or switch the electrical power off immediately, and call dealer of purchase for help.

1-3 System Requirements

- Computer or network device(s) with wired or wireless network interface card.
- Web browser (*Microsoft Internet Explorer 4.0 or above, Netscape Navigator 4.7 or above, Opera web browser, Mozilla Firefox web browser or Safari web browser*).
- An available AC power socket (100 – 240 V, 50/60Hz)

1-4 Package Contents

Before you starting to use this range extender, please check if there is anything missing in the package. Contact your place of purchase to claim missing items:

1x - 150N Mini Range Extender

1x - 2dBi Dipole Antenna

1x - Quick Installation Guide

1x - A/C power adapter




1x - Ethernet cord

1x - Setup CD


1-5 Product Overview

Top Panel



LED Name (Left to Right)	Light Status	Description
WLAN 	On	Wireless is Enabled and Connected
	Off	WLAN is disabled.
	Flashing	Wireless LAN activity (transferring or receiving data)
LAN 1 	On	LAN port is connected
	Off	LAN port is not connected
	Flashing	LAN activity (transferring or receiving data)
LAN 2 	On	LAN port is connected
	Off	LAN port is not connected
	Flashing	LAN activity (transferring or receiving data)

Back Panel



Front Panel



Item Name	Description
Antenna	One SMA antenna connector for the 2dBi detachable antenna enclosed with the product.
Power (5V DC/1A)	Power connector, connects to A/C power adapter.
Wired 1/2	Local Area Network (LAN) ports
WPS/Reset	Reset the router to factory default settings (clear all settings) or start WPS function. Press this button and hold for 15 seconds to restore all settings to factory defaults, power off/on. Press this button for less than 5 seconds to start WPS function.

Chapter II: Quick Setup and Basic Settings

2-1 Installing the 150N Mini Range Extender to your Network

Complete the following instructions to build the network connection between your new wireless range extender and your computers or network devices:

1. Connect the range extender to your computer (source) through the LAN (Wired 1 or Wired 2) port of the range extender by Ethernet cable or connect to it wirelessly.
2. Connect the A/C power adapter to the wall socket, and then connect it to the 'Power' socket of the range extender.
3. Please check all LEDs on the front panel. LAN LEDs should be on if the range extender is correctly connected to the router. If it is not on, or any LED you expect is not on, please recheck the cabling, or jump to '**6-2 Troubleshooting**' for possible reasons and solutions.

2-2 Connecting to the Range Extender by Web Browser

After your 150N Mini Range Extender has been connected and powered the next step is to access the Web Menu for initial configuration. To do this, your computer must be able to get an IP address automatically (use dynamic IP address setting).

Try to access: <http://192.168.1.240>

If the Web Menu appears you can skip the next steps and go to step 2-3. You will need to enter the following default login and password to access the 'Quick Setup' menu:

Login: admin

Password: 1234

If it's set to use a static IP address or you are unsure, please follow the following instructions to configure your computer to use a dynamic IP address:


Note: Please be sure to set your network IP addresses back to default after you have finished configuration.

If the operating system of your computer is....


Windows 95/98/Me	- please go to section 2-2-1
Windows 2000	- please go to section 2-2-2
Windows XP	- please go to section 2-2-3
Windows Vista/7	- please go to section 2-2-4
Mac OS X	- please go to section 2-2-5

2-2-1 Windows 95/98/Me IP Address Setup:

1. Click 'Start' button (it should be located at lower-left corner of your computer), then click control panel. Double-click **Network** icon, and **Network** window will appear. Select 'TCP/IP', then click 'Properties'.




2. Select 'Obtain an IP address from a DHCP server' and then click 'OK'.




2-2-2 Windows 2000 IP Address Setup

1. Click 'Start' button (it should be located at lower-left corner of your computer), then click control panel. Double-click **Network and Dial-up Connections** icon; click **Local Area Connection**, and **Local Area Connection Properties** window will appear. Select 'Internet Protocol (TCP/IP)' and then click 'Properties'




2. Select 'Obtain an IP address automatically' and 'Obtain DNS server address automatically', then click 'OK'.




2-2-3 Windows XP IP Address Setup

1. Click 'Start' button (it should be located at lower-left corner of your computer), then click control panel. Double-click **Network and Internet Connections** icon, click **Network Connections**, and then double-click **Local Area Connection, Local Area Connection Status** window will appear, and then click 'Properties'




2. Select 'Obtain an IP address automatically' and 'Obtain DNS server address automatically', then click 'OK'.




2-2-4 Windows Vista/7 IP Address Setup

1. Click 'Start' button (it should be located at lower-left corner of your computer), then click control panel. Under **Network and Internet**, Click **View Network Status and Tasks**, then click **Manage Network Connections/Change Adapter Settings** on the right hand column. Right-click **Local Area Network**, then select '**Properties**'. **Local Area Connection Properties** window will appear, select 'Internet Protocol Version 4 (TCP / IPv4)', and then click 'Properties'




2. Select 'Obtain an IP address automatically' and 'Obtain DNS server address automatically', then click 'OK'.



2-2-5 Mac OS X IP Address Setup

Go to your system preferences, go to network. Select your network connection. Make sure 'Configure' is set to 'Using DHCP'.



The screenshot shows the Network System Preferences window for an Ethernet connection. The status is 'Cable Unplugged' with a sub-message 'The cable for Ethernet is not plugged in.' The 'Configure' dropdown menu is set to 'Using DHCP'. Below this, there are fields for 'IP Address:', 'Subnet Mask:', 'Router:', 'DNS Server:', and 'Search Domains:'. At the bottom of the window, there are three buttons: 'Assist me...', 'Revert', and 'Apply'. An 'Advanced...' button with a help icon is also visible.

Status: **Cable Unplugged**
The cable for Ethernet is not plugged in.

Configure: Using DHCP

IP Address:

Subnet Mask:

Router:

DNS Server:


Search Domains:

Advanced... ?


Assist me... Revert Apply

2-2-6 Connecting to Web Management Interface

All functions and settings of this range extender can be configured via web management interface. Please start your web browser, and input '192.168.1.240' in address bar, then press the 'Enter' key. The following message should be shown:



Please input user name and password in the fields respectively, default user name is 'admin', and default password is '1234', then press the 'OK' button, and you will see the web management interface of this range extender:



NOTE: If you can't see the web management interface, and you are being prompted to input the user name and password again, it means you didn't input the username and password correctly. Retype the user name and password again. If you're certain about the username and password you typed are correct, please go to '6-2 Troubleshooting' to perform a factory reset.

2-3 Quick Setup

After you have connected to the range extender by web browser, the first thing you see is 'Quick Setup' page. This is where you will setup and connect to your wireless networks.

Step 1) This will prompt you to create a custom name. By default, the range extender will be the same SSID as your original wireless network. If you wish to change it, please uncheck and manually input a custom name. Otherwise, leave checked.

- 1** By default, the HWREN15 will use the same SSID as your home wireless connection.
Note: To name the extended SSID with a different SSID, please uncheck the box below:

SSID:

Step 2) Please select your wireless network from the list below by selecting the network with your mouse. If your wireless network does not appear, please click 'Scan' so our HWREN15 can rescan the wireless networks. You can also manually input your SSID and channel if you know them.

2 Scan for a wireless network to extend your WiFi network:

1	Hawking Tech	WEP	OPEN	89%
2	SSA	WEP	OPEN	89
2	BFRE-Wireless	TKIP	WPASK	89
3	WLAN	TKIP	WPASK	89
4	Hawking Tech	WEP	OPEN	89

-OR- If you want to manually input your SSID:

Source AP ID: Enter the SSID and channel of your original access point:

SSID: Ch: #

Step 3) After you select your network, press "Connect" to proceed to the next step.

- 3** Select and click Connect:

Step 4) If your wireless network requires a password, the next page should prompt you to enter your wireless key. This key should be the exact same key as your wireless access point or wireless router. Please contact your network administrator if you do not know the security code.

Click 'Continue' to proceed to the next step or 'Back' if you wish to make some changes.

Welcome to the Setup Wizard

The wireless network you are trying to connect has wireless security enabled. Please enter the security code below:

If you do not know your security code, please contact the network administrator.



Security key or passphrase:

Display characters

Back

Continue

Step 5) Final summary page. If everything seems to be in order, please click 'Finish'. Your device should automatically reboot and restart after 30 seconds. If you need to make changes, please click 'Back'.

Welcome to the Setup Wizard

Congratulations, you have completed the setup of your H-Gain™ Wireless-150N Mini Range Extender

Wireless Configuration

Range Extender ID:

Source Access Point ID:

Wireless Channel

Encryption Security:


Click Back if you wish to change any of the setting above.

Back

Finish

2-4 Status

The Status time will give you a quick run through of the basic settings on the 150N Wireless-150N Mini Range Extender.



System

<i>Up Time</i>	<i>How long the device has been running.</i>
<i>Hardware Version</i>	<i>Current Version of the hardware.</i>
<i>Runtime Code Version</i>	<i>Current Version of the firmware.</i>

Wireless Configuration

<i>Range Extender ID</i>	<i>The HWREN15's wireless name (SSID)</i>
<i>Source Access Point ID</i>	<i>SSID of the connected access point/wireless router</i>
<i>Encryption Security</i>	<i>The type of wireless security being used.</i>

Network Configuration


<i>IP Address</i>	<i>IP address of the HWREN15</i>
<i>Subnet Mask</i>	<i>Subnet Mask of the HWREN15</i>
<i>Default Gateway</i>	<i>Gateway address of the HWREN15</i>
<i>MAC Address</i>	<i>MAC address of the HWREN15</i>

2-5 Wireless Security

This wireless range extender provides many types of wireless security (wireless data encryption). When you use data encryption, data transferred by radio signals in the air will become unreadable for those people who don't know correct encryption key (encryption password).

Note: All security settings for the Range Extender must be identical to the original root Access Point's/Wireless Router's security settings. If you do not know, refer to your manual or contact your network admin for this information.

1. Click the 'Security' tab and on the left hand column, click the 'Wireless Security' sub-tab in the web management interface.



The screenshot shows a web management interface with a navigation menu on the left containing 'MAC Address Filtering' and 'Wireless Security'. The main content area is titled 'Wireless Security' and includes a descriptive paragraph: 'This section allows your data being transmitted over the wireless network securely. If this function is enabled, please make sure your wireless stations are using the same encryption keys as the Access Point.' Below this, there are several configuration options: 'WEP Mode' set to '128-bit WEP', 'Key Length' set to '128-bit', 'Key Format' set to 'ASCII (5 Characters)', and 'Default Transmit Key' set to 'Key 1'. There are four 'Encryption Key' input fields, each containing a series of asterisks. At the bottom right, there are 'Apply' and 'Cancel' buttons.

There are three types of security levels you can select: Disable (no security - data encryption disabled), WEP, WPA Pre-shared Key. Please refer to the following sections for detailed instructions.

Please remember it's very important to set wireless security settings properly! Without a proper setting, hackers and intruders may gain access to your local network and cause serious problems in your network.

There are several things you can do to improve wireless security:

1. Always enable data encryption. Only disable it when you want to open your wireless range extender to the public.
2. Never use simple words as encryption password. Using random combinations of symbols, numbers, and alphabets will greatly improve security.
3. Use WPA when possible - it's much safer than WEP.
4. Change encryption password after you've used it for too long time.

2-5-1 Disable Security

Note: The wireless security must match whatever network you are trying to extend. Otherwise, the device will not function.

When you select 'Disable', wireless encryption for the network is disabled.

Wireless Security

This section allows your data to be transmitted over the wireless network securely. If this function is enabled, please make sure your wireless Range Extender is using the same encryption keys as the original root Access Point.

Encryption :

Enable 802.1x Authentication

After you finish with setting, click 'Apply', and the following message will be displayed:

Save setting successfully!

You may press CONTINUE button to continue configuring other settings or press APPLY button to restart the system for changes to take effect


When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.

2-5-2 WEP

WEP (Wired Equivalent Privacy) is a common encryption mode. It is safe enough for home and personal use but if you need higher level of security, please consider using WPA encryption (see next Section).

However, some wireless clients don't support WPA, but only support WEP, so WEP is still a good choice for you if you have such a client in your network environment.

When you select 'WEP' as encryption type, the following page will be displayed:



The screenshot shows a configuration window for WEP encryption. It includes the following fields and options:


- Encryption : WEP (dropdown menu)
- Key Length : 64-bit (dropdown menu)
- Key Format : Hex (10 characters) (dropdown menu)
- Default Tx Key : Key 1 (dropdown menu)
- Encryption Key 1 : [Masked text box]
- Encryption Key 2 : [Masked text box]
- Encryption Key 3 : [Masked text box]
- Encryption Key 4 : [Masked text box]
- Enable 802.1x Authentication
- Apply (button)
- Cancel (button)

Here are descriptions of every setup item:

<i>Key Length</i>	<i>There are two types of WEP key length: 64-bit and 128-bit. Using 128-bit is safer than 64-bit, but will reduce some data transfer performance.</i>
<i>Key Format</i>	<i>There are two types of key format: ASCII and Hex. When you select a key format, the number of characters of key will be displayed. For example, if you select 64-bit as key length, and Hex as key format, you'll see the message at the right of 'Key</i>

	<i>Format' is Hex (10 characters), which means the length of WEP key is 10 characters.</i>
<i>Default Tx Key</i>	<i>You can set up to four sets of WEP key, and you can decide which key is being used by default here. If you don't know which one you should use, select "Key 1".</i>
<i>Encryption Key 1 to 4</i>	<i>Input WEP key characters here, the number of characters must be the same as the number displayed at "Key Format" field. You can use any alphanumerical characters (0-9, a-z, and A-Z) if you select 'ASCII' key format, and if you select "Hex" as key format, you can use characters 0-9, a-f, and A-F. You must enter at least one encryption key here, and if you entered multiple WEP keys, they should not be same with each other.</i>
<i>Enable 802.1x Authentication</i>	<i>Check this box to enable 802.1x user authentication.</i>

After you finish with setting, click 'Apply', and the following message will be displayed:




When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.

2-5-3 WPA Pre-shared Key

WPA Pre-shared key is currently the safest encryption method. It is recommended to use this encryption method to ensure the safety of your data.

When you select 'WPA pre-shared key' as encryption type, the following messages will be displayed:




The screenshot shows a configuration dialog box for WPA Pre-shared Key. It contains the following fields and options:

- Encryption : WPA pre-shared key (dropdown menu)
- WPA Unicast Cipher Suite : WPA(TKIP) WPA2(AES) WPA2 Mixed
- Pre-shared Key Format : Passphrase (dropdown menu)
- Pre-shared Key : (empty text input field)
- Buttons: Apply, Cancel

Here are descriptions of every setup item:

<i>WPA Unicast Cipher Suite</i>	<i>Available options are: WPA (TKIP), WPA2 (AES), and WPA2 Mixed. You can select one of them, but you have to make sure your wireless client supports the cipher you selected.</i>
<i>Pre-shared Key Format</i>	<i>Please select the format of pre-shared key here, available options are "Passphrase" (8 to 63 alphanumerical characters) and "Hex" (64 hexadecimal characters – 0 to 9 and a to f).</i>
<i>Pre-shared Key</i>	<i>Please input pre-shared key according to the key format you selected here. For security reasons, don't use simple words).</i>

After you finish with setting, click 'Apply', and the following message will be displayed:



When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.

2-6 WPS Setting

Wi-Fi Protected Setup (WPS) is the simplest way to build a connection between wireless network clients and this extender. You don't have to select encryption mode and input a long encryption passphrase every time when you need to setup a wireless client, you only have to press a button on wireless client and this extender, and the WPS will do the setup for you.

This range supports two types of WPS: Push-Button Configuration (PBC), and PIN code. If you want to use PBC, you have to switch this range extender to WPS mode and push a specific button on the wireless client to start WPS mode. You can push Reset/WPS button of this range extender or click 'Start PBC' button in the web configuration interface to do this; if you want to use PIN code, you have to provide the PIN code of the wireless client you wish to connect to this extender and then switch the wireless client to WPS mode. The detailed instructions are listed below:

Note: WPS function of this range extender will not work for those wireless clients that do not support WPS.

To use WPS function to set encrypted connection between this extender and WPS-enabled wireless client by WPS, click 'WPS Setting' on the left of web management menu, and the following information will be displayed:

WPS (Wi-Fi Protected Setup) Setting

This page allows you to change the setting for WPS(Wi-Fi Protected Setup).WPS can help your wireless client automatically connect to the Access Point.

Enable WPS

Enable WPS Proxy

Wi-Fi Protected Setup Information

WPS Status: Configured
 Self PinCode: 10328149
 SSID: HawkTech HawkTech
 Authentication Mode: WPA pre-shared key WPA pre-shared key
 Passphrase Key: *****

Device Configure

Config Mode: Registrar ▼

Configure via Push Button:

Configure via Client PinCode:

Here are descriptions of every setup item:

<i>Enable WPS</i>	<i>Check this box to enable or disable WPS function</i>
<i>Wi-Fi Protected Setup Information</i>	<p><i>WPS Status: Displays WPS status. If data encryption settings of this extender has never been set, an 'unConfigured' message will be displayed here. If the data encryption settings have been set before, a 'Configured' message will be displayed here.</i></p> <p><i>Self PinCode: This is the WPS PIN code of this extender. This code is useful when you need to build wireless connection by WPS with other WPS-enabled wireless devices.</i></p> <p><i>SSID: Displays the SSID (ESSID) of this extender.</i></p>

	<p><i>Authentication Mode: The wireless security authentication mode of this extender will be displayed here. If you don't enable security function of the range extender before WPS is activated, the extender will auto set the security to WPA (AES) and generate a set of passphrase keys for WPS connection.</i></p> <p><i>Passphrase Key: Displays the WPA passphrase here, all characters will be replaced by asterisk for security reasons. If encryption is not set on this extender, nothing will be displayed here.</i></p>
<i>Config Mode</i>	<i>There are 'Registrar' and 'Enrollee' modes for the WPS connection. When 'Registrar' is enabled, the wireless clients will follow the extender's wireless settings for WPS connection. When 'Enrollee' mode is enabled, the extender will follow the wireless settings of wireless client for WPS connection.</i>
<i>Start PBC</i>	<i>Click 'Start PBC' to start Push-Button style WPS setup procedure. This range extender will wait for WPS requests from wireless clients for 2 minutes. The 'WLAN' LED on the range extender will be steady on for 2 minutes when this extender is waiting for incoming WPS request.</i>
<i>Start PIN</i>	<i>Please input the PIN code of the wireless client you wish to connect, and click 'Start PIN' button. The 'WLAN' LED on the extender will be steady on when this extender is waiting for incoming WPS request.</i>

NOTE: When you're using PBC type WPS setup, you must press 'PBC' button (hardware or software) of wireless client within 120 seconds; if you didn't press PBC button of wireless client within this time period, please press 'PBC' button (hardware or software) of this extender again.

2-7 MAC Filtering

Another security measure you can use to keep hackers and intruders away is ‘MAC filtering’. You can pre-define a so-called ‘white-list’, which contains MAC addresses of the wireless clients you trust. All other wireless clients with a MAC address that is not in your list will be denied by this wireless range extender.

To setup MAC filtering, click ‘MAC Address Filtering’ on left hand column under the ‘Security’ tab in the web management interface and the following page will be displayed:

The screenshot shows a web management interface with a navigation menu on the left and a main content area. The navigation menu includes 'Quick Setup', 'Status', 'Security', 'Advanced Settings', 'Configuration', 'Upgrade', and 'Reset'. The 'Security' tab is selected, and 'MAC Address Filtering' is highlighted in the left sidebar. The main content area is titled 'MAC Address Filtering' and contains the following elements:

- A header bar with 'Quick Setup', 'Status', 'Security', 'Advanced Settings', 'Configuration', 'Upgrade', and 'Reset'.
- A sub-header 'MAC Address Filtering'.
- A paragraph: 'For security reason, the Range Extender features MAC Address Filtering that only allows authorized MAC Addresses associating to the Range Extender.'
- A checkbox labeled 'Enable Wireless Access Control' which is checked.
- A table with two columns: 'MAC Address' and 'Comment'. Below the table are two input fields and 'Add' and 'Reset' buttons.
- A section titled 'MAC Address Filtering List' containing a table with columns 'No.', 'MAC Address', and 'Select'. Below the table are 'Delete Selected', 'Delete All', and 'Reset' buttons.

This page contains two parts of MAC filtering information. All allowed MAC addresses will be listed in upper part, and you can add new MAC addresses by components in lower part.

Here are descriptions of every setup item:

<i>Enable Wireless Access Control</i>	<i>Check this box to enable MAC address restriction. If unchecked, no restriction will be enforced (any wireless client with proper encryption setting will be able to connect to this wireless range extender).</i>
---------------------------------------	--

<i>MAC address</i>	<i>Input MAC address allowed using this wireless range extender here. You don't have to add colon (:) or hyphen (-) by yourself, just input 0 to 9 and a to f here, like 112233445566 or aabbccddeeff.</i>
<i>Comment</i>	<i>You can input any text here as the comment of this MAC address, like 'ROOM 2A Computer' or anything. You can input up to 16 alphanumerical characters here. This is optional and you can leave it blank. However, it's recommended to use this field to write a comment for every MAC address as a memory aid. This is optional.</i>
<i>Add</i>	<i>When you finish inputting MAC address and (optional) Comment, click this button to add the MAC address to the list.</i>
<i>Reset</i>	<i>Remove all characters in 'MAC address' and 'Comments' field.</i>
<i>Select</i>	<i>Check this box to select one or more MAC addresses to delete.</i>
<i>Delete Selected</i>	<i>Click this button to delete all selected MAC addresses.</i>
<i>Delete All</i>	<i>Delete all MAC address entries.</i>
<i>Reset</i>	<i>Uncheck all selected MAC address entries.</i>

After you finish with setting, click 'Apply', and the following message will be displayed:

Save setting successfully!

You may press CONTINUE button to continue configuring other settings or press APPLY button to restart the system for changes to take effect

When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.

Chapter III: Advanced Settings

3-1 Advanced Wireless Settings

This wireless range extender has many advanced wireless features. Please note that all settings listed here are for experienced users only, if you're not sure about the meaning and function of these settings, do not modify them, or the wireless performance will be reduced.

You can click 'Advanced Setting' tab at the top of web interface to enter advanced settings menu, and the following message will be displayed:

Advanced Wireless Settings

This section allows your data being transmitted over the wireless network securely. If this function is enabled, please make sure your wireless stations are using the same encryption keys as the Access Point.

Fragment Threshold: (256-2346)
RTS Threshold: (0-2347)
Beacon Interval: (20-1024 ms)
DTIM Period: (1-10)
Data Rate: ▾
N Data Rate: ▾
Channel Width: Auto 20/40 MHZ 20 MHZ
Preamble Type: Short Preamble Long Preamble
Broadcast ESSID: Enable Disable
WMM: Enable Disable
CTS Protect: Auto Always None
TX Power: ▾


Here are descriptions of every setup item:

<i>Fragment Threshold</i>	<i>Set the Fragment threshold of wireless radio. Do not modify default value if you don't know what it is, default value is 2346</i>
---------------------------	---

<i>RTS Threshold</i>	<i>Set the RTS threshold of wireless radio. Do not modify default value if you don't know what it is, default value is 2347</i>
<i>Beacon Interval</i>	<i>Set the beacon interval of wireless radio. Do not modify default value if you don't know what it is, default value is 100</i>
<i>DTIM Period</i>	<i>Set the DTIM period of wireless radio. Do not modify default value if you don't know what it is, default value is 3</i>
<i>Data Rate</i>	<i>Set the wireless data transfer rate to a certain value. Since most of wireless devices will negotiate with each other and pick a proper data transfer rate automatically, it's not necessary to change this value unless you know what will happen after modification.</i>
<i>N Data Rate</i>	<i>Set the data rate of 802.11 Draft-N clients, available options are MCS 0 to MCS 15, it's safe to set this option to 'Auto' and it's not necessary to change this value unless you know what will happen after modification.</i>
<i>Channel Width</i>	<i>Select wireless channel width (bandwidth taken by wireless signals of this range extender). It's suggested to select 'Auto 20/40MHz'. Do not change to '20 MHz' unless you know what it is.</i>
<i>Preamble Type</i>	<i>Set the type of preamble of wireless radio, Do not modify default value if you don't know what it is, default setting is 'Short Preamble'.</i>
<i>Broadcast ESSID</i>	<i>Decide if the wireless range extender will broadcast its own ESSID or not. You can hide the ESSID of your wireless range extender (set the option to 'Disable'), so only people those who know the ESSID of your wireless range extender can get connected.</i>
<i>WMM</i>	<i>WMM (Wi-Fi Multimedia) technology, which can improve the performance of certain network applications, like audio/video streaming, network telephony (VoIP), and others. When you enable WMM function, the range extender will define the</i>

	<i>priority of different kinds of data, to give higher priority to applications which require instant responding. Therefore you can improve the performance of such network applications.</i>
<i>CTS Protect</i>	<i>Enabling this setting will reduce the chance of radio signal collisions between 802.11b and 802.11g wireless range extenders. It's recommended to set this option to 'Auto'.</i>
<i>TX Power</i>	<i>You can set the output power of wireless radio. Unless you're using this wireless range extender in a really big space, you may not have to set output power to 100%. This will enhance security (malicious / unknown users in distance will not be able to reach your wireless range extender).</i>

After you finish with setting, click 'Apply', and the following message will be displayed:



When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.


3-2 System Utilities

This range extender provides some control functions including password, IP address management, and DHCP server function. Click 'Advanced Settings' tab and then click 'System Utility' sub-tab beneath it in the web management interface to access these functions. Below are detailed descriptions of every control function.

3-2-1 Change Password


You can change the password used to enter the web configuration menu of this wireless range extender.

Click 'System Utility' on the left column, and the following message will be displayed:



The screenshot shows a web form titled "Password Settings" with a dark header. Below the header are three input fields: "Current Password:", "New Password:", and "Retype Password:". Each label is followed by a white rectangular input box with a thin border.

Input current password in 'Current Password' field, then input new password in both 'New Password' and 'Re-Enter Password' fields. After you finish, please go to the bottom of this page and click 'Apply', and the following message will be displayed:



The screenshot shows a message box with a black border. At the top, it says "Save setting successfully!". Below that, it says "You may press CONTINUE button to continue configuring other settings or press APPLY button to restart the system for changes to take effect". At the bottom, there are two buttons: "Continue" and "Apply".

When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.


3-2-2 IP Address of the Wireless Range extender

You can change the IP address of this wireless range extender so it can become a part of your local network. Please remember this address or you will not be able to connect to the configuration menu of this wireless range extender.

Default IP address: 192.168.1.240 / Subnet Mask: 255.255.255.0.

You can press and hold 'Reset' button 15 seconds, then power off/on to change the IP address back to default value if you forget the IP address you set.

To change IP address, please click 'System Utility' sub-tab, and the following message will be displayed:




The screenshot shows a configuration page titled "Management IP". It contains five input fields and a dropdown menu:

- IP Address: 192.168.1.240
- Subnet Mask: 255.255.255.0
- Gateway Address: 0.0.0.0
- DNS Server: 0.0.0.0
- DHCP Server: Enable (with a dropdown arrow)

Please input IP address and Subnet Mask in corresponding field, and you can input the IP address of gateway in the 'Gateway Address' field, if you need to manage this wireless range extender from another network (like the Internet).

If you want to activate the DHCP server function of this wireless range extender, select 'Enabled' in 'DHCP Server' option. Please go to section 3-2-3 for DHCP settings. If you don't want to use DHCP server function of this wireless range extender, or there's another DHCP server on the network, please select 'Disable'. The default mode for the DHCP server is 'Disable'.

After you finish, please go to the bottom of this page and click 'Apply', and the following message will be displayed:



When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.

3-2-3 DHCP Server

This wireless range extender is capable of acting as a DHCP server for your network, but it's disabled by default. If you want to activate this function, please click 'System Utility' sub-tab and the following message will be displayed:

DHCP Server

Default Gateway IP:

Domain Name Server IP:

Gateway Address:

Start IP:

Domain Name:

Lease Time: ▼


NOTE: Please remember to select 'Enable' in 'DHCP Server' option as described in Section 3-2-2 or all DHCP-related fields will be grayed out, and you will not be able to input any DHCP parameter.

Here are descriptions of every setup item:

<i>Default Gateway IP</i>	<i>Please input the IP address of default gateway of your network here.</i>
<i>Domain Name Server IP</i>	<i>Please input the IP address of domain name server (DNS) here.</i>
<i>Start IP</i>	<i>Please input the start IP address of the IP range.</i>
<i>End IP</i>	<i>Please input the end IP address of the IP range.</i>
<i>Domain Name</i>	<i>If you wish, you can also optionally input the domain name for your network. This is optional.</i>
<i>Lease Time</i>	<i>Please choose a lease time (the duration that every computer can keep a specific IP address) of every IP address assigned by this range extender from dropdown menu.</i>

After you finish, please go to the bottom of this page and click 'Apply',

and the following message will be displayed:



When you see this message, the settings you made are successfully saved. You can click the 'Continue' button to return to the previous page and modify other settings, or click the 'Apply' button to restart the wireless range extender. The changes will take effect after about 30 seconds.

Chapter IV: Advanced Configuration

4-1 Configuration Backup and Restore

You can backup all configurations of this range extender to a file, so you can make several copies of range extender configuration for security reasons.

To backup or restore range extender configuration, please follow the following instructions:

Click the 'Configuration' tab in the web management interface, and the following message will be displayed on your web browser:

Backup Tool

Use the "Backup tool" to save the Range Extender's current configurations to a file named "config.bin". You can restore your previous setting by selecting the pervious "config.bin" file. Alternatively, you can use the "Restore to Factory Default" tool to force the Range Extender to perform System Reset and restore the original factory settings.

Backup Settings

Restore Settings

Restore to Factory Default

Here are descriptions of every button:

<i>Backup Settings</i>	<i>Press "Save" button, and you'll be prompted to download the configuration as a file, default filename is "config.bin", you can save it as another filename for different versions, and keep it in a safe place.</i>
------------------------	--

<i>Restore Settings</i>	<i>Press “Browse” to pick a previously-saved configuration file from your computer, and then click “Upload” to transfer the configuration file to range extender. After the configuration is uploaded, the range extender’s configuration will be replaced by the file you just uploaded.</i>
<i>Restore to Factory Default</i>	<i>Click this button to remove all settings you made, and restore the configuration of this range extender back to factory default settings.</i>

4-2 Firmware Upgrade

If there is new firmware available for your wireless range extender, you can upload the firmware to the range extender to change the firmware to the updated version to get extra functions or fix problems.

To perform firmware upgrade, click 'Upgrade' tab on the top-right of web management interface, and the following message will be displayed:

Upgrade

This tool allows you to upgrade the Range Extender's system firmware. It is recommended that upgrading the firmware from wired stations.

Enter the path and name of the upgrade file and then click the Apply button below. You will be prompted to confirm the upgrade.

Current Firmware Version: x.xx

Click 'Browse' button first. You will be prompted to provide the filename of firmware upgrade file. Download the latest firmware file from our website (<http://www.hawkingtech.com/>) and save it to a location on your computer. Then browse to it and use it to upgrade your range extender.

After a firmware upgrade file is selected, click 'Apply' button, and the range extender will start firmware upgrade procedure automatically. The procedure may take several minutes.

NOTE: Never interrupt the upgrade procedure by closing the web browser or physically disconnecting your computer from the range extender. If the firmware you uploaded is corrupt, the firmware upgrade will fail, and you may have to return this range extender. (Warranty is void if you interrupt the upgrade procedure).

4-3 System Reset

When you think the range extender is not working properly, you can use this function to restart the range extender; this may help to solve certain problems.

This function is useful when the range extender is far from you or unreachable. However, if the range extender is not responding, you may have to switch it off by unplugging the power plug and plugging it back again after 10 seconds.


To reset your range extender, please click 'Reset' tab in the web management interface, and the following message will be displayed:

Reset

In the event that the system stops responding correctly or stops functioning, you can perform a Reset. Your current settings will not be modified. To perform the reset, click on the Apply button below. You will be asked to confirm your decision. The Reset will be complete when the LED Power light stops blinking. To perform a factory restore, hold down the reset button for 30 seconds and power off/on. This will restore your device to factory default.



Please click 'Apply', and a popup message will ask you again, to make sure you really want to reset the range extender:



Click 'OK' to reset the range extender, or click 'Cancel' to abort. Please remember all connections between wireless client and this range extender will be disconnected.


Chapter V Setup Wizard

The HWREN15 Setup Wizard is used to help troubleshoot a connection or for easy access to the basic configuration settings of the HWREN15. This Utility may often be used in conjunction with support calls from our support department or by the user when on site for quick configuration purposes.



To run the support utility, insert the CD into your computer's CD rom and click on 'Setup Wizard'. Note: this utility only supports Windows operating systems. If your computer prompts you, please allow the program through your firewall.

The following window should appear. If no devices appear automatically, please click on 'Scan'.



You should see your device listed under Mac Address. Each HWREN15 on the network will have a unique Mac Address. This number should correspond to the numbers/letters listed on the bottom of your device. Please select the unit that you wish to configure. Next to the Mac Address, there will be an IP address that is assigned to that particular HWREN15. Highlight the unit and click ‘Connect’. A web browser will open and take you into the setup page of the device. (Refer to earlier sections on this manual.)

If the device does not appear, you may have to reset the unit. Press and hold the reset button for 15 seconds, power off/on. Then reconnect and start from section 2-1.

Chapter VI: Appendix

6-1 Hardware Specification

SoC+ RF: Realtek RTL 8136C + Realtek RTL 8188CE

Flash: 2MB

SDRAM: 16MB

LAN Port: 10/100M UTP Port x 2

Antenna: 2dBi Detachable Dipole Antenna

Power: 5VDC, 1A Switching Power Adapter

Dimension: 20(H) x 58(W) x 87(D) mm

Transmit Power: 11n: 13dBm±1.5dBm, 11g: 14dBm±1.5dBm, 11b: 17dBm±1.5dBm

Temperature: 32~104°F (0 ~ 40°C)

Humidity: 10-90% (NonCondensing)

Certification: FCC, CE

6-2 Troubleshooting

If you found the range extender is working improperly or stops responding to you, don't panic! Before you contact your dealer of purchase for help, please read this troubleshooting first. Some problems can be solved by yourself within very short time!

Scenario	Solution
Range extender disconnects after a period of time.	a. Check the wireless channel on your router. Make sure it is set to a static channel. Some routers use an AUTO channel function in which the channel changes itself periodically. If so, our range extender cannot update these changes and that may explain your disconnects.
Range extender is not responding to me when I want to access it by web browser	b. Please check the connection of power cord and network cable of this range extender. All cords and cables should be correctly and firmly inserted to the range extender. c. If all LEDs on this range extender are out, please check the status of A/C power adapter, and make sure it's correctly powered. d. You must use the same IP address section which range extender uses. e. Are you using MAC or IP address filter? Try to connect the range extender by another computer and see if it works; if not, please perform a hard reset (pressing 'reset' button for 15 seconds, power off/on). f. Set your computer to obtain an IP address automatically (DHCP), and see if your computer can get an IP address. g. If you did a firmware upgrade and this happens, contact your dealer of purchase for help. h. If all above solutions don't work, contact Hawking Technologies for help.

<p>Can't get connected to wireless range extender</p>	<ol style="list-style-type: none"> a. If encryption is enabled, please re-check WEP or WPA passphrase settings on your wireless client. b. Try to move closer to wireless range extender. c. Unplug the power plug of range extender, and plug it back again after 10 seconds. d. If all LEDs on this range extender are out, please check the status of A/C power adapter, and make sure it's correctly powered.
<p>I can't locate my range extender by my wireless client</p>	<ol style="list-style-type: none"> a. 'Broadcast ESSID' set to off? b. Is Antenna properly installed and secured? c. Are you too far from your range extender? Try to get closer. d. Please remember that you have to input ESSID on your wireless client manually, if ESSID broadcast is disabled.
<p>File download is very slow or breaks frequently</p>	<ol style="list-style-type: none"> a. Try to reset the range extender and see if it's better after that. b. Try to know what computers do on your local network. If someone's transferring big files, other people will think Internet is really slow. c. Change the wireless channel on your router and reconfigure our device to match this. Sometimes interference can cause slowness.
<p>I can't log onto web management interface: password is wrong</p>	<ol style="list-style-type: none"> a. Make sure you're connecting to the correct IP address of the range extender! b. Password is case-sensitive. Make sure the 'Caps Lock' light is not illuminated. c. If you really forget the password, do a hard reset.
<p>Range extender is very hot</p>	<ol style="list-style-type: none"> a. If you smell something wrong or see the smoke coming out from range extender or A/C power adapter, please disconnect the range extender and A/C power adapter from utility power (make sure it's safe before

	you're doing this!), and call Hawking Technologies for help.
--	--

6-3 Glossary

Default Gateway (Range extender): Every non-range extender IP device needs to configure a default gateway's IP address. When the device sends out an IP packet, if the destination is not on the same network, the device has to send the packet to its default gateway, which will then send it out towards the destination.

DHCP: Dynamic Host Configuration Protocol. This protocol automatically gives every computer on your home network an IP address.

DNS Server IP Address: DNS stands for Domain Name System, which allows Internet servers to have a domain name (such as www.Broadbandrange extender.com) and one or more IP addresses (such as 192.34.45.8). A DNS server keeps a database of Internet servers and their respective domain names and IP addresses, so that when a domain name is requested (as in typing "Broadbandrange extender.com" into your Internet browser), the user is sent to the proper IP address. The DNS server IP address used by the computers on your home network is the location of the DNS server your ISP has assigned to you.

DSL Modem: DSL stands for Digital Subscriber Line. A DSL modem uses your existing phone lines to transmit data at high speeds.

Ethernet: A standard for computer networks. Ethernet networks are connected by special cables and hubs, and move data around at up to 10/100 million bits per second (Mbps).

Idle Timeout: Idle Timeout is designed so that after there is no traffic to the Internet for a pre-configured amount of time, the connection will automatically be disconnected.

IP Address and Network (Subnet) Mask: IP stands for Internet Protocol. An IP address consists of a series of four numbers separated by periods, that identifies a single, unique Internet computer host in an IP network. Example: 192.168.2.1. It consists of 2 portions: the IP network address, and the host identifier.

The IP address is a 32-bit binary pattern, which can be represented as four cascaded decimal numbers separated by ".": aaa.aaa.aaa.aaa, where each

“aaa” can be anything from 000 to 255, or as four cascaded binary numbers separated by “.”: bbbbbbbb.bbbbbbbb.bbbbbbbb.bbbbbbbb, where each “b” can either be 0 or 1.

A network mask is also a 32-bit binary pattern, and consists of consecutive leading

1’s followed by consecutive trailing 0’s, such as

11111111.11111111.11111111.00000000. Therefore sometimes a network mask can also be described simply as “x” number of leading 1’s.

When both are represented side by side in their binary forms, all bits in the IP address that correspond to 1’s in the network mask become part of the IP network address, and the remaining bits correspond to the host ID.

For example, if the IP address for a device is, in its binary form,

11011001.10110000.10010000.00000111, and if its network mask is, 11111111.11111111.11110000.00000000

It means the device’s network address is

11011001.10110000.10010000.00000000, and its host ID is,

00000000.00000000.00000000.00000111. This is a convenient and efficient method for range extenders to route IP packets to their destination.

ISP Gateway Address: (see ISP for definition). The ISP Gateway Address is an IP address for the Internet range extender located at the ISP’s office.

ISP: Internet Service Provider. An ISP is a business that provides connectivity to the Internet for individuals and other businesses or organizations.

LAN: Local Area Network. A LAN is a group of computers and devices connected together in a relatively small area (such as a house or an office). Your home network is considered a LAN.

MAC Address: MAC stands for Media Access Control. A MAC address is the hardware address of a device connected to a network. The MAC address is a unique identifier for a device with an Ethernet interface. It is comprised of two parts: 3 bytes of data that corresponds to the Manufacturer ID (unique for each manufacturer), plus 3 bytes that are often used as the product’s serial number.

NAT: Network Address Translation. This process allows all of the computers on your home network to use one IP address. Using the broadband range extender's NAT capability, you can access the Internet from any computer on your home network without having to purchase more IP addresses from your ISP.

Port: Network Clients (LAN PC) uses port numbers to distinguish one network application/protocol over another. Below is a list of common applications and protocol/port numbers:

Application	Protocol	Port Number
Telnet	TCP	23
FTP	TCP	21
SMTP	TCP	25
POP3	TCP	110
H.323	TCP	1720
SNMP	UCP	161
SNMP Trap	UDP	162
HTTP	TCP	80
PPTP	TCP	1723
PC Anywhere	TCP	5631
PC Anywhere	UDP	5632

PPPoE: Point-to-Point Protocol over Ethernet. Point-to-Point Protocol is a secure data transmission method originally created for dial-up connections; PPPoE is for Ethernet connections. PPPoE relies on two widely accepted standards, Ethernet and the Point-to-Point Protocol. It is a communications protocol for transmitting information over Ethernet between different manufacturers

Protocol: A protocol is a set of rules for interaction agreed upon between multiple parties so that when they interface with each other based on such a protocol, the interpretation of their behavior is well defined and can be made objectively, without confusion or misunderstanding.

Range extender: A range extender is an intelligent network device that forwards packets between different networks based on network layer address information such as IP addresses.

Subnet Mask: A subnet mask, which may be a part of the TCP/IP information provided by your ISP, is a set of four numbers (e.g. 255.255.255.0) configured like an IP address. It is used to create IP address numbers used only within a particular network (as opposed to valid IP address numbers recognized by the Internet, which must be assigned by InterNIC).

TCP/IP, UDP: Transmission Control Protocol/Internet Protocol (TCP/IP) and Unreliable Datagram Protocol (UDP). TCP/IP is the standard protocol for data transmission over the Internet. Both TCP and UDP are transport layer protocol. TCP performs proper error detection and error recovery, and thus is reliable. UDP on the other hand is not reliable. They both run on top of the IP (Internet Protocol), a network layer protocol.

Universal Repeater: Another name for range extender.

WAN: Wide Area Network. A network that connects computers located in geographically separate areas (e.g. different buildings, cities, countries). The Internet is a wide area network.

Web-based management Graphical User Interface (GUI): Many devices support a graphical user interface that is based on the web browser. This means the user can use the familiar Netscape or Microsoft Internet Explorer to Control/configure or monitor the device being managed.