



ScanSnap iX500



Scan
Wirelessly
to PC or
Mac



iOS



Scan to iOS and Android too!

shaping tomorrow with you



ScanSnap

Simple, Fast & Wireless!

Free yourself with ScanSnap iX500!

Wi-Fi scanning to a PC or Mac

And now iOS and Android mobile device and tablets

Easy One-button PDF creation

Just stack in the paperwork and press the scan button

Handles a stack of documents

Load up to 50 sheets in the automatic document feeder

Scans both sides of each page at the same time

Images are automatically straightened and cropped with blank sides removed

Fast and reliable document scanning

Scans up to 25 pages per minute with advanced paper handling

Scans business cards to oversized documents

With carrier sheet, scans A3 documents, photos, and much more



Wi-Fi or USB connectivity to a computer



Break free from USB and place ScanSnap just about anywhere in the room with Wi-Fi connectivity to a PC or Mac.*

* May require latest online updates. Requires use of an existing wireless router. Only one computer can be registered for Wi-Fi connection.

Scan directly to mobile devices



Quickly bypass the computer altogether and scan a PDF or JPEG file directly to an iOS or Android mobile device or tablet.*

* See list of supported devices at <http://scansnap.fujitsu.com>

Advanced paper feeding system

Inheriting the superior paper feeding technology of our professional-grade scanners, iX500 achieves exceptional feeding reliability using “Separation Roller” technology to minimize jams and multi-feeds.



Built-in GI microprocessor

A dual-core CPU-mounted “GI” processor performs the intelligent image enhancement responsible for great looking images with dramatically faster results and more sophisticated connectivity:

- Image processing: Automatic corrections and image output
- Supports Wi-Fi: WPS (Wi-Fi Protected Setup) wireless LAN (IEEE802.11b/g/n)
- Supports USB 3.0



ScanSnap iX500

Quick Menu saves time!



Quick Menu for Windows® shown

The ScanSnap Quick Menu for PC and Mac automatically pops up after scanning to provide you a variety of ways to be immediately productive with your scans. It can be easily customized to display just your favorites, present a recommendation, and even display custom profiles.

Accelerated Searchable PDF creation

Making PDF files searchable at the point of scanning is a great way to keep them instantly accessible and now you can create a searchable PDF at nearly the same speed as a standard PDF.



Scan to Cloud

For the ultimate in accessibility to your scans across multiple platforms, computers and devices, iX500 provides operators a convenient way to scan directly to your existing Evernote, Dropbox, Google Docs, SugarSync and Salesforce accounts.



Scan there! ScanSnap Folder

Scan to virtually any application or web service that can open, insert or attach a PDF or JPEG file from your Windows® computer.



Organize business cards



CardMinder for Windows® shown

Scan, store, and edit business card information with the bundled CardMinder software for Mac and PC and even export data into other applications like Address Book, Excel, and Salesforce.

ScanSnap iX500 Deluxe model



For Windows® users, Rack2-File Smart is a feature-rich scanning and content viewing application incorporating an ultra-intuitive bookcase and binder interface that gives users a familiar and enjoyable interaction with their scanned paperwork. Magic Desktop is designed to organize scans from ScanSnap as well as memos and images from mobile devices and upload your information to Facebook.

■ General Specifications

Description		ScanSnap iX500 / PA03656-B005
Scanner type		ADF (Automatic Document Feeder), Duplex scanning
Scanning modes		Color, grayscale, monochrome, automatic (color / grayscale / monochrome *3 detection)
Image sensor		Color CIS x 2 (front x 1, back x 1)
Light source		3 Color LED (Red / Green / Blue)
Scanning speed (A4 portrait) *1	Auto mode *2	Simplex / Duplex: 25 ppm
	Normal mode	Color / Grayscale: 150 dpi, Monochrome: 300 dpi, Simplex / Duplex: 25 ppm
	Better mode	Color / Grayscale: 200 dpi, Monochrome: 400 dpi, Simplex / Duplex: 25 ppm
	Best mode	Color / Grayscale: 300 dpi, Monochrome: 600 dpi, Simplex / Duplex: 25 ppm
	Excellent mode *3	Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi, Simplex / Duplex: 7 ppm
Document size	Normal mode without Carrier Sheet	A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes (Max: 216 x 360 mm (8.5 x 14.17 in.), Min: 50.8 x 50.8 mm (2 x 2 in.) *3 / Automatically recognizes document size
	Normal mode with Carrier Sheet *3	Use of a Carrier Sheet permits the scanning of A3, B4, 11 x 17 in. and photographs as well as the document sizes that are listed above
	Long paper scanning *3 *4	863 mm (34 in.)
Paper weight (Thickness)		● A4 to 209 g/m ² (11 to 56 lb) ● A8 size: 127 to 209 g/m ² or 34 to 56 lb ● Cards (ISO/7810 ID-1 type conforming) can be used. (thickness 0.76 mm or less) Embossed card : useable (Landscape only)
Paper chute capacity *5		Maximum 50 sheets (A4, 80 g/m ² or 21 lb)
USB Interface		USB3.0 (USB2.0 / USB1.1 Supported) *6
Wi-Fi Interface *7	Observed standards	IEEE802.11b / IEEE802.11g / IEEE802.11n
	Communication mode	Infrastructure mode
	Frequency *8	2.412 GHz to 2.462 GHz / 2.412 GHz to 2.472 GHz Indoors, 50 m (Recommended: indoors, within 25 m) * May vary depending on the surrounding environment and the access point to be connected
	Security *9	WPA-PSK (TKIP / AES), WPA2-PSK (TKIP / AES), WEP (64-bit / 128-bit)
Easy installation		WPS2.0 supported (button / PIN code)
Power requirement		AC 100 to 240 V, 50 / 60 Hz
Power consumption	USB connected	Operating Mode: 20W or less Sleep Mode: 1.6W or less Auto Standby (Off) Mode: less than 0.4 watt
	Wi-Fi connected	Operating Mode: 20W or less Sleep Mode: 2.5W or less Auto Standby (Off) Mode: less than 0.4 watt
Operation environment		Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80 % (Non-condensing)
Dimensions (W x D x H) *10		292 x 159 x 168 mm (11.5 x 6.2 x 6.6 in.)
Device weight		3.0 kg (6.62 lb)
Environmental compliance		ENERGY STAR® / RoHS / EPEAT Silver Compliant
Multifeed detection		Supported (Standard) ultrasonic multifeed detection sensor
Driver		Specific driver ● Windows®: Does not support TWAIN / ISIS™ ● Mac OS: Does not support TWAIN

*1 Scanning speeds may vary due to the system environment used. *2 Documents measuring approximately 148 mm in length or less are scanned in "Best mode", while other documents are scanned in "Better mode". *3 Only computer connection *4 ScanSnap iX500 is capable of scanning documents that exceed A4 size in length. It supports the scanning of longer documents in all modes, except for "Excellent mode". *5 Maximum capacity varies, depending upon paper weight. *6 Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. *7 Mobile devices that can be connected include iPad / iPhone / iPod touch and Android™ devices. Refer to ScanSnap website for details. *8 Values depends on country. *9 IEEE802.1X Authentication is not supported. *10 Excluding the stacker and other external attachments.

■ Rack2-Fileer Smart V1.0 / Magic Desktop V1.0 *1 *2 *3 System Requirements

Compatible operating systems		Windows® 8 (32-bit / 64-bit) *4	Windows® 7 (32-bit / 64-bit) SP1 or later	Windows Vista® (32-bit / 64-bit) SP2 or later	Windows® XP (32-bit) SP3 or later
Hardware requirements	CPU	Intel® Pentium® 4 1.8 GHz or higher (Recommended: Intel® Core™ 2 Duo 2.2 GHz or higher)			
	Memory capacity	2 GB or more (Recommended: 4 GB or more)			
	Display	1,024 x 768 pixels or higher			
	Disk capacity	System drive *5	64-bit: 2 GB or more	32-bit: 850 MB or more	-
Supported scanners		ScanSnap iX500, S1500, S1300i, S1300, S1100			
Supported mobile devices	iOS	Model	iPad series, iPhone series (4 or later), iPod touch series (4th generation or later)		
		OS	iOS 4.3 or later		
	Android	Application	Rack2-Fileer Smart for iOS 1.1.0 or later		
		Model	Wi-Fi equipped device with Android OS 2.2 or later		
Application		Rack2-Fileer Smart for Android 1.1.1 or later			

*1 This product only supports Microsoft® Windows®. *2 Please refer to the Rack2-Fileer Smart Web site and the Magic Desktop Web site. *3 When installing Magic Desktop, Internet connection is required. *4 Rack2-Fileer Smart and Magic Desktop runs as a desktop application. *5 This is the free capacity required when .NET Framework 4 or later is not installed.

■ Options

Description	Part number	Remarks
ScanSnap Carrier Sheets *1	PA03360-0013	5 Carrier Sheets Intended for ScanSnap iX500, S1500, S1500M, S510, S510M, S500, S500M and ScanSnap fi-S110E/OX series scanners
ScanSnap Bag	PA03951-0651	Intended for ScanSnap iX500, S1500, S1500M, S510, S510M, S500, S500M and ScanSnap fi-S110E/OX series scanners and included items

*1 Although ScanSnap Carrier Sheets have a listed lifespan of 500 scans, the lifespan may vary with usage. ScanSnap Carrier sheets are intended to scan paper documents with weights of 127 g/m² or less. They also support the scanning of folded documents that are as large as 216 x 297 mm.

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

©2013 Fujitsu Computer Products of America, Inc. All rights reserved. Fujitsu and the Fujitsu logo are registered trademarks of Fujitsu Limited. ABBYY™ FineReader™ Engine ©2011 ABBYY. OCR by ABBYY. ABBYY and FineReader are trademarks of ABBYY. Adobe, Acrobat are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States and/or other countries. Evernote is a registered trademark or trademark of Evernote Corporation. Google, Google Docs, Android and Google Play are registered trademarks or trademarks of Google Inc. Intel, Pentium, and Intel Core are registered trademarks or trademarks of Intel Corporation in the United States and other countries. ISIS® is a registered trademark of EMC Corporation in the United States, Mac, OS X, iPad, iPhone and App Store are trademarks of Apple Inc. Microsoft, Windows, Windows Vista, Excel, PowerPoint, SharePoint and Internet Explorer are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. Word is the product of Microsoft Corporation in the United States. Salesforce and Salesforce CRM are registered trademarks or trademarks of Salesforce.com, inc. in the United States and other countries. ScanSnap, ScanSnap Logo, ScanSnap Manager, ScanSnap Organizer, CardMinder and Rack2-Fileer are registered trademarks or trademarks of PFI LIMITED in Japan. Wi-Fi and Wi-Fi Protected Setup are trademarks of Wi-Fi Alliance. Other company names and product names are the registered trademarks or trademarks of the respective companies. Specifications are subject to change without notice. All statements herein are valid in the US for US residents only, are based on normal operating conditions, are for informational purposes only, and are not intended to create any implied warranty of merchantability or fitness for a particular purpose. DS39701130

Fujitsu Computer Products of America, Inc.

1250 East Arques Avenue Sunnyvale, CA 94085-4701 (800) 626-4686 (408) 746-6000

• info@fcpa.fujitsu.com • http://us.fujitsu.com/fcpa

■ ScanSnap iX500 System Requirements

Compatible operating systems	Windows® 8 (32-bit / 64-bit)	Windows® 7 (32-bit / 64-bit) SP1 or later	Windows Vista® (32-bit / 64-bit) SP2 or later	Windows® XP (32-bit) SP3 or later
ScanSnap Manager V6.0 *3	Supported	Supported	Supported	Supported
ScanSnap Organizer V5.0	Supported	Supported	Supported	Supported
CardMinder™ V5.0	Supported	Supported	Supported	Supported
ABBY FineReader for ScanSnap™ 5.0	Supported	Supported	Supported	Supported
Scan to Microsoft® SharePoint® 3.4	Supported	Supported	Supported	Supported
Adobe® Acrobat® Standard	Please refer to the Web site of Adobe Systems Incorporated for latest support information.			
Evernote for Win 4.5	Supported	Supported	Supported	Supported
Hardware requirements *4	CPU *5	Intel® Core™ 2 Duo 2.2 GHz or higher (Recommended: Intel® Core™ i5 2.5 GHz or higher)		
	Memory capacity *5	64-bit: 2 GB or more (Recommended: 4 GB or more) 32-bit: 1 GB or more (Recommended: 4 GB or more)		
	Display	1,024 x 768 pixels or higher	800 x 600 pixels or higher	
	Disk capacity *6	4.5 GB free hard disc space for installation		
	DVD-ROM drive	Required for installation *7		
	USB port *5 *8	USB3.0 *9 / USB2.0 / USB1.1		

*1 This product supports Microsoft® Windows®. *2 Please refer to the ScanSnap Web site for latest support information. *3 It is necessary to update ScanSnap Manager to V6.1 in order to use the Wi-Fi connectivity between iX500 and a computer. *4 The ScanSnap device may not work if the connected computer does not meet these requirements. *5 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *6 .NET Framework 3.5 SP1 will be installed (requires 500 MB of disk space) together with either ScanSnap Manager, ScanSnap Organizer or CardMinder for systems that do not have .NET Framework 3.5 SP1 installed. *7 If you have no DVD-ROM drive, please visit the following web page: http://scansnap.fujitsu.com/g-support/en/. *8 ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. *9 Some computers do not recognize the ScanSnap when it is connected to a USB3.0 port. In this case, please use a USB2.0 port. *10 System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

■ Mac OS

Compatible operating systems	OS X v10.8 (Recommended: 10.8.1 or later)	Mac OS X v10.7 (Recommended: 10.7.4 or later)	Mac OS X v10.6 (Recommended: 10.6.8)
ScanSnap Manager V6.0 *3	Supported	Supported	Supported
CardMinder™ V5.0	Supported	Supported	Supported
ABBY FineReader for ScanSnap™ 5.0	Supported	Supported	Supported
ABBY FineReader Express Edition for Mac 8.3	Supported	Supported	Supported
Evernote for Mac 3.3	Supported	Supported	Supported
Hardware *4	CPU *5	Intel® Core™ 2 Duo 2.4 GHz or higher (Recommended: Intel® Core™ i5 2.5 GHz or higher)	
	Memory capacity *5	2 GB or more (Recommended: 4 GB or more)	
	Display	1,024 x 768 pixels or higher	
	Disk capacity	2.8 GB free hard disc space for installation	
	DVD-ROM drive	Required for installation *6	
USB port *5 *7	USB3.0 *8 / USB2.0 / USB1.1		

*1 This product supports Mac operating systems. *2 Please refer to the ScanSnap Web site for latest support information. *3 It is necessary to update ScanSnap Manager to V6.1 in order to use the Wi-Fi connectivity between iX500 and a computer. *4 The ScanSnap device may not work if the connected computer does not meet these requirements. *5 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *6 If you have no DVD-ROM drive, please visit the following web page: http://scansnap.fujitsu.com/g-support/en/. *7 ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. *8 Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. *9 System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

■ Software

Driver *1 *2 *3	Windows®	Mac OS
ScanSnap Manager V6.0	ScanSnap Manager V6.0	ScanSnap Manager V6.0
ScanSnap Organizer V5.0	-	-
CardMinder™ V5.0	-	CardMinder™ V5.0
ABBY FineReader for ScanSnap™ 5.0	ABBY FineReader for ScanSnap™ 5.0	ABBY FineReader Express Edition for Mac 8.3
Scan to Microsoft® SharePoint® 3.4	-	-
Adobe® Acrobat® Standard	-	-
Evernote for Win 4.5	Evernote for Win 4.5	Evernote for Mac 3.3

*1 TWAIN or ISIS™ applications cannot be used directly. *2 "One Touch" image file (JPEG, PDF and searchable PDF) generation. These functions are operable with ScanSnap Manager (ScanSnap specific driver). *3 It is necessary to update ScanSnap Manager to V6.1 in order to use the Wi-Fi connectivity between iX500 and a computer.

■ Included items

- ScanSnap ● AC cable ● AC adapter ● USB cable (USB 3.0 supported) ● Safety Precautions
- Setup DVD-ROM ● Adobe® Acrobat® DVD-ROM ● ScanSnap Carrier Sheet
- Rack2-Fileer Smart with Magic Desktop (Bundled with ScanSnap iX500 Deluxe)

We recommend the use of our genuine products for the consumables. Failures, troubles, and damage of this product resulting from the use of consumables other than our genuine products are subject to repair fees even within the warranty period.

■ Consumables

Description	Part number	Remarks
Roller Set	PA03656-0001	Lifetime: Every 200,000 sheets or one year. (For ScanSnap iX500 only)
F1 Cleaner	PA03950-0352	100 ml bottle For use on the Brake roller and Pick roller
Cleaning Wipe	PA03950-0419	1 pack (24 sheets) For use on the Brake roller and Pick roller

* These recommended lifetimes are for 80 g/m² (21 lb) A4 sized documents. Therefore, appropriate replacement lifetimes may vary for other document types.

POWERED BY ABBYY

FineReader OCR

ABBY™ FineReader™ Engine ©2011 ABBYY. OCR by ABBYY
ABBY and FineReader are trademarks of ABBYY.

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. This product is a green product and Fujitsu promotes recycling for the scanner. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

