

## Support for the J9054B and J9054C 100-FX SFP-LC Transceiver

---

Product	Minimum Software Required	Support Notes
Switch 1400 Series J9077A J9078A	N/A	100-FX is not supported in these products.
1410G Series Switches J9559A J9560A J9561A	For J9559A, J9560A: Not supported. For J9561A: Any software version.	For use in the SFP ports of the <b>J9561A</b> 1410-24G Switch. (The <b>J9559A</b> 1410-8G Switch and <b>J9560A</b> 1410-16G Switch do not have SFP ports.)
Switch 1700 Series J9079A J9080A	N/A	100-FX is not supported in these products.
Switch 1800 Series J9028A/B J9029A	N/A	100-FX is not supported in these products.
1810G Series Switches J9449A J9450A J9660A	For J9449A: Not supported. For J9450A, J9660A: Any software version.	For use in the SFP ports of the <b>J9450A</b> 1810G-24 Switch and <b>J9660A</b> V1810-48G Switch. (The <b>J9449A</b> 1810G-8 Switch does not have SFP ports.)
1810G v2 Switches J9801A J9803A	Any software version	For use in the SFP ports of the <b>J9801A</b> 1810-24 v2 and <b>J9803A</b> 1810-24G v2 Switches.
PS1810 Switch J9834A	Any software version	For use in the SFP ports of the the <b>J9834A</b> PS1810-24G Switch.
Switch 2510-24 J9019A/B	Q.10.04	
Switch 2510-48 J9020A	Any software version	
Switch 2510G Series J9279A J9280A	Any software version	
2520 Series Switches J9137A J9138A	Any software version	
2520G Series Switches J9298A J9299A	J9054B: Any software version J9054C: J.14.32	

Product	Minimum Software Required	Support Notes
2530 Series Switches J9772A J9773A J9774A J9775A J9776A J9777A J9778A J9779A J9780A J9781A J9782A J9783A J9853A J9854A J9855A J9856A	For J9853A, J9854A, J9855A, and J9856A: Not supported. For all other switches: Any software version.	For use in the SFP ports of the 2530 Series Switches. (The <b>J9853A</b> 2530-48G-PoE+-2SFP+ Switch, <b>J9854A</b> 2530-24G-PoE+-2SFP+ Switch, <b>J9855A</b> 2530-48G-2SFP+ Switch, and <b>J9856A</b> 2530-24G-2SFP+ Switch do not have SFP ports.)
Switch 2600 Series J4899A/B/C J4900A/B/C J8164A J8165A J8762A	N/A	100-FX is not supported in these products.
Switch 2610 Series J9085A J9086A J9087A J9088A J9089A	Any software version	
2615-8-PoE Switch J9565A	J9054B: Any software version J9054C: A.14.07	
2620 Series Switches J9623A J9624A J9625A J9626A J9627A	Any software version	
Switch 2800 Series J4903A J4904A	J9054B/C 1990-3613 and J9054C 1990-4112: i.10.30; J9054C 1990-4483: Not supported.	J9054C part number <b>1990-4483</b> is not supported in these products.
Switch 2810 Series J9021A J9022A	N.10.07	
Switch 2900 Series J9049A J9050A	T.12.01	
2910a1 Series Switches J9145A J9146A J9147A J9148A	Any software version	
2915-8G-PoE Switch J9562A	J9054B: Any software version J9054C: A.14.07	

Product	Minimum Software Required	Support Notes
2920 Series Switches J9726A J9727A J9728A J9729A J9836A	Any software version	For use in the SFP ports of the 2920 Series Switches.  100-FX is not supported in the SFP+ ports of the <b>J9731A</b> 2-Port 10GbE SFP+ Module.
Switch 3400cl Series J4905A J4906A	N/A	100-FX is not supported in these products.
3500 Series Switches J9470A J9471A J9472A J9473A	J9054B/C 1990-3613: K.14.31; J9054C 1990-4112 and 1990-4483: K.15.08.0007	
Switch 3500yl Series J8692A J8693A J9310A J9311A	For J8692A, J8693A: K.12.01 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).  For J9310A, J9311A K.14.50 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).	
3800 Series Switches J9573A J9574A J9575A J9576A J9584A	For J9573A, J9574A, J9575A, J9576A: Not supported.  For J9584A: Any software version.	For use in the SFP ports of the <b>J9584A</b> 3800-24SFP-2SFP+ Switch.  (The <b>J9573A</b> 3800-24G-PoE+-2SFP+ Switch, <b>J9574A</b> 3800-48G-PoE+-4SFP+ Switch, <b>J9575A</b> 3800-24G-2SFP+ Switch, and <b>J9576A</b> 3800-48G-4SFP+ Switch do not have SFP ports.)
Switch 4100gl Series J4865A J4887A	N/A	100-FX is not supported in these products.
Switch 4200vl Series J8770A J8771A J8772A/B J8773A	L.10.24	Supported: <b>J9033A</b> Switch vl 20-Port Gig-T + 4-Port SFP Module.  Not supported: <b>J8776A</b> Switch vl 4-Port Mini-GBIC Module.
Switch 5300xl Series J4819A J4850A	N/A	100-FX is not supported in these products.
Switch 5400zl Series J8697A J8698A J9642A J9643A	For J8705A and J8706A modules: K.12.01 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).  For the J9308A module: K.14.34 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).  For J9537A, J9549A, J9535A, and J9637A modules: K.15.02.0004 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).	For use in the <b>J8705A</b> Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module, the <b>J8706A</b> Switch zl 24-Port Mini-GBIC Module, the <b>J9308A</b> 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module, the <b>J9537A</b> 24-Port SFP v2 zl Module, the <b>J9549A</b> 20-Port Gig-T / 4-Port SFP v2 zl Module, the <b>J9535A</b> 20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module, and the <b>J9637A</b> 12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module.

Product	Minimum Software Required	Support Notes
Switch 5400R Series J9821A J9822A J9823A J9824A J9825A J9826A J9868A	Any software version	For use in the <b>J9537A</b> 24-Port SFP v2 zl Module, the <b>J9549A</b> 20-Port Gig-T / 4-Port SFP v2 zl Module, the <b>J9535A</b> 20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module, and the <b>J9637A</b> 12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module.
Switch 6108 J4902A	N/A	100-FX is not supported in this product.
6120 Series Blade Switches 498358-B21 516733-B21	N/A	100-FX is not supported in these products.
Switch 6200yl-24G-mGBIC J8992A	K.12.01 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).	For use in all 24 ports of the <b>J8992A</b> Switch 6200yl-24G-mGBIC.
6600 Series Switches J9263A J9264A J9265A J9451A J9452A	For J9263A, J9264A: K.14.03 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483). For J9451A: K.14.24 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).	For use in the SFP ports of the <b>J9263A</b> 6600-24G Switch, the <b>J9264A</b> 6600-24G-4XG Switch, and the <b>J9451A</b> 6600-48G Switch.  (The <b>J9265A</b> 6600-24XG Switch and <b>J9452A</b> 6600-48G-4XG Switch do not have SFP ports.)
Switch 8100fl Series J8727A J8728A	N/A	100-FX is not supported in these products.
Switch 8200zl Series J8715A/B J9475A J9640A J9641A	For J8705A and J8706A modules: Any software version (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483). For the J9308A module: K.14.34 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483). For J9537A, J9549A, J9535A, and J9637A modules: K.15.02.0004 (for J9054B/C 1990-3613); K.15.08.0007 (for J9054C 1990-4112 and 1990-4483).	For use in the <b>J8705A</b> Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module, the <b>J8706A</b> Switch zl 24-Port Mini-GBIC Module, the <b>J9308A</b> 20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module, the <b>J9537A</b> 24-Port SFP v2 zl Module, the <b>J9549A</b> 20-Port Gig-T / 4-Port SFP v2 zl Module, the <b>J9535A</b> 20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module, and the <b>J9637A</b> 12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module.
Switch 9300m Series J4138A J4139A J4874A	N/A	100-FX is not supported in these products.
Switch 9408sl J8680A	N/A	100-FX is not supported in this product.

---

## Download Switch Software from the Web

HP Networking provides software updates for your switch on the HP Networking Web site. Go to [www.hp.com/networking/support](http://www.hp.com/networking/support), search for your product, display that product, and click on **Software downloads** to go to the “Download software” page.

To determine whether you have the latest software, you can compare the software version that is available on the Web site with the version that is currently installed on your switch.

© Copyright 2014 Hewlett-Packard Company, L.P.  
The information contained herein is subject to  
change without notice.

August 2014

