



Linksys WAP300N

- **Antenna connector**—For connecting the included antennas.
- **Wireless activity indicator**—In Access Point mode, it lights up solid when the wireless interface is ready. In other modes, it lights up solid when the WAP300N connected to a router, access point, or another WAP300N. Flashes while actively sending or receiving data over a wireless connection.
- **Wi-Fi Protected Setup™ button**—Press this button to easily set up a wireless connection.
- **Wi-Fi Protected Setup indicator**—Stays on steadily following a successful Wi-Fi Protected Setup connection or when wireless security is enabled. Flashes slowly during Wi-Fi Protected Setup. Flashes quickly when there is a Wi-Fi Protected Setup error.
- **Ethernet port**—Connect a wired network device to this port.
- **Ethernet activity indicator**—Lights up when there is a wired connection. Flashes while actively sending or receiving data over the Ethernet port.
- **Power port**—Connect the included AC power adapter to this port.

Specifications

Linksys WAP300N

Model	WAP300N
Description	Linksys Wireless-N Access Point
Ethernet Port Speed	10/100 Mbps (Fast Ethernet)
Radio Frequency	2.4 or 5 GHz
Number of Antennas	2
Antenna Type	External dipole antenna with R-SMA connector
Detachable	Yes
Ports	Power, Ethernet
Buttons	Reset, Wi-Fi Protected Setup™, Power (European model only)
LEDs	Power, Wi-Fi Protected Setup, Ethernet, Wireless
Wireless Security Features	WEP, Wi-Fi Protected Access™ (WPA), Wi-Fi Protected Access™ 2 (WPA2), Wireless MAC Filtering
Security Key Bits	Up to 128-bit encryption

Environmental

Dimensions	188.7 × 151.7 × 31.2 mm (7.43" × 5.97" × 1.23") without external antennas
Unit Weight	207.0 g (7.3 oz), without external antennas 229.6 g (8.1 oz), with external antennas
Power	12V, 0.5A
Operating Temperature	0 to 40°C (32 to 104°F)
Storage Temperature	-20 to 60°C (-4 to 140°F)
Operating Humidity	10 to 80% non-condensing
Storage Humidity	5 to 90% non-condensing

Made in China

