



SMART3000RM2U Estimated Runtime

UPS	Battery Configuration	Load in Watts													
		100	200	300	400	500	600	800	1,000	1,200	1,400	1,600	1,800	2,000	2,250
SMART3000RM2U	Internal batteries	152	76	49	35	27	22	15	12	9.1	7.2	5.9	4.9	4.2	3.5

Maximum load 2250 watts without external battery packs. All runtime values are shown in minutes.

UPS	Battery Pack	BP Qty.	Load in Watts													
			100	200	300	400	500	600	700	800	900	1,000	1,200	1,400	1,500	1,600
SMART3000RM2U	BP48V24-2U	1	521	275	181	132	102	83	69	59	51	45	35	28	26	23
SMART3000RM2U	BP48V27-2US	1	707	379	252	185	145	118	98	84	73	64	51	41	37	34
SMART3000RM2U	BP48V27-2US	2	1,253	692	469	350	277	227	191	165	144	127	102	83	75	69
SMART3000RM2U	BP48V27-2US	3	1,779	1,000	686	517	411	340	288	249	218	194	156	127	116	107
SMART3000RM2U	BP48V27-2US	4	2,283	1,302	900	683	546	453	385	334	294	262	212	174	159	146
SMART3000RM2U	BP48V27-2US	5	2,769	1,597	1,112	847	681	566	483	420	371	331	268	221	203	187
SMART3000RM2U	BP48V27-2US	6	3,235	1,886	1,321	1,010	814	679	581	506	447	400	325	269	247	228
SMART3000RM2U	BP48V27-2US	7	3,684	2,169	1,526	1,171	947	792	678	592	524	469	383	317	291	269
SMART3000RM2U	BP48V27-2US	8	4,117	2,445	1,729	1,331	1,078	903	775	678	601	539	440	365	336	311
SMART3000RM2U	BP48V27-2US	9	4,533	2,716	1,928	1,488	1,208	1,014	872	763	677	608	497	414	381	353
SMART3000RM2U	BP48V27-2US	10	4,935	2,980	2,124	1,644	1,337	1,124	967	848	753	677	555	462	426	395
SMART3000RM2U	BP48V60RT-3U	1	1,037	567	382	284	223	183	154	132	115	101	81	65	60	55
SMART3000RM2U	BP48V60RT-3U	2	1,881	1,061	729	550	438	362	307	266	233	207	167	136	125	115
SMART3000RM2U	BP48V60RT-3U	3	2,673	1,539	1,070	814	654	544	464	403	355	317	257	211	194	179
SMART3000RM2U	BP48V60RT-3U	4	3,417	2,000	1,403	1,075	867	724	620	541	478	428	348	288	265	244
SMART3000RM2U	BP48V60RT-3U	5	4,117	2,445	1,729	1,331	1,078	903	775	678	601	539	440	365	336	311
SMART3000RM2U	BP48V60RT-3U	6	4,776	2,875	2,046	1,582	1,286	1,080	929	814	723	649	532	443	408	378
SMART3000RM2U	BP48V60RT-3U	7	5,399	3,290	2,356	1,828	1,490	1,255	1,081	949	844	759	623	520	480	445
SMART3000RM2U	BP48V60RT-3U	8	5,987	3,691	2,658	2,070	1,692	1,427	1,232	1,083	964	868	715	598	552	512
SMART3000RM2U	BP48V60RT-3U	9	6,544	4,078	2,952	2,308	1,890	1,598	1,381	1,215	1,083	977	806	675	624	579
SMART3000RM2U	BP48V60RT-3U	10	7,072	4,453	3,240	2,540	2,085	1,766	1,529	1,347	1,202	1,084	896	752	695	646

Maximum load 1600 watts with external battery packs. All runtime values are shown in minutes.