



OWNER'S MANUAL

Smart TV Upgrader

Please read this manual carefully before operating your set and retain it for future reference.

ST600

P/NO : SAC35193504

www.lg.com

Safety Information



CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK DO NOT REMOVE COVER (OR BACK) NO USER-SERVICEABLE PARTS INSIDE REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.



This lightning flash with arrowhead symbol within an equilateral triangle is intended to alert the user to the presence of uninsulated dangerous voltage within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the product.

WARNING: TO PREVENT FIRE OR ELECTRIC SHOCK HAZARD, DO NOT EXPOSE THIS PRODUCT TO RAIN OR MOISTURE.

WARNING: Do not install this equipment in a confined space such as a book case or similar unit.

CAUTION: Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.

Slots and openings in the cabinet are provided for ventilation and to ensure reliable operation of the product and to protect it from over heating. The openings shall be never be blocked by placing the product on a bed, sofa, rug or other similar surface. This product shall not be placed in a built-in installation such as a bookcase or rack unless proper ventilation is provided or the manufacturer's instruction has been adhered to.

CAUTION concerning the Power Cord

Most appliances recommend they be placed upon a dedicated circuit;

That is, a single outlet circuit which powers only that appliance and has no additional outlets or branch circuits. Check the specification page of this owner's manual to be certain. Do not overload wall outlets. Overloaded wall outlets, loose or damaged wall outlets, extension cords, frayed power cords, or damaged or cracked wire insulation are dangerous. Any of these conditions could result in electric shock or fire. Periodically examine the cord of your appliance, and if its appearance indicates damage or deterioration, unplug it, discontinue use of the appliance, and have the cord replaced with an exact replacement part by an authorized service center. Protect the power cord from physical or mechanical abuse, such as being twisted, kinked, pinched, closed in a door, or walked upon. Pay particular attention to plugs, wall outlets, and the point where the cord exits the appliance. To disconnect power from the mains, pull out the mains cord plug. When installing the product, ensure that the plug is easily accessible.

This device is equipped with a portable battery or accumulator.

Safety way to remove the battery or the battery from the equipment:

Remove the old battery or battery pack, follow the steps in reverse order than the assembly. To prevent contamination of the environment and bring on possible threat to human and animal health, the old battery or the battery put it in the appropriate container at designated collection points. Do not dispose of batteries or battery together with other waste. It is recommended that you use local, free reimbursement systems batteries and accumulators. The battery shall not be exposed to excessive heat such as sunshine, fire or the like.

CAUTION: The apparatus shall not be exposed to water (dripping or splashing) and no objects filled with liquids, such as vases, shall be placed on the apparatus.

FCC Compliance Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

CAUTION: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

FCC RF Radiation Exposure Statement : This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20 cm between the radiator and your body. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

FCC Radio Frequency Interference

Requirements : This device is restricted to indoor use due to its operation in the 5.15 to 5.25 GHz frequency range. FCC requires this product to be used indoors for the frequency range 5.15 to 5.25 GHz to reduce the potential for harmful interference to co-channel Mobile Satellite systems.

CAUTION: Regulations of the FCC and FAA prohibit airborne operation of radio-frequency wireless devices because their signals could interfere with critical aircraft instruments.

Responsible Party :

LG Electronics USA, Inc. 1000 Sylvan Avenue
Englewood Cliffs, NJ 07632

TEL. : +1-800-243-0000

Notes on Copyrights

- Recording equipment should be used only for lawful copying and you are advised to check carefully what is lawful copying in the area in which you are making a copy. Copying of copyright material such as films or music is unlawful unless permitted by a legal exception or consented to by the rights owner.
- CONSUMERS SHOULD NOTE THAT NOT ALL HIGH DEFINITION TELEVISION SETS ARE FULLY COMPATIBLE WITH THIS PRODUCT AND MAY CAUSE ARTIFACTS TO BE DISPLAYED IN THE PICTURE. IN CASE OF 480 PROGRESSIVE SCAN PICTURE PROBLEMS, IT IS RECOMMENDED THAT THE USER SWITCH THE CONNECTION TO THE 'STANDARD DEFINITION' OUTPUT. IF THERE ARE QUESTIONS REGARDING OUR TV SET COMPATIBILITY WITH THIS MODEL 480p UNIT PLEASE CONTACT OUR CUSTOMER SERVICE CENTRE.

IMPORTANT SAFETY INSTRUCTIONS

1. Read these instructions.
2. Keep these instructions.
3. Heed all warnings.
4. Follow all instructions.
5. Do not use this apparatus near water.
6. Clean only with dry cloth.
7. Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
8. Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
10. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
11. Only use attachments/accessories specified by the manufacturer.
12. Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.
13. Unplug this apparatus during lightning storms or when unused for long periods of time.
14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.



Table of Contents

1 Getting Started

- 3 Safety Information
- 8 Introduction
 - 8 – About the “O” Symbol Display
 - 8 – File requirement
 - 10 – About DLNA
 - 10 – Certain System Requirements
 - 10 – LG Remote
 - 10 – WOL (Wake On LAN)
 - 10 – Compatibility Notes
- 11 Main Unit
- 11 Remote control

2 Connecting

- 12 Connecting the AC Adapter
- 12 – HDMI Connecting to Your TV
- 12 – If you have a HDMI TV or monitor, you can connect it to this unit using a HDMI cable (Type A, High Speed HDMI™ Cable). Connect the HDMI jack on the unit to the HDMI jack on a HDMI compatible TV or monitor.
- 13 – Resolution Setting
- 14 Connecting to an Amplifier
- 14 – Connecting to an Amplifier via HDMI Output
- 15 – Connecting to an Amplifier via Digital Audio Output
- 16 Connecting to your Home Network
- 16 – Wired network connection
- 17 – Wired Network Setup
- 18 – Wireless Network Connection
- 18 – Wireless Network Setup
- 21 USB device connection
- 21 – Playback content in the USB device

3 System Setting

- 22 Settings
 - 22 – Adjust the Setup Settings
 - 22 – [DISPLAY] Menu
 - 23 – [LANGUAGE] Menu
 - 24 – [AUDIO] Menu
 - 25 – [NETWORK] Menu
 - 25 – [OTHERS] Menu

4 Operating

- 27 General Playback
 - 27 – Using [HOME] menu
 - 27 – Playing a file media from a USB device
 - 28 – Playing a file media from a network server
 - 29 – Basic operations for video and audio content
 - 29 – Basic operations for photo content
- 30 Advanced Playback
 - 30 – Zoom in & out during slide show
 - 30 – Repeat Playback
 - 30 – Viewing content information
 - 30 – Changing content list view
 - 31 – Selecting a subtitle file
 - 31 – Setting your photo as a wallpaper
 - 31 – Options while viewing a photo
 - 32 – Listening to music while slide show
- 32 On-Screen display
 - 32 – Displaying content information on-screen
 - 33 – Playing from selected time
 - 33 – Listening to a different audio track
 - 33 – Selecting a subtitle language
 - 33 – Changing TV Aspect Ratio
 - 33 – Changing subtitle code page
 - 34 – Changing Picture Mode
- 34 Using the Premium
- 35 Using the LG Apps
 - 35 – Signing in
- 36 Using the Browser Home
 - 37 – Editing your favorite web pages
 - 37 – Additional browser options

5 Troubleshooting

- 38 Troubleshooting
- 38 – General
- 38 – Picture
- 39 – Resetting
- 39 – Network
- 39 – Customer Support
- 39 – Open source software notice

6 Appendix

- 40 Network Software Update
- 40 – Network update notification
- 40 – Software Update
- 41 About Nero MediaHome 4 Essentials
- 42 – Installing Nero MediaHome 4 Essentials
- 42 – Sharing files and folders
- 43 Trademarks and Licenses
- 44 Audio Output Specifications
- 45 Specifications
- 46 Maintenance
- 46 – Handling the Unit
- 46 Important Information Relating to Network Services

1

2

3

4

5

6

Introduction

1

About the “⊘” Symbol Display

“⊘” may appear on your TV display during operation and indicates that the function explained in this owner’s manual is not available on that specific media.

File requirement

Video files

| File Location | File Extension | Codec Format | Audio Format | Subtitle |
|---------------|---|--|---|--|
| USB | “.avi”, “.divx”, “.mpg”, “.mpeg”, “.mkv”, “.mp4”, “.asf”, “.wmv”, “.m4v” (DRM free) | DIVX3.xx, DIVX4.xx, DIVX5.xx, DIVX6.xx (standard playback only), XVID, H.264/ MPEG-4 AVC, VC-1 SM (WMV3), MPEG1, MPEG2 | Dolby Digital, DTS, MP3, WMA, AAC, Dolby Digital Plus | SubRip (.srt / .txt), SAMI (.smi), SubStation Alpha (.ssa/.txt), MicroDVD (.sub/.txt), VobSub (.sub), SubViewer 1.0 (.sub), SubViewer 2.0 (.sub/.txt), TMUnit (.txt), DVD Subtitle System (.txt) |
| DLNA, PC | “.avi”, “.divx”, “.mpg”, “.mpeg”, “.mkv”, “.mp4”, “.asf”, “.wmv”, “.m4v” (DRM free) | DIVX3.xx, DIVX4.xx, DIVX5.xx, DIVX6.xx (standard playback only), XVID, H.264/ MPEG-4 AVC, VC-1 SM (WMV3), MPEG1, MPEG2 | Dolby Digital, DTS, MP3, WMA, AAC, Dolby Digital Plus | SubRip (.srt / .txt), SAMI (.smi), SubStation Alpha (.ssa/.txt), MicroDVD (.sub/.txt), SubViewer 1.0 (.sub), SubViewer 2.0 (.sub/.txt), TMUnit (.txt), DVD Subtitle System (.txt) |

Audio files

| File Location | File Extension | Sampling Frequency | Bitrate | Note |
|---------------|-----------------------------------|--|--|--|
| USB, DLNA, PC | “.mp3”, “.wma”, “.m4a” (DRM free) | within 32 - 48 kHz (WMA), within 16 - 48 kHz (MP3) | within 20 - 320 kbps (WMA), within 32 - 320 kbps (MP3) | Some audio files are not supported on this unit. |

Photo files

| File Location | File Extension | Recommended Size | Note |
|---------------|-------------------------|--|---|
| USB, DLNA, PC | “.jpg”, “.jpeg”, “.png” | Less than 4,000 x 3,000 x 24 bit/pixel Less than 3,000 x 3,000 x 32 bit/pixel | Progressive and lossless compression photo image files are not supported. |

Note

- The file name is limited to 180 characters.
- Maximum files/Folder: Less than 2000 (total number of files and folders)
- Depending on the size and number of the files, it may take several minutes to read the contents on the media.
- File compatibility may differ depending on the server.
- Because the compatibility on DLNA server are tested on the bundle DLNA server (Nero MediaHome 4 Essentials) environment, file requirements and playback functions may differ depending on media servers.
- The file requirements on page 8 are not always compatible. There may have some restrictions by file features and media server's ability.
- Playing a video subtitle files are only available on share folder of a PC or DLNA media server created by supplied Nero MediaHome 4 Essentials software on this unit package.
- The files from removable media such as USB drive etc. on your media server may not be shared properly.
- This unit cannot support the ID3 Tag embedded MP3 file.
- The total playback time of audio file indicated on the screen may not correct for VBR files.
- HD video files contained on the USB 1.0/1.1 may not played properly. USB 2.0 are recommended to play back HD video files.
- This unit supports H.264/MPEG-4 AVC profile Main, High at Level 4.1. For a file with higher level, the warning message will appear on the screen.
- This unit does not support files that are recorded with GMC or Qpel.
- GMC – Global Motion Compensation
- Qpel – Quarter pixel

About DLNA

This Unit is a DLNA Certified digital media unit that can display and play movie, photo and music content from your DLNA-compatible digital media server (PC and Consumer Electronics).

The Digital Living Network Alliance (DLNA) is a cross-industry organization of consumer electronics, computing industry and mobile device companies. Digital Living provides consumers with easy sharing of digital media through your home network.

The DLNA certification logo makes it easy to find products that comply with the DLNA Interoperability Guidelines. This unit complies with DLNA Interoperability Guidelines v1.5.

When a PC running DLNA server software or other DLNA compatible device is connected to this unit, some setting changes of software or other devices may be required. Please refer to the operating instructions for the software or device for more information.

Certain System Requirements

For high definition video playback:

- High definition display that has HDMI input jacks.

For Dolby® Digital Plus and DTS multi-channel audio playback:

- An amplifier/receiver with a built-in (Dolby Digital, Dolby Digital Plus or DTS) decoder.
- Main, center, surround speakers and subwoofer as necessary for chosen format.

For playing files on your PC's share folder via your home network, the PC requires below.

- Windows® XP (Service Pack 2 or higher), Windows Vista® (no Service Pack required) Windows 7® (no Service Pack required)
- 1.2 GHz Intel® Pentium® III or AMD Sempron™ 2200+ processors
- Network environment: 100 Mb Ethernet, WLAN
- More than 1 folder on your PC has to be shared. Visit support link of your operating system for more information on file share settings.

LG Remote

You can control this unit with your iPhone or Android phone via your home network. This unit and your phone must be connected to your wireless network device such as access point. Visit "Apple iTunes" or "Google Apps Marketplace" for detailed information of "LG Remote".


WOL (Wake On LAN)

Users can turn on this unit using WOL embedded utility on your personal computer or smartphone via your home network. To use this feature, this unit must be connected to the WOL available access point or router with wired network connection. Refer to the relevant manual of the utility or network devices for more detailed information.


Compatibility Notes

- If you experience compatibility problems, please contact an authorized Customer Service Center.
- Dolby Digital Plus are supported with maximum 7.1 channels if you use HDMI connection for the audio output of the unit.

Main Unit




Remote control



- 1** **⏻ (POWER):** Switches the unit ON or OFF.
- 2** **☐ (MENU):** Displays or exits On-Screen Display.
- 3** **Direction buttons:** Selects an option in the menu.
- 4** **Center buttons (Touch Sensors):** Enters the selected item.
In web browser menu, You can control this button displayed cursor in all directions.
Note: If you leave the unit without touching, the touch function will be disabled for energy saving. To activate the touch function, press direction button and touch the sensors.
- 5** **HOME (🏠):** Displays or exits the Home Menu.
- 6** **BACK (↶):** Exits the menu or resumes playback.

- 7** **Colored (R, G, Y, B) buttons:**
They are also used for [Smart Share], [Premium], [LG Apps] and [Web Browser] menu.
- 8** **▶ (Play):** Starts playback.
⏸ (Pause): Pauses playback.
- 9** **◀◀/▶▶:** Searches backward or forward.
◀◀◀/▶▶▶: Press and hold for two seconds to skip previous/next chapter or file.
■ (Stop): Stops playback.


Battery Installation



Remove the battery cover on the rear of the Remote Control, and insert two R6 (size AA, alkaline) batteries with **+** and **-** matched correctly.

Connecting the AC Adapter

Connect the unit to the power supply with the supplied AC adapter.
Connect the power cord to the adapter, and then plug the other end into an AC outlet.



- Contact an electrical parts distributor for assistance in selecting a suitable AC plug adapter or AC cord set.
- This AC adapter is manufactured by Asian Power Devices Inc.




Caution

Only use the AC adapter supplied with this device. Do not use a power supply from another device or another manufacturer. Using any other power cable or power supply may cause damage to the device and void your warranty.

HDMI Connecting to Your TV

If you have a HDMI TV or monitor, you can connect it to this unit using a HDMI cable (Type A, High Speed HDMI™ Cable). Connect the HDMI jack on the unit to the HDMI jack on a HDMI compatible TV or monitor.



Set the TV's source to HDMI (refer to TV's Owner's manual).



Note

- If you select a resolution manually and then connect the HDMI jack to TV and your TV does not accept it, the resolution setting is set to [Auto].
- If you select a resolution that your TV does not accept, the warning message will appear. After resolution change, if you cannot see the screen, please wait 20 seconds and the resolution will automatically revert back to the previous resolution.
- The 1080p video output frame rate may be automatically set to either 24 Hz or 60 Hz depending both on the capability and preference of the connected TV.

Additional Information for HDMI

- When you connect a HDMI or DVI compatible device make sure of the following:
 - Try switching off the HDMI/DVI device and this unit. Next, switch on the HDMI/DVI device and leave it for around 30 seconds, then switch on this unit.
 - The connected device's video input is set correctly for this unit.
 - The connected device is compatible with 720x480p, 1280x720p, 1920x1080i or 1920x1080p video input.
- Not all HDCP-compatible HDMI or DVI devices will work with this unit.
 - The picture will not be displayed properly with non-HDCP device.

! Note

- If a connected HDMI device does not accept the audio output of the unit, the HDMI device's audio sound may be distorted or may not output.
- When you use HDMI connection, you can change the resolution for the HDMI output. (Refer to "Resolution Setting" on page 13)
- Select the type of video output from the HDMI OUT jack using [HDMI Color Setting] option on the [Setup] menu (see page 23).
- Changing the resolution when the connection has already been established may result in malfunctions. To solve the problem, turn off the unit and then turn it on again.
- When the HDMI connection with HDCP is not verified, TV screen is changed to black screen. In this case, check the HDMI connection, or disconnect the HDMI cable.
- If there are noises or lines on the screen, please check the HDMI cable (length is generally limited to 4.5 m(15 ft)).

Resolution Setting

The unit provides several output resolutions for HDMI OUT. You can change the resolution using [Setup] menu.

- Press HOME (🏠).



- Press green (G) colored button. The [Setup] menu appears.
- Use \wedge / \vee to select [DISPLAY] option then press \rightarrow to move to the second level.
- Use \wedge / \vee to select the [Resolution] option then press **Center button** to move to the third level.



- Use \wedge / \vee to select the desired resolution then press **Center button** to confirm your selection.

Connecting to an Amplifier

Make one of the following connections, depending on the capabilities of your existing equipment.

- HDMI Audio connection (page 14)
- Digital Audio connection (page 15)


Since many factors affect the type of audio output, see "Audio Output Specifications" on page 44 for details.

About Digital Multi-channel sound

A digital multi-channel connection provides the best sound quality. For this, you need a multi-channel Audio/Video Receiver that supports one or more of the audio formats supported by your unit. Check the logos on the front of the Audio/Video receiver and the manual. (PCM Stereo, Dolby Digital, Dolby Digital Plus or DTS)

Connecting to an Amplifier via HDMI Output

Connect the unit's HDMI OUT jack to the corresponding jack on your amplifier using a HDMI cable.




Connect the amplifier's HDMI output jack to HDMI input jack on your TV using a HDMI cable if your amplifier has HDMI output jack.

You will need to activate the unit's digital output. (See "[AUDIO] Menu" on page 24)

Connecting to an Amplifier via Digital Audio Output

Connect the unit's OPTICAL AUDIO OUT jack to the corresponding in jack (OPTICAL) on your amplifier using an optional digital audio cable.



You will need to activate the unit's digital output.
(See "[AUDIO] Menu" on page 24.)

Connecting to your Home Network

This unit can be connected to a local area network (LAN) via the LAN port on the rear panel or the internal wireless module.

By connecting the unit to a broadband home network, you have access to services such as software updates, Web Browser and on-line content services.

Wired network connection


Using a wired network provides the best performance, because the attached devices connect directly to the network and are not subject to radio frequency interference.

Please refer to the documentation for your network device for further instructions.

Connect the unit's LAN port to the corresponding port on your Modem or Router using a commercially available LAN or Ethernet cable.

! Note

- When plugging or unplugging the LAN cable, hold the plug portion of the cable. When unplugging, do not pull on the LAN cable but unplug while pressing down on the lock.
- Do not connect a modular phone cable to the LAN port.
- Since there are various connection configurations, please follow the specifications of your telecommunication carrier or internet service provider.
- If you want to access content from PCs or DLNA servers, this unit must be connected to the same local area network with them via a router.




Wired Network Setup

If there is a DHCP server on the local area network (LAN) via wired connection, this unit will automatically be allocated an IP address. After making the physical connection, a small number of home networks may require the unit's network setting to be adjusted. Adjust the [NETWORK] setting as follow.


Preparation

Before setting the wired network, you need to connect the broadband internet to your home network.

1. Select [Connection Setting] option in the [Setup] menu then press **Center button**.




2. The [Connection Setting] menu appear on the screen. Use \wedge/\vee to select the [Wired] and press **Center button**.



3. Use $\wedge/\vee/</>$ to select the IP mode between [Dynamic] and [Static].


Normally, select [Dynamic] to allocate an IP address automatically.



Note

If there is no DHCP server on the network and you want to set the IP address manually, select [Static] then set [IP Address], [Subnet Mask], [Gateway] and [DNS Server] using $\wedge/\vee/</>$.


4. Select [OK] and press **Center button** to apply network settings.
5. The unit will ask you to test the network connection. Select [OK] and press **Center button** to complete the network connection.
6. If you select [Test] and press **Center button** at step 5 above, the network connection status is displayed on the screen.
You can also test it on the [Connection Status] in the [Setup] menu.



Wireless Network Connection

Another connection option is to use an Access Point or a wireless router. The network configuration and connection method may vary depending on the equipment in use and the network environment.

This unit is equipped with an IEEE 802.11n (Dual-band, 5 GHz and 2.4 GHz band) wireless module, which also supports the 802.11a/b/g standards. For the best wireless performance, we recommend using a IEEE 802.11n certified Wi-Fi network (access point or wireless router).



Refer to the setup instructions supplied with your access point or wireless router for detailed connection steps and network settings.

For best performance, a direct wired connection from this unit to your home network's router or cable/DSL modem is always the best option. If you do chose to use the wireless option, note that performance can sometimes be affected by other electronic devices in the home.

Note

Available frequency range and channels for 5 GHz band are listed as below. But, there may have the differences and restrictions depending on the country. Try setting your access point with other channel if you have difficulties in wireless network connection.

| Area | Frequency Range |
|---------------|---|
| North America | 5.15-5.25 GHz (ch. 36-48), 5.725-5.825 GHz (ch. 149-161), 5.825-5.850 GHz (ch.165) |
| Europe | 5.15-5.25 GHz (ch. 36-48) |
| Others | 5.15-5.25 GHz (ch. 36-48), 5.725-5.825 GHz (ch. 149-161), 5.825- 5.850 GHz (ch.165) |

Wireless Network Setup


For the wireless network connection, the unit needs to be set up for network communication. This adjustment can be done from the [Setup] menu. Adjust the [NETWORK] setting as follow. Setting up the access point or the wireless router is required before connecting the unit to the network.

Preparation


Before setting the wireless network, you need to:

- Connect the broadband internet to the wireless home network.
- Set the access point or wireless router.
- Note the SSID and security code of the network.

1. Select [Connection Setting] option in the [Setup] menu then press **Center button**.



- The [Connection Setting] menu appear on the screen. Use **▲/▼** to select [Wireless] and press **Center button**.
- Select [Yes] and press **Center button** to continue. The new connection settings reset the current network settings.
- The unit scans the all available access points or wireless routers within range and display them as a list. Use **▲/▼** to select an access point or wireless router on the list, and then press **Center button**.



If you have security on your access point or wireless router, verify that the WEP or WPA key that was entered into the unit matches the router's information exactly. You need to input the security code as necessary.

! Note

- WEP security mode generally have 4 keys available on an access point or wireless router's setting. If your access point or wireless router use WEP security, enter the security code of the key "No.1" to connect on your home network.
- An Access Point is a device that allows you to connect to your home network wirelessly.
- If your access point or wireless router supports the PIN Code configuration method based on WPS(Wi-Fi Protected Setup), press yellow (Y) colored button and note the code number on the screen. And then, enter the PIN number on a setting menu of your access point or wireless router to connect. Refer to the documentation for your network device.

[Manual] – Your access point may not be broadcasting its access point name (SSID). Check your router settings through your computer and either set your router to broadcast SSID, or manually enter the access point name (SSID) in [Manual].

[Push Button] – If your access point or wireless router that supports the Push Button Configuration method, select this option and press the Push Button on your access point or wireless router within 120 counts. You do not need to know the access point name (SSID) and security code of your access point or wireless router.

- Use **▲/▼/◀/▶** to select the IP mode between [Dynamic] and [Static]. Normally, select [Dynamic] to allocate an IP address automatically.

! Note

If there is no DHCP server on the network and you want to set the IP address manually, select [Static] then set [IP Address], [Subnet Mask], [Gateway] and [DNS Server] using **▲/▼/◀/▶** and numerical buttons.

- Select [OK] and press **Center button** to apply network settings.
- The unit will ask you to test the network connection. Select [OK] and press **Center button** to complete the network connection.
- If you select [Test] and press **Center button** at step 7 above, the network connection status is displayed on the screen. You can also test it on the [Connection Status] in the [Setup] menu.

Notes on Network Connection:


- Many network connection problems during set up can often be fixed by re-setting the router or modem. After connecting the unit to the home network, quickly power off and/or onnect the power cable of the home network router or cable modem. Then power on and/or connect the power cable again.
- Depending on the internet service provider (ISP), the number of devices that can receive internet service may be limited by the applicable terms of service. For details, contact your ISP.
- Our company is not responsible for any malfunction of the unit and/or the internet connection feature due to communication errors/malfunctions associated with your broadband internet connection, or other connected equipment.
- Some internet contents may require a higher bandwidth connection.
- Even if the unit is properly connected and configured, some internet contents may not operate properly because of internet congestion, the quality or bandwidth of your internet service, or problems at the provider of the content.
- Some internet connection operations may not be possible due to certain restrictions set by the Internet service provider (ISP) supplying your broadband Internet connection.
- Any fees charged by an ISP including, without limitation, connection charges are your responsibility.
- A 10 Base-T or 100 Base-TX LAN port is required for wired connection to this unit. If your internet service does not allow for such a connection, you will not be able to connect the unit.
- You must use a Router to use xDSL service.
- A DSL modem is required to use DSL service and a cable modem is required to use cable modem service. Depending on the access method of and subscriber agreement with your ISP, you may not be able to use the internet connection feature contained in this unit or you may be limited to the number of devices you can connect at the same time. (If your ISP limits subscription to one device, this unit may not be allowed to connect when a PC is already connected.)
- The use of a "Router" may not be allowed or its usage may be limited depending on the policies and restrictions of your ISP. For details, contact your ISP directly.
- The wireless network operate at 2.4 GHz radio frequencies that are also used by other household devices such as cordless telephone, Bluetooth® devices, microwave oven, and can be affected by interference from them.
- Turn off all unused network equipment in your local home network. Some devices may generate network traffic.
- For the purpose of the better transmission, placing the unit from the access point as close as possible.
- In some instances, placing the access point or wireless router at least 0.45 m (1.5 ft.) above the floor may improve the reception.
- Move closer to the access point if possible or re-orient the unit so there is nothing between it and the access point.
- The reception quality over wireless depends on many factors such as type of the access point, distance between the unit and access point, and the location of the unit.
- Set your access point or wireless router to Infrastructure mode. Ad-hoc mode is not supported.

USB device connection

This unit can play video, audio and photo files contained in the USB device.

Playback content in the USB device


1. Insert a USB device to the USB port until it fits into place.



When you connect the USB device on the HOME menu, the unit plays an audio file contained in the USB storage device automatically. If the USB storage device is containing various types of files, a menu for the file type selection will appear.

File loading may takes few minutes depending on the number of content stored in the USB storage device. Press **Center button** while [Cancel] is selected to stop loading.

2. Press HOME (🏠).
3. Select [Smart Share] using </>, and press **Center button**.
4. Select [Movie], [Photo] or [Music] using ^/V, and press **Center button**.
5. Select [USB] option using ^/V, and press **Center button**.



6. Select a file using ^/V/</>, and press ► or **Center button** to play the file.
7. Withdraw the USB device carefully.

! Note


- This unit supports USB flash drive/external HDD formatted in FAT16, FAT32 and NTFS when accessing files (audio, photo, video).
- This unit can support up to 8 partitions of the USB device.
- Do not extract the USB device during operation (play, etc.).
- A USB device which requires additional program installation when you have connected it to a computer, is not supported.
- USB device: USB device that supports USB1.1 and USB2.0.
- Movie, music and photo files can be played. For details of operations on each file, refer to relevant pages.
- Regular back up is recommended to prevent data loss.
- If you use a USB extension cable, USB HUB or USB Multi-reader, the USB device may not be recognized.
- Some USB device may not work with this unit.
- Digital camera and mobile phone are not supported.
- USB Port of the unit cannot be connected to PC. The unit cannot be used as a storage device.

Settings


Adjust the Setup Settings

You can change the settings of the unit in the [Setup] menu.


1. Press HOME (🏠).



2. Press green (G) colored button. The [Setup] menu appears.



3. Use \wedge / \vee to select the first setup option, and press \rightarrow to move to the second level.



4. Use \wedge / \vee to select a second setup option, and press **Center button** or \rightarrow to move to the third level.



5. Use \wedge / \vee to select a desired setting, and press **Center button** or \rightarrow to confirm your selection.

[DISPLAY] Menu

TV Aspect Ratio

Select a TV aspect ratio option according to your TV type.

[4:3 Letter Box]

Select when a standard 4:3 TV is connected. Displays theatrical images with masking bars above and below the picture.

[4:3 Pan Scan]

Select when a standard 4:3 TV is connected. Displays pictures cropped to fill your TV screen. Both sides of the picture are cut off.

[16:9 Original]

Select when a 16:9 wide TV is connected. The 4:3 picture is displayed with an original 4:3 aspect ratio, with black bars appearing at the left and right sides.

[16:9 Full]

Select when a 16:9 wide TV is connected. The 4:3 picture is adjusted horizontally (in a linear proportion) to fill the entire screen.

! Note

You cannot select [4:3 Letter Box] and [4:3 Pan Scan] option when the resolution is set to higher than 720p.

Resolution

Sets the output resolution of the Component and HDMI video signal. Refer to page 13 for details about the resolution setting.

[Auto]

If the HDMI OUT jack is connected to TVs providing display information (EDID), automatically selects the resolution best suited to the connected TV.

[1080p]

Outputs 1080 lines of progressive video.

[1080i]

Outputs 1080 lines of interlaced video.

[720p]

Outputs 720 lines of progressive video.

[480p]

Outputs 480 lines of progressive video.

1080p Display Mode

When the resolution is set to 1080p, select [24 Hz] for smooth presentation of film material (1080p/24 Hz) with a HDMI-equipped display compatible with 1080p/24 Hz input.



Note

- When you select [24 Hz], you may experience some picture disturbance when the video switches video and film material. In this case, select [60 Hz].
- Even when [1080p Display Mode] is set to [24 Hz], if your TV is not compatible with 1080p/24 Hz, the actual frame frequency of the video output will be 60 Hz to match the video source format.

HDMI Color Setting

Select the type of output from the HDMI OUT jack. For this setting, please refer to the manuals of your display device.

[YCbCr]

Select when connecting to a HDMI display device.

[RGB]

Select when connecting to a DVI display device.

Wallpaper

Changes the background of the initial screen.

[LANGUAGE] Menu

Display Menu

Select a language for the [Setup] menu and on-screen display.

[AUDIO] Menu

Set the unit's Audio options according to the type of audio system you use.

! Note

Since many factors affect the type of audio output, see "Audio Output Specifications" on page 44 for details.

HDMI / Digital Output

[PCM Stereo]

Select if you connect this unit's HDMI OUT or DIGITAL AUDIO OUT jack to a device with two-channel digital stereo decoder.

[DTS Re-Encode]

Select if you connect this unit's HDMI OUT or DIGITAL AUDIO OUT jack to a device with DTS decoder.

[Primary Pass-Thru]

Select if you connect this unit's OPTICAL AUDIO OUT and HDMI OUT jack to a device with LPCM, Dolby Digital, Dolby Digital Plus and DTS decoder.

Sampling Freq. (Digital Audio Output)

[192 kHz]

Select this if your A/V Receiver or Amplifier is capable of handling 192 kHz signals.

[96 kHz]

Select this if your A/V Receiver or Amplifier is not capable of handling 192 kHz signals. When this choice is made, this unit automatically converts any 192 kHz signals to 96 kHz so your system can decode them.

[48 kHz]

Select this if your A/V Receiver or Amplifier is not capable of handling 192 kHz and 96 kHz signal. When this choice is made, this unit automatically converts any 192 kHz and 96 kHz signals to 48 kHz so your system can decode them.

Check the documentation for your A/V Receiver or Amplifier to verify its capabilities.

DRC (Dynamic Range Control)

This function allows you to listen to a movie at a lower volume without losing clarity of sound.

[Off]

Turns off this function.

[On]

Compress the dynamic range of the Dolby Digital or Dolby Digital Plus audio output.

[Auto]

The dynamic range of the Dolby Digital and Dolby Digital Plus are operated as same as the [On] mode.

! Note

The DRC setting can be changed only the unit is in complete stop mode.

[NETWORK] Menu

The [NETWORK] settings are needed to use the software update, Web Browser and on-line content services.

Connection Setting

If your home network environment is ready to connect the unit, the unit needs to be set the wired or wireless network connection for network communication. (See "Connecting to your Home Network" on pages 16.)

Connection Status

If you want to check the network status on this unit, select the [Connection Status] options and press **Center button** to check whether a connection to the network and the internet have been established.

Netflix

[Netflix ESN]

Display its unique Netflix ESN (Electronic Serial Number) that allows you to use the Netflix streaming.

[Deactivate Netflix]

Deactivates your unit. To activate the Netflix again, contact to the service provider.

Deactivate Vudu

You can deactivate your unit from your Vudu account. It is recommended that you do this if you give your unit to someone else who should not share your Vudu account.

Premium/LG Apps

[Country Setting]

Select your area for displaying proper services and contents on the [Premium] and [LG Apps] feature.

[Registration Code]

Display the unique code of this unit for servicing [Premium] and [LG Apps] feature.

[OTHERS] Menu

DivX® VOD

ABOUT DIVX VIDEO: DivX® is a digital video format created by DivX, Inc. This is an official DivX Certified® device that plays DivX video. Visit divx.com for more information and software tools to convert your files into DivX video.

ABOUT DIVX VIDEO-ON-DEMAND: This DivX Certified® device must be registered in order to play purchased DivX Video-on-Demand (VOD) movies. To obtain your registration code, locate the DivX VOD section in your device setup menu. Go to vod.divx.com for more information on how to complete your registration.

[Register]

Displays the registration code of your unit.

[Deregister]

Deactivate your unit and display the deactivation code.



Note

All the downloaded videos from DivX VOD with this unit's registration code can only be played back on this unit.

Auto Power Off

The screen saver appears when you leave the unit in Stop mode for about five minutes. If you set this option to [On], the unit automatically turns off within 25 minutes since the Screen Saver is displayed. Set this option to [Off] to leave the screen saver until the unit is operated by the user.

Factory Set

You can reset the unit to its original factory settings.



Note

If you reset the unit to its original factory settings using [Factory Set] option, you have to set all the activation for the on-line services and network settings again.

Software

[Information]

Displays the current software version.

[Update]

You can update the software by connecting the unit directly to the software update server (see page 40).

Disclaimer Notice

Press **Center button** to view the notice of Network Service Disclaimer.

General Playback

Using [HOME] menu

The home menu appears when you press HOME (🏠). Use $\wedge / \vee / < / >$ to select a category and press **Center button**.




- 1 [Premium] - Displays the Premium Home screen.
- 2 [LG Apps] - Displays the [LG Apps] screen.
- 3 [Web Browser] - Displays the Browser Home screen.
- 4 [Sign In] - Displays the [Premium] or [LG Apps] Login menu screen.
- 5 [Setup] - Adjusts the system settings.
- 6 [Smart Share] - Plays [Movie], [Photo] or [Music] contents.
- 7 [Search] - This function will be updated later.
- 8 [LG Apps] - Displays the [LG Apps] screen.
- 9 [Favorite Apps] - Shortcut for user's favorite Apps.
- 10 [My Apps] - Display the [My Apps] screen.


Playing a file media from a USB device

This unit can play video, audio and photo files contained in the USB device.

1. Insert a USB device into the USB port until it fits into place.
2. Press HOME (🏠).
3. Select [Smart Share] using $< / >$, and press **Center button**.



4. Select [Movie], [Photo] or [Music] using \wedge / \vee , and press **Center button**.
5. Select [USB] option using \wedge / \vee , and press **Center button**.




6. Select a file using $\wedge / \vee / < / >$, and press ► or **Center button** to play the file.

Playing a file media from a network server

This unit can play video, audio and photo files located in a PC or a DLNA server through your home network.

1. Check the network connection and settings (page 16).
2. Press HOME (🏠).
3. Select [Movie], [Photo] or [Music] using **Λ/V**, and press **Center button**.
4. Select a DLNA media server or a share folder on your PC on the list using **Λ/V**, and press **Center button**.



If you want to rescan available media server, press the green (G) colored button.

5. Select a file using **Λ/V/</>**, and press **Center button** to play the file.

! Note


- The file requirements are described on page 8.
- The thumbnail of the unplayable files can be displayed, but those cannot be played on this unit.
- The subtitle file name and video file name have to be the same and located at the same folder.
- The playback and operating quality may be affected by your home network condition.
- You may experience connection problems depending on your server's environment.

Entering a network user ID and the password

Depending on your PC's environment, you may need to enter a network user ID and the password for accessing a shared folder.

1. The keyboard menu appears automatically if the network user ID and the password are required.
2. Use **Λ/V/</>** to select a character then press **Center button** to confirm your selection on the virtual keyboard.

To enter a letter with an accent mark, press **⌂** (MENU) to display the extended character set.



[Cancel] – Clear all entered characters.

[Space] – Inserts a space at the cursor position.

[<-] – Deletes the previous character at the cursor position.

[ABC / abc / #+==&] – Change the keyboard menu settings to capital letters, small letters or symbols.

3. When you finish entering the network user ID and password, select [OK] using **Λ/V/</>** and press **Center button** to access the folder.

The network user ID and password will be remembered after accessing the folder for your convenience. If you do not want the network user ID and password to be remembered, press red (R) colored button to un-tick the [Remember] check box before accessing the folder.

Basic operations for video and audio content

To stop playback

Press ■ (STOP) while playback.

To pause playback

Press || (PAUSE) while playback.

Press ► (PLAY) to resume playback.

To play frame-by-frame (Video)

Press || (PAUSE) while movie playback.

Press || (PAUSE) repeatedly to play Frame-by-Frame playback.

To scan forward or backward

Press ◀◀ or ▶▶ to play fast forward or fast reverse during playback.

You can change the various playback speeds by pressing ◀◀ or ▶▶ repeatedly.

To slow down the playing speed

While the playback is paused, press ▶▶ repeatedly to play various speeds of slow motion.

To skip to the next/previous file

During playback, press ◀◀◀ or ▶▶▶ and hold for two seconds to go to the next file or to return to the beginning of the current track/file.

Press ◀◀ twice briefly to step back to the previous file.

In the file list menu of a server, there may have many types of contents in a folder together. In this case, press ◀◀◀ or ▶▶▶ and hold for two seconds to go to the previous or next content with same type.

Basic operations for photo content

To play a slide show

Press ► (PLAY) to start slide show.

To stop a slide show

Press ■ (STOP) while slide show.

To pause a slide show

Press || (PAUSE) while slide show.



Press ► (PLAY) to re-start the slide show.

To skip to the next/previous photo

While viewing a photo in full screen, press < or > to go to the previous or next photo.

Advanced Playback


Zoom in & out during slide show


1. During playback, press  (MENU) to display the option menu.
2. Select the [Zoom] option using Δ/∇ , and press **Center button** to display the [Zoom] menu.
3. Use red (R) or green (G) colored button to zoom out or in the picture. You can move through the zoomed picture using $\Delta/\nabla/</>$ buttons.
4. To return to the normal picture size, press yellow (Y) colored button.
5. Press BACK () to exit the [Zoom] menu.


Repeat Playback


During playback, press red (R) colored button repeatedly to select a desired repeat mode.

Music files

 **Track** – The current track or file will be played back repeatedly.

 **All** – All the tracks or files will be played back repeatedly.


 – The tracks or files will be played back in random order.

 **All** – All the tracks or files will be played back repeatedly in random order.

To return to normal playback, press red (R) colored button repeatedly to select [Off].

Viewing content information

The unit can display the content information.

1. Select a file using $\Delta/\nabla/</>$.
2. Press  (MENU) to display the option menu.
3. Select the [Information] option using Δ/∇ , and press **Center button**.

The file information appears on the screen.



Note



The information displayed on the screen may not correct comparing actual content information.

Changing content list view


On the [Movie], [Music] or [Photo] menu, you can change the content list view.

Method 1

Press red (R) colored button repeatedly.



Method 2

1. On the content list, press  (MENU) to display the option menu.
2. Use Δ/∇ to select the [View Change] option.
3. Press **Center button** to change the content list view.

Selecting a subtitle file

If the subtitle file name is different from the video file name, you need to select the subtitle file on the [Movie] menu before playing the movie.

1. Use **^ / V / < / >** to select the subtitle file you wish to play in the [Movie] menu.
2. Press **Center button**.



Press **Center button** again to deselect the subtitle file. Selected subtitle file will be displayed when you play the video file.

! Note

- If you press **■** (STOP) while playback, the subtitle selection is cancelled.
- This function is not available for playing file on a server via home network.

Setting your photo as a wallpaper

You can apply your photo to the wallpaper.


1. Press HOME (**⬇**).
2. Select [Smart Share] using **< / >**, and press **Center button**.
3. Select [Photo] using **^ / V**, and press ENTER (**⊙**).
4. Select [USB] option using **^ / V**, and press **Center button**.
5. Select a photo file, and press **□** (MENU) to display the option menu.
6. Use **^ / V** to select [Wallpaper], and press **Center button**.
7. Use **< / >** to select [Yes], and press **Center button** to be applied.

The photo will be set as [Wallpaper 5] on the [Setup] menu.

Options while viewing a photo

You can use various options during viewing a photo in full screen.

1. While viewing a photo in full screen, press **□** (MENU) to display the option menu.
2. Select an option using **^ / V**.




- 1 **Current photo/Total number of photos**
– Use **< / >** to view previous/next photo.
- 2 **Slide Show** – Press **Center button** to start or pause slide show.
- 3 **Music Select** – Select the background music for the slide show (page 32).
- 4 **Music** – Press **Center button** to start or pause background music.
- 5 **Rotate** – Press **Center button** to rotate the photo clockwise.
- 6 **Zoom** – Press **Center button** to display the [Zoom] menu.
- 7 **Effect** – Use **< / >** to select a transition effect between photos in a slide show.
- 8 **Speed** – Use **< / >** to select a delaying speed between photos in a slide show.

3. Press BACK (**⬅**) to exit the option menu.

Listening to music while slide show


You can display photo files while listening to audio files.

1. While viewing a photo in full screen, press  (MENU) to display the option menu.
2. Use Δ / ∇ to select [Music Select] option, and press **Center button** to display the [Music Select] menu.
3. Use Δ / ∇ to select a device, and press **Center button**.

Device that you can select are differ depending on the location of the photo file you are displaying in full screen.

| Photo location | Available Device |
|-------------------|-------------------|
| USB | USB |
| Share Folder (PC) | Share Folder (PC) |
| DLNA server | DLNA server |

4. Use Δ / ∇ to select a file or a folder you wish to play.



Select  and press **Center button** to display the upper directory.

Note

When selecting the audio file from a server, folder selection is not available. Only file selection is available.

5. Use \triangleright to select [OK], and press **Center button** to complete music selection.

On-Screen display


You can display and adjust various information and settings about the content.

Displaying content information on-screen

1. While playback, press  (MENU) to show various playback information.




- 1 **Title** – current title number/total number of titles
- 2 **Time** – elapsed playing time/total playback time
- 3 **Audio** – selected audio language or channel
- 4 **Subtitle** – selected subtitle.
- 5 **Code Page** – selected subtitle code page (page 33).
- 6 **TV Aspect Ratio** – selected TV aspect Ratio.
- 7 **Picture Mode** – selected picture mode.

2. Select an option using Δ / ∇ .
3. Use \triangleleft / \triangleright to adjust the selected option value.
4. Press BACK() to exit the On-Screen display.


Note

- If no button is pressed for a few seconds, the on-screen display disappears.
- Available items may differ depending on titles.

Playing from selected time

1. Press  (MENU) during playback. The time search box shows the elapsed playing time.
2. Select the [Time] option and then input the required start time in hours, minutes, and seconds from left to right.

For example, to find a scene at 2 hours, 10 minutes, and 20 seconds, enter "21020".

Press  to skip the playback 60 seconds forward or backward.




3. Press **Center button** to start playback from selected time.



Note

- This function may not work on some titles.
- This function may not work depending on the file type and ability of the DLNA server.

Listening to a different audio track





1. During playback, press  (MENU) to display the On-Screen display.
2. Use  to select the [Audio] option.
3. Use  to select desired audio language, audio track or audio channel.



Note





Immediately after you have switched sound, there may be a temporary discrepancy between the display and actual sound.

Selecting a subtitle language

1. During playback, press  (MENU) to display the On-Screen display.
2. Use  to select the [Subtitle] option.
3. Use  to select desired subtitle language.
4. Press BACK() to exit the On-Screen display.

Changing TV Aspect Ratio

You can change the TV aspect ratio setting while playback.

1. During playback, press  (MENU) to display the On-Screen display.
2. Use  to select the [TV Aspect Ratio] option.
3. Use  to select desired option.
4. Press BACK() to exit the On-Screen display.







Note

Even if you change the value of the [TV Aspect Ratio] option in On-Screen display, the [TV Aspect Ratio] option in the [Setup] menu is not changed.



Changing subtitle code page

If the subtitle is displayed in broken letter, you can change the subtitle code page to view the subtitle file properly.


1. During playback, press  (MENU) to display the playback menu.
2. Use  to select the [Code Page] option.
3. Use  to select desired code option.
4. Press BACK() to exit the On-Screen display.


Changing Picture Mode

You can change the [Picture mode] option while playback.

1. During playback, press  (MENU) to display the On-Screen display.
2. Use \wedge/\vee to select the [Picture Mode] option.
3. Use \lt/\gt to select desired option.
4. Press BACK() to exit the On-Screen display.

Setting the [User setting] option

1. During playback, press  (MENU) to display the On-Screen display.
2. Use \wedge/\vee to select the [Picture Mode] option.
3. Use \lt/\gt to select the [User setting] option, and press **Center button**.




4. Use $\wedge/\vee/\lt/\gt$ to adjust the [Picture Mode] options.

Select [Default] option then press **Center button** to reset the all video adjustments.

5. Use $\wedge/\vee/\lt/\gt$ to select the [Close] option, and press **Center button** to finish setting.

Using the Premium

You can use various content services via Internet with the Premium feature.

1. Check the network connection and settings (page 16).
2. Press HOME ()
3. Select the [Premium] using \lt/\gt , and press **Center button**.



4. Select an on-line service using $\wedge/\vee/\lt/\gt$, and press **Center button**.

! Note

- Detailed information of each service, contact to the content provider or visit support link of the service.
- The content of Premium services and service related information, including user interface, is subject to changes. Please refer to the web site of each service for most up-to-date information.
- Using Premium features with wireless network connection may result in improper streaming speed by interference from household devices that are using radio frequencies.
- When you are first time to access [Premium] or [LG Apps] feature, current country setting appears. If you want to change the country setting, select [Edit] and press **Center button**.

Using the LG Apps

You can use the LG application services on this unit via Internet. You can easily find and download various applications from LG Apps store.

1. Check the network connection and settings (page 16).
2. Press HOME (🏠).
3. Select the [LG Apps] using </>, and press **Center button**.



4. Select a category using </>, and press **Center button**.
5. Use ^/∇/</> to select an application, and press **Center button** to display the information.
6. Press **Center button** while [Install] icon is highlighted. The application will be installed to the unit.

To install an application to the unit, user needs to sign in. Refer to page 35 for more information of signing in.

7. Press yellow (Y) colored button to display the [My Apps] screen.
8. Select the installed application and press **Center button** to execute it.



Note

To install a paid application, you need to be a paid member. Visit www.lgtvapp.com for more information.

Signing in

To use the [LG Apps] feature, you need to sign in with your account.

1. On the [LG Apps] or [My Apps] screen, press red (R) colored button.
2. Fill the [ID] and [Password] field using the virtual keyboard.

If you do not have an account, press red (R) colored button to register.

3. Use ^/∇/</> to select [OK], and press **Center button** to sign in with your account.

If you select the [Auto Sign In] check box, your ID and password are remembered and automatically signed in without entering them.



Note

- If you want to sign in with other account, press red (R) colored button on [LG Apps] or [My Apps] screen, and select [Change User] option.
- To view the information of your account and applications, press red (R) colored button on [LG Apps] or [My Apps] screen, and select [Account Setting] option.

Managing my Apps

You can move or delete an installed application in the [My Apps] menu.

Move an application

1. Select an application, and press green (G) colored button to display the options.
2. Use ^/∇ to select [Move], and press **Center button**.
3. Use ^/∇/</> to select a position you want to move to, and press **Center button**.

Delete an application

1. Select an application, and press green (G) colored button to display the options.
2. Use ^/∇ to select [Delete], and press **Center button**.
3. Use </> to select [Yes], and press **Center button** to confirm.

Using the Browser Home

You can browse, search web pages using the web browser feature over the Internet.

! Note

- Web browser on this unit is different with a web browser on your PC. The web browser on this unit does not support additional plug-ins and platform-dependant technology such as ActiveX.
- Compatible Flash version on this unit is up to Flash 8.
- Playing a movie on the web browser can be restricted depending on a movie **source**.
- The web browser will force quit when the unit runs out of memory.


About the Browser Home menu

There are various options on the Browser Home menu. Use $\wedge / \vee / < / >$ to select an option and press **Center button** to select the options as described below.



Options available within the browser menu include.

1. Check the network connection and settings (page 16).
2. Press HOME (🏠).
3. Select the [Web Browser] using $< / >$, and press **Center button**.



4. Select an web page using $\wedge / \vee / < / >$, and press **Center button**.

! Note


Press **V** and $\wedge / \vee / < / >$ to select the desired web page in the web browser menu. Press **Center button** to enter the web page.

- 1 URL** – You can find a web page entering a web site address. The virtual keyboard will be displayed and enter a web address.
- 2 Favorites** – You can directly open your favorites web pages without entering web address.
- 3 History** – Displays web address list of previously opened web pages. Use \wedge / \vee to select a website address, and press **Center button** to open the web page. Press the red (R) colored button to clear history.

Editing your favorite web pages

In the Favorites menu, you can edit your favorites.

1. Press red (R) colored button to change the highlighter to edit mode.
2. The highlighter color will be changed to green color.
3. Select a web page and press **Center button** to display the [Edit] menu.



4. Use **Λ / V** to select an option and press **Center button**.

[Move] - Moves the web page to desired position in the favorites menu.


[Rename] - Edits the selected web page name. The virtual keyboard will be displayed.

[Delete] - Deletes the web page from favorites menu.

[Close] - Exits the edit menu

Additional browser options

There are various options on the browser menu. Press the corresponding remote buttons to use the options. You can also move the pointer and click the buttons to use the options.



- 1 Returns to previous page.
- 2 Returns to Browser Home menu.
- 3 You can zoom in and out the currently viewing page.
- 4 Saves current page to your favorites web page. The virtual keyboard will be displayed.
- 5 Searches web pages from Google by entering a keyword.
- 6 Display the browser menu.

[← / →] - Moves to the previous or next web page.

[Refresh] - Reloads the current web page.

[Settings] - To clear the saved data such as cookies and history, select this and select an option from the menu.

Troubleshooting

General

| Symptom | Cause & Solution |
|---|--|
| No Power. | <ul style="list-style-type: none">• Plug the power cord into the wall outlet securely. |
| Cannot play movie, photo or audio files. | <ul style="list-style-type: none">• The files are not recorded in a format that the unit can play.• The unit does not support the codec of the video file. |
| The remote control does not work properly. | <ul style="list-style-type: none">• The remote control is not pointed at the remote sensor of the unit.• The remote control is too far from the unit.• There is an obstacle in the path of the remote control and the unit.• The batteries in the remote control are exhausted.• We recommend using alkaline batteries. |
| The connected USB storage device is not recognized. | <ul style="list-style-type: none">• Try another different USB cable, some of USB cable may not support enough current for normal USB operation.• If you use a USB extension cable or USB HUB, the USB devices may not be recognized.• An USB device which requires additional program installation when you have connected it to a computer is not supported.• This unit supports only USB Flash Drive and USB External HDD with FAT16, FAT32 or NTFS format. |

Picture

| Symptom | Cause & Solution |
|-----------------------|---|
| There is no picture. | <ul style="list-style-type: none">• Select the appropriate video input mode on the TV so the picture from the unit appears on the TV screen.• Check the [HDMI Color Setting] in the [Setup] menu is set to the appropriate item that conforms to your video connection.• Your TV may not support the resolution you have set on the unit. Change the resolution that your TV accepts.• The player's HDMI OUT jack is connected to a DVI device that does not support copyright protection. |
| Picture noise appears | <ul style="list-style-type: none">• Set the resolution which your TV accepts. |

Resetting

| Symptom | Cause & Solution |
|------------------------------------|---|
| You can reset the unit as follows. | <ul style="list-style-type: none"> Press RESET button on the unit. This will force the unit to power off. Unplug the power cord, wait at least five seconds, and then plug it in again. |

Network

| Symptom | Cause & Solution |
|--|--|
| Streaming video services (such as YouTube™, etc.) are often stopped or “buffer” during playback. | <ul style="list-style-type: none"> Your broadband service speed may not be fast enough to stream video services. Contact your Internet Service Provider (ISP) and increase the broadband speed is recommended. |
| Shared folder or files from your PC or a media server are not displayed on the device list. | <ul style="list-style-type: none"> The firewall or anti-virus software on your media server is running. Turn off the fire wall or anti-virus software running on your PC or media server. The unit is not connected to the local area network that your PC or the media server are connected. |
| Cannot connect the unit to the access point or wireless LAN router. | <ul style="list-style-type: none"> The wireless communication may be interrupted from household devices that are using radio frequencies. Move the unit away from them. |
| Access point is not displayed on the “Access point name” list. | <ul style="list-style-type: none"> The access point or wireless LAN router may not broadcast its SSID. Set your access point to broadcast its SSID through your computer. Your network device such as access point may not set with available frequency range and channel that this unit can support. Try setting the frequency range and channel on the network device setting. |

Customer Support

You can update the Unit using the latest software to enhance the products operation and/or add new features. To obtain the latest software for this unit (if updates have been made), please visit <http://us.lgservice.com> or contact LG Electronics customer care center.

Open source software notice

To obtain the corresponding source code under GPL, LGPL and other open source licenses, please visit <http://opensource.lge.com>. All referred license terms, warranty disclaimers and copyright notices are available to download with the source code.


Network Software Update

Network update notification

From time to time, performance improvements and/or additional features or services may be made available to units that are connected to a broadband home network. If there is new software available and the unit is connected to a broadband home network, the unit will inform you about the update as follows.

Option 1:

1. The update menu will appear on the screen when you turn on the unit.
2. Use **</>** to select a desired option and then press **Center button**.



| | |
|----------|--|
| [OK] | Starts the software update. |
| [Cancel] | Exits the update menu and displays it next booting. |
| [Hide] | Exits the update menu and it does not appear until next software is uploaded in the update server. |

Option 2:

If the software update is available from the update server, the "Update" icon appears in the Home menu. Press blue (B) colored button to start the update procedure.


Software Update

You can update the unit using the latest software to enhance the products operation and/or add new features. You can update the software by connecting the unit directly to the software update server.

! Note

- Before updating the software in your unit, remove USB Device from the unit.
- Before updating the software in your unit, turn the unit off and then turn it back on.
- During the software update procedure, do not turn off the unit or disconnect AC power, or do not press any button.
- If you cancel the update, turn off the power and turn it on for stable performance.
- This unit cannot be updated to previous software version.

1. Check the network connection and settings (page 16).
2. Select [Software] option in the [Setup] menu then press **Center button**.
3. Select [Update] option, and press **Center button**.



The unit will check for the newest update.

! Note

- Pressing **Center button** while checking for the update will end the process.
- If there is no update available, the Message, "No update is found" appears. Press **Center button** to return to the [Home Menu].

4. If a newer version exists, the message "Do you want to update?" appears.
5. Select [OK] to start update. (Selecting [Cancel] will end the update.)

! Caution

Do not turn off the power during the software update.

! Note

If the software includes the driver update, disc tray may open during the process.

6. When update is completed, the message, "Update is complete." will appear, and then power will turn off automatically after 5 seconds.
7. Turn the power back on. The system now operates with the new version.

! Note

The Software Update function may not work properly depending on your internet environment. In this case, you can obtain the latest software from the authorized LG Electronics Service Center then update your unit. Refer to "Customer Support" on page 39.

About Nero MediaHome 4 Essentials

Nero MediaHome 4 Essentials is a software for sharing video, audio and photo files stored on your computer to this unit as a DLNA-compatible digital media server.

! Note

- The Nero MediaHome 4 Essentials CD-ROM is designed for PCs and should not be inserted in this unit or in any product other than a PC.
- The supplied Nero MediaHome 4 Essentials CD-ROM is a customized software edition only for sharing files and folders to this unit.
- The supplied Nero MediaHome 4 Essentials software does not support following functions: Transcoding, Remote UI, TV control, Internet services and Apple iTunes
- This manual explains operations with the English version of Nero MediaHome 4 Essentials as examples. Follow the explanation referring to the actual operations of your language version.

Installing Nero MediaHome 4 Essentials

Before you install Nero MediaHome 4 Essentials, check the system requirement shown below.

- Windows® XP (Service Pack 2 or higher), Windows Vista® (no Service Pack required), Windows® XP Media Center Edition 2005 (Service Pack 2 or higher), Windows Server® 2003
- Windows Vista® 64-bit edition (application runs in 32-bit mode)
- Hard drive space: 200 MB hard drive space for a typical installation of Nero MediaHome stand-alone
- 1.2 GHz Intel® Pentium® III or AMD Sempron™ 2200+ processors
- Memory: 256 MB RAM
- Graphics card with at least 32 MB video memory, minimum resolution of 800 x 600 pixels, and 16-bit color settings
- Windows® Internet Explorer® 6.0 or higher
- DirectX® 9.0c revision 30 (August 2006) or higher
- Network environment: 100 Mb Ethernet, WLAN

Start up your computer, and insert the supplied CD-ROM disc into your computer's CD-ROM drive. An installation wizard will walk you through the quick and uncomplicated installation process. To install Nero MediaHome 4 Essentials, proceed as follows:

1. Close all Microsoft Windows programs and exit any anti-virus software that may be running.
2. Insert the supplied CD-ROM disc into your computer's CD-ROM drive.
3. Click [Nero MediaHome 4 Essentials].
4. Click [Run] to start installation.
5. Click [Nero MediaHome 4 Essentials]. The installation is prepared and the installation wizard appears.
6. Click the [Next] button to display the serial number input screen. Click [Next] to go to the next step.
7. If you accept all conditions, click [I accept the License Conditions] check box and click [Next]. Installation is not possible without this agreement.
8. Click [Typical] and click [Next]. The installation process is started.

9. If you want to take part in the anonymous collection of data, select the check box and click the [Next] button.
10. Click the [Exit] button to complete the installation.

Sharing files and folders

On your computer, you must share the folder contained video, audio and/or photo content to play them on this unit.

This parts explains the procedure for selecting the shared folders on your computer.

1. Double-click the "Nero MediaHome 4 Essentials" icon on the desktop.
2. Click [Network] icon on the left and define your network name in the [Network name] field. The Network name you enter will be recognized by your unit.
3. Click [Shares] icon on the left.
4. Click [Local Folders] tab on the [Shares] screen.
5. Click [Add] icon to open the [Browse Folder] window.
6. Select the folder containing the files you want to share. The selected folder is added to the list of shared folders.
7. Click [Start Server] icon to start the server.

Note

- If the shared folders or files are not displayed on the unit, click the folder on the [Local Folders] tab and click [Rescan Folder] at the [More] button.
- Visit www.nero.com for more information and software tools

Trademarks and Licenses



HDMI, the HDMI logo and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC.



Manufactured under license from Dolby Laboratories. Dolby and the double-D symbol are trademarks of Dolby Laboratories.



Manufactured under license under U.S. Patent Nos: 5,956,674; 5,974,380; 6,487,535 & other U.S. and worldwide patents issued & pending. DTS, the Symbol, & DTS and the Symbol together are registered trademarks & DTS 2.0+Digital Out is a trademark of DTS, Inc. Product includes software. © DTS, Inc. All Rights Reserved.



DLNA®, the DLNA Logo and DLNA CERTIFIED® are trademarks, service marks, or certification marks of the Digital Living Network Alliance.



The Wi-Fi CERTIFIED Logo is a certification mark of the Wi-Fi Alliance.



DivX®, DivX Certified® and associated logos are trademark of DivX, Inc., and are used under license

Audio Output Specifications

| Jack/Setting Source | Digital Output (DIGITAL AUDIO OUT) *4 | | |
|------------------------|---------------------------------------|--------------------|-------------------|
| | PCM Stereo | DTS Re-Encode*3 *5 | Primary Pass-Thru |
| Dolby Digital | PCM 2ch | DTS | Dolby Digital |
| Dolby Digital Plus | PCM 2ch | DTS | Dolby Digital |
| DTS | PCM 2ch | DTS | DTS |
| Linear PCM 2ch | PCM 2ch | DTS | PCM 2ch |
| Linear PCM 5.1ch | PCM 2ch | DTS | PCM 2ch |
| Linear PCM 7.1ch | PCM 2ch | DTS | PCM 2ch |

| Jack/Setting Source | HDMI OUT | | |
|------------------------|------------|--------------------|----------------------------|
| | PCM Stereo | DTS Re-Encode*3 *5 | Primary Pass-Thru *1 *2 *3 |
| Dolby Digital | PCM 2ch | DTS | Dolby Digital |
| Dolby Digital Plus | PCM 2ch | DTS | Dolby Digital Plus |
| DTS | PCM 2ch | DTS | DTS |
| Linear PCM 2ch | PCM 2ch | DTS | Linear PCM 2ch |
| Linear PCM 5.1ch | PCM 2ch | DTS | Linear PCM 5.1ch |
| Linear PCM 7.1ch | PCM 2ch | DTS | Linear PCM 7.1ch |

*1 The secondary and interactive audio may not be included in the output bitstream if [Digital Output] or [HDMI] option is set to [Primary Pass-Thru]. (Except LPCM Codec: the output always include interactive and secondary audio.)

*2 This unit automatically selects the HDMI audio according to the decoding capability of the connected HDMI device even though [HDMI] option is set to [Primary Pass-Thru].

*3 The [Primary Pass-Thru] setting of the [HDMI] option and [DTS Re-Encode] setting of the [Digital Output] option cannot be set together. If you set them together, the [HDMI] or [Digital Output] option is set to [PCM Stereo] automatically.

*4 On the [Digital Output] audio output, the sampling frequency of DIGITAL AUDIO OUT is limited to 96 kHz.

*5 If the [HDMI] or [Digital Output] option is set to [DTS re-encode], the audio output is limited to 48 kHz and 5.1Ch.


- If [HDMI] option is set to [Digital Output] option is set to [Primary Pass-Thru] while playback Dolby Digital Plus or DIGITAL AUDIO OUT is limited to "PCM 2ch".

- If the HDMI OUT jack is connected to your TV with High Speed HDMI™ Cable and Dolby Digital Plus is outputted from HDMI OUT jack, DIGITAL AUDIO OUT jack is limited to "PCM 2ch" (When the HDMI and DIGITAL AUDIO OUT are connected simultaneously).
- The audio is outputted as PCM 48 kHz/16 bit for MP3/WMA file.
- You must select a digital audio output and a maximum sampling frequency that your Amplifier (or AV receiver) accepts using [Digital Output], [HDMI] and [Sampling Freq.] options on the [Setup] menu (see page 24).
- If the audio format of the digital output does not match the capabilities of your receiver, the receiver will produce a strong, distorted sound or no sound at all.
- Multi-channel Digital Surround Sound via digital connection can only be obtained if your receiver is equipped with a Digital Multi-channel decoder.

Specifications

| General | |
|------------------------|--|
| Power Supply | Refer to the main label |
| Power consumption | Refer to the main label |
| AC adapter | DA-18B12 |
| Dimensions (W x H x D) | Approx. 110 x 110 x 29 mm (4.3 x 4.3 x 1.1 inches) |
| Net Weight (Approx.) | 0.28kg |
| Operating temperature | 5 °C to 35 °C (41 °F to 95 °F) |
| Operating humidity | 5 % to 90 % |

| Outputs | |
|-----------------------------|----------------------------------|
| HDMI OUT (video/audio) | 19 pin (Type A, HDMI™ Connector) |
| DIGITAL AUDIO OUT (OPTICAL) | 3 V (p-p), Optical jack x 1 |

| System | |
|---------------------------------|---|
| Signal system | Standard NTSC color TV system |
| LAN port | Ethernet jack x 1, 10BASE-T / 100BASE-TX |
| Wireless LAN (internal antenna) | Integrated IEEE 802.11n (5 GHz and 2.4 GHz bands) wireless networking access, compatible with 802.11a/b/g Wi-Fi networks. |
| Bus Power Supply (USB) | DC 5 V  500 mA |

- Design and specifications are subject to change without notice.

Maintenance

Handling the Unit

When shipping the unit

Please save the original shipping carton and packing materials. If you need to ship the unit, for maximum protection, re-pack the unit as it was originally packed at the factory.

Keeping the exterior surfaces clean

- Do not use volatile liquids such as insecticide spray near the unit.
- Wiping with strong pressure may damage the surface.
- Do not leave rubber or plastic products in contact with the unit for a long period of time.

Cleaning the unit

To clean the unit, use a soft, dry cloth. If the surfaces are extremely dirty, use a soft cloth lightly moistened with a mild detergent solution. Do not use strong solvents such as alcohol, benzene, or thinner, as these might damage the surface of the unit.

Important Information Relating to Network Services

All information, data, documents, communications, downloads, files, text, images, photographs, graphics, videos, webcasts, publications, tools, resources, software, code, programs, applets, widgets, applications, products and other content ("Content") and all services and offerings ("Services") provided or made available by or through any third party (each a "Service Provider") is the sole responsibility of the Service Provider from whom it originated.

The availability of and access to Content and Services furnished by the Service Provider through the LGE Device are subject to change at any time, without prior notice, including, but not limited to the suspension, removal or cessation of all or any part of the Content or Services.

Should you have any inquiry or problem related to the Content or Services, you may refer to the Service Provider's website for the most up-to-date information. LGE is neither responsible nor liable for customer service related to the Content and Services. Any question or request for service relating to the Content or Services should be made directly to the respective Content and Service Providers.

Please note that LGE is not responsible for any Content or Services provided by the Service Provider or any changes to, removal of, or cessation of such Content or Services and does not warrant or guaranty the availability of or access to such Content or Services.

