

HOME THEATER PC CHASSIS

Model: HTPC 6000B Color: Black Quick Installation Guide

(U.S. & Canada Only)
Version 1.0



DISCLAIMER

No warranty or representation, either expressed or implied, is made with respect to the content of this documentation, its quality, performance, merchantability, or fitness for a particular purpose. Information presented in this documentation has been carefully checked for reliability; however, no responsibility is assumed for inaccuracies. The information contained in this documentation is subject to change without notice. In no event will nMedia will be liable for direct, indirect, special, incidental, or consequential damages arising out of the use or inability to use this product or documentation, even if advised of the possibility of such damages.

TRADEMARKS

All trademarks used in this user guide are the property of their respective owners.

COPYRIGHT

© 2004-2013 by NMEDIA SYSTEM, INC. All rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language in any form by any means without the written permission of NMEDIA SYSTEM, INC.

TECHNICAL SUPPORT

If a problem arises with your system and no solution can be obtained from this user guide, please contact your place of purchase or local dealer.

REVISION HISTORY

V 1.0 January, 2013

Table of Contents

Overview	2
Standard Components Equipped	2
Other Suggested Components	2
Installation Flowchart (Basic Procedures)	2
Installation Tools	2
Step 1: Remove top cover and remove the optical drive bracket	3
Step 2: Install Motherboard and connect cables	3
Step 3: Install Hard Drive and Optical Drive	3
Step 4: Connect Cables	4
Step 5: Other Component Installation	4
Specifications	5
Reference	5
Visit our website for more detail installation in PDF format.	5
Safety Instructions	5
RMA Return Policy	6

Note:

This user guide is designed to provide the user a quick reference for chassis setup. We assume you need the information regarding how to assemble the system, such as Motherboard, CPU, RAM Memory, Hard Drive, DVD ROM, Operating System..., etc. Based on this assumption, we make this user guide of quick installation guide. Please follow the description step by step to install the components. If you have any question in assembling the system, please refer your questions to the appropriate Technical Support of the component vendors.

Overview

Standard Components Equipped

- HTPC 6000B Black Chassis
- 2 x 80mm silent case fan; 1 x 120mm silent HDD fan
- Front connectors (onboard connectors required)
 - USB 2.0 x 1; USB 3.0 x 1
 - HD or AC97 MIC & HeadPhone x 1
 - SDHC 2.0 compliance all in one card reader x 1
- Tight cables, screws, installation guide

Other Suggested Components


- Window 8 Premium or Ultimate Operation System
- ATX and or Micro ATX Motherboard
- ATX Power Supply
- CPU / Quiet Cooler
- Hard Drive (SATA is **recommended**)
- RAM Memory
- Optical Drive (DVD Burner is **recommended**)
- 2.4GHz Wireless Keyboard (nMEDIAPC HTPCKB-100 is **recommended**)



Suggested upgrades

- 20X2 nMEDIAPC programmable LCD module
- Sound Card
- Video Graphic Card (Fanless model is **recommended**)
- TV Tuner Card (MCE certified is **recommended**)

Installation Flowchart (Basic Procedures)



Installation Tools

Screw driver / Screws / Tight cables / Installation guides

Installation Tips:

1. Some optical drives may need to take off the DVD tray cover in order to eject the tray smoothly without blocking by the DVD flip down door.
2. Install the optical drive to the "A" position slot.
3. Use the special made hard drive noise reduction screws to install hard drive.




4. Do not perform cable management until your system is fully configured. This will make the cable management a better smooth procedure.

5. Do not install optional upgrade, i.e. video card, TV tuner card etc. Use everything on board (video & sound) to configure system and install operation system. After then, install the upgrades one by one and restart the system on every step to ensure component compatibility and save times of troubleshooting when issue arises.
6. To ensure front access ports and card reader work properly, check cable connection accuracy & Bios setting if needed.
7. Case fans are super quiet. If you hear abnormal loud noise, take off the fan to hear the noise again to ensure not fan defectiveness, then re-install with properly screw installation to achieve minimum noise.

Step 1: Remove top cover and remove the optical drive bracket

1. Take off the 2 finger screws and move the top cover backward to take off. Put it aside on a safety place.
2. Take off the two screws that hold the optical/hard drive bracket. Push a little backward then raise it up or take it off
3. Note the arrow pointing is the front "F" facing when slotting back the rack after installing the optical drive & hard drive.




Step 2: Install Motherboard and connect cables


1. Follow motherboard user manual to connect cables, CPU, memory etc...
2. Install power supply

Step 3: Install Hard Drive and Optical Drive

1. Install Optical Drive. Lock the drive to the "B" position
2. Install hard drives. You can install up to 6 hard drives in this model. But, you have to follow the exact sequence to install them. First, take the two slots that are next to the optical drive first, then, use the four slots that are under the bracket. If you don't follow, the bottom drives will block the screw holes for the upper drive slots.



3. Install Optical Drive Bracket back to the case
4. Put the bracket in the slot hole that will hold it in 110 degree angel, connect cables and the power cords for the hard drive and optical drive
5. Connect power supply cords
6. Re-install the optical drive bracket



Step 4: Connect Cables

Following your motherboard user guide to:

<p>Onboard USB 2.0 Port Diagram</p>	<p>Connect Card Reader & USB Ports</p> <ul style="list-style-type: none"> • There are two USB connectors. One for the card reader (4 pins) and front USB 2.0 port (10 pins). So, two onboard USB 2.0 port are required • For the 4 pins Card Reader connector, Red Wire is always = "+5V"; Black = "GND", save the other side for PRO-LCD 4 pins connector • Connect USB 3.0 20 pin cable to your onboard USB 3.0 20x pins port
	<p>Connect HD Audio Check your board to see if it has HD onboard port that supports HD audio</p> <ul style="list-style-type: none"> • If yes, plug the HD connector to your HD onboard audio port • If no, plug it to your AC 97 chipset onboard audio port using the Y tale connector
	<ul style="list-style-type: none"> • Connect Power Switch connector to your onboard port • Connect Reset Switch connector to your onboard port • Connect HDD Power Switch connector to your onboard port
	<p>LCD Module</p> <p>If you purchase the LCD programmable module. Simply take off the black label that blocks the LCD window, install it behind the panel. No need to take off the panel, just take out the Optical bracket, you can install the module directly inside the case.</p>
	<p>Organize the cables with provided tied cables. See picture for reference.</p>

Step 5: Other Component Installation

For other components, including hard drive connection; RAM; CPU & cooler; optical drive, operating system, video card, sound card, TV tuner card and power supply connection etc., follow the user manuals and motherboard manual instruction.

Specifications

<u>Model</u>	HTPC 6000B
<u>Color</u>	Black
<u>Dimension</u>	Case: 17"(W) x 6.6"(H w/ feet) x 16.4"(D w/ panel) Metal Chassis: 17"(W) x 6.3"(H) x 15.4" (D)
<u>Material</u>	Aluminum & Acrylic panel & Steel Case
<u>Motherboard</u>	Support ATX; Micro-ATX; DTX & M-iTX
<u>Power Supply</u>	Support ATX PSU (not included)
<u>Drive Bays</u>	External 5.25" Bay x 1 Internal 3.5" Bay x 6 Internal 2.5" SSD x 1
<u>Expansions</u>	7 Slots / Full Size
<u>Cooling</u>	80mm Silent Case Fan x 2 120mm Case Fan x 1
<u>Front Connection</u>	USB 3.0 port x 1 USB 2.0 port x 1 High Definition Audio x 2 (support AC 97) All in one Card Reader (SDHC 2.0 compliance - high capacity & speed)
<u>LCD Display</u> (Optional, not included)	20X2 Programmable LCD display module with Internal USB connector, support all Window, Window Media Center Edition, Vista and Vista Media Center Edition operating system.

Reference

Visit our website for more detail installation in PDF format.

http://www.nmediapc.com/HTPC 2000/Quick_Guide_2000.pdf

Technical Support: support@nmediapc.com

Safety Instructions

- Always read the step by step installation instruction to protect your components
- Keep the user guide for future reference
- Keep away from humidity, liquid and temperature above 60c (140 f) environment
- Make sure the voltage of the power supply and adjust properly 110/230V
- Always unplug the power cord before inserting any add-on devices
- Get the system checked by service personnel if below happens:
- The power cable is damage

- Liquid has penetrated into the system
- Dropped and damaged

RMA Return Policy

- All accessories and cables must be returned as they were shipped
- Carefully re-packaging is needed to avoid shipping damages
- All warranties are subject to properly uses. Any human power damages return may be rejected according to warranty terms and conditions