

# Owner's Manual

## USB 3.0 to Dual SATA Docking/Cloning Station

Model: U339-002

### Product Features

- Connect two 2.5 in. or 3.5 in. SATA I, II or III hard drives via your computer's USB port
- Quickly access hard drive content without time-consuming internal installation
- Offline cloning at the touch of a button—duplicate one hard drive on another without connecting to a host computer
- LED progress bar displays cloning status
- Supports USB 3.0 data transfer rates up to 5 Gbps
- Backward compatible with USB 2.0 and USB 1.1

### PROTECT YOUR INVESTMENT!

Register your product for quicker service and ultimate peace of mind.  
You could also win an ISOBAR6ULTRA surge protector—a \$100 value!

[www.tripplite.com/warranty](http://www.tripplite.com/warranty)



1111 W. 35th Street, Chicago, IL 60609 USA • [www.tripplite.com/support](http://www.tripplite.com/support)

Copyright © 2016 Tripp Lite. All rights reserved.

## Package Includes

- U339-002 Docking/Cloning Station
- USB 3.0 Cable, 4 ft.
- External Power Supply (Input: 100–240V, 50/60 Hz, 1.2A; Output: 12V, 3A)
- Owner's Manual

## System Requirements

- Two 2.5 in. or 3.5 in. SATA hard drives
- Computer with available USB port (USB 3.0 port required to achieve maximum speeds)
- Windows, Mac or Linux OS

**Note:** Unit does not have to be connected to a computer to clone SATA drives.

## Docking Station Instructions

**Note:** If your SATA drive has not yet been formatted, you must format it using your computer's Disk Management utility to access it.

- 1)** Connect the included external power supply to the unit, and plug it into a Tripp Lite surge protector, power distribution unit (PDU) or uninterruptible power supply (UPS).
- 2)** Insert your 2.5 in. or 3.5 in. SATA drive into an available bay on the unit, making sure it seats securely on the SATA connector. Repeat this step to connect a second SATA drive.
- 3)** Connect the included USB 3.0 cable between your computer and the unit.
- 4)** Use the ON/OFF button on the rear of the unit to turn on power. The green Power LED will light to indicate power is being received. The orange Drive LEDs will light to indicate a SATA drive is connected to the corresponding port. The orange LEDs will blink while the SATA drive is being recognized by the computer, then turn solid once the drive is available for use.

## Offline Cloning Instructions

### Notes:

- If your SATA drive has not yet been formatted, you must format it using your computer's Disk Management utility to access it.
  - The Slave Drive's (Bay B) capacity must be larger than that of the Master Drive (Bay A). If its capacity is smaller than or equal to the Master Drive, you will not be able to clone data to it.
  - Before cloning, ensure no important data is stored on the Slave Drive. Once cloning begins, all data on the Slave Drive will be deleted and replaced with the cloned data from the Master Drive.
- 1) Connect the included external power supply to the unit, and plug it into a Tripp Lite surge protector, power distribution unit (PDU) or uninterruptible power supply (UPS).
  - 2) Insert the 2.5 in. or 3.5 in. SATA Master drive (the drive you want to clone) into the unit's Master Drive (Bay A).
  - 3) Insert the 2.5 in. or 3.5 in. SATA Slave drive (the drive the cloned data will be copied to) into the unit's Slave Drive (Bay B).
  - 4) Use the ON/OFF button on the rear of the unit to turn on power. The green Power LED will light to indicate power is being received. The orange Drive LEDs will light to indicate a SATA drive is connected to the corresponding port and ready for cloning.
  - 5) Press and hold the CLONE button for approximately 3 seconds, then release.
  - 6) When the blue 100% LED lights, press and release the CLONE button again. The blue 25% LED will blink, indicating cloning is occurring. The progress bar's LEDs will light solid blue to indicate the percentage of cloning completed as the process continues.
  - 7) When all the LEDs are solid blue, cloning is complete.

## Warranty and Product Registration

### 1-YEAR LIMITED WARRANTY

TRIPP LITE warrants its products to be free from defects in materials and workmanship for a period of one (1) year from the date of initial purchase. TRIPP LITE's obligation under this warranty is limited to repairing or replacing (at its sole option) any such defective products. To obtain service under this warranty, you must obtain a Returned Material Authorization (RMA) number from TRIPP LITE or an authorized TRIPP LITE service center. Products must be returned to TRIPP LITE or an authorized TRIPP LITE service center with transportation charges prepaid and must be accompanied by a brief description of the problem encountered and proof of date and place of purchase. This warranty does not apply to equipment, which has been damaged by accident, negligence or misapplication or has been altered or modified in any way.

EXCEPT AS PROVIDED HEREIN, TRIPP LITE MAKES NO WARRANTIES, EXPRESS OR IMPLIED, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Some states do not permit limitation or exclusion of implied warranties; therefore, the aforesaid limitation(s) or exclusion(s) may not apply to the purchaser.

# Warranty and Product Registration

EXCEPT AS PROVIDED ABOVE, IN NO EVENT WILL TRIPP LITE BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE. Specifically, TRIPP LITE is not liable for any costs, such as lost profits or revenue, loss of equipment, loss of use of equipment, loss of software, loss of data, costs of substitutes, claims by third parties, or otherwise.

## PRODUCT REGISTRATION

Visit [www.triplite.com/warranty](http://www.triplite.com/warranty) today to register your new Tripp Lite product. You'll be automatically entered into a drawing for a chance to win a FREE Tripp Lite product!\*

\* No purchase necessary. Void where prohibited. Some restrictions apply. See website for details.

## FCC Notice, Class B

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Any changes or modifications to this equipment not expressly approved by Tripp Lite could void the user's authority to operate this equipment.

## WEEE Compliance Information for Tripp Lite Customers and Recyclers (European Union)



Under the Waste Electrical and Electronic Equipment (WEEE) Directive and implementing regulations, when customers buy new electrical and electronic equipment from Tripp Lite they are entitled to:

- Send old equipment for recycling on a one-for-one, like-for-like basis (this varies depending on the country)
- Send the new equipment back for recycling when this ultimately becomes waste

Use of this equipment in life support applications where failure of this equipment can reasonably be expected to cause the failure of the life support equipment or to significantly affect its safety or effectiveness is not recommended. Do not use this equipment in the presence of a flammable anesthetic mixture with air, oxygen or nitrous oxide.

Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice.



1111 W. 35th Street, Chicago, IL 60609 USA • [www.triplite.com/support](http://www.triplite.com/support)