

2 Port VGA Auto Switch
StarTech ID: ST122VGAU



The ST122VGAU VGA Auto Switcher lets you share a display between two computers and prioritize your VGA signals. The VGA switch features a primary and secondary VGA input port, and automatically outputs the signal from the primary input. When the signal feed connected to the primary input port is cut, the switcher automatically defaults to the video signal on the secondary VGA input port.

Designed for maximum control and versatility, the VGA Auto switcher also offers manual control of connected signals with easy-to-use front panel buttons that allow you to toggle between video sources.

Applications and Solutions

- Ideal for use with a laptop computer and a boardroom projector in meetings and presentations, backup safety control systems, and home A/V switching applications

Features

- Automatically selects the priority of incoming video signals for display
- Easy installation and set up in minutes
- Supports resolutions up to 1920x1440.

Technical Specifications

- Warranty: 1 Year warranty
- Color: Black
- Connector Types: 3 - High Density 15 pin Female
- Enclosure Type: Steel
- Number of Ports: 2
- Power Adapter Included: Yes
- Power Adapter - Amperage: .3
- Power Adapter - DC Voltage: 9 DC
- Center Tip Polarity: Positive
- Carton Quantity: 20
- Shipping (Package) Weight: 1.56 lb [0.71 kg]
- Video Bandwidth: 250 MHz
- DDC Support: DDC1, DDC2, DDC2B, DDC2B+, DDC2AB. DDC Support is only available on Port 1.
- Priority: Port 1 is set to have higher priority than port 2 when both signals are on.
- Wide Screen Supported:: Yes

