

# Veriton | Z

Z2660G

## Great flexibility, better efficiency

- Ergonomic viewing and placement options
  - Frame stand tilts from 8° to 60°
  - Optional Acer ErgoStand tilts from -5° to 35°
  - VESA wall mount supported
- Full HD webcam can rotate up to 180°
- Screwless design, modular components



- **Model:** VZ2660G
- **Part No:** DQ.VK5EQ.001
- **Family:** Veriton Z
- **EAN:** 4713147339037




Front view, with frame stand



Rear view, with optional ErgoStand



Bottom view

**Product views**

1 HD microphone	11 19.5" LED-backlit LCD (touch optional)	21 VESA mounting holes
2 Optical drive (optional)	12 Internet/optical drive indicator light	22 Adjustable ErgoStand (optional)
3 Audio-in jack	13 Power indicator light	23 DC-in power jack
4 Tilttable frame stand (6°-60°)	14 Power button	24 Ethernet port
5 Audio-out jack	15 Monitor on/off button	25 USB 3.0 port
6 SD card reader	16 Brightness button	26 VGA port
7 USB 3.0 port (optional)	17 One-button recovery (OBR) pinhole	27 Serial port (optional)
8 Removable feet for stand	18 Rear view of rotating HD webcam	28 Combo stereo headphone/mic jack
9 Two HD speakers	19 Dust-proof intake hole of fan	29 Two USB 2.0 ports
10 Rotating webcam (180°) with indicator light	20 Ventilation hole	30 DisplayPort™ port

**Operating system<sup>1,2</sup>**

Windows 7 Professional 64-bit and Windows 8.1 Pro 64-bit (DA/SV/FI/NO/EN)

**CPU<sup>1,3</sup>**

Intel® Celeron® Processor G1820T (2M Cache, 2.40 GHz)

**Chipset**

Intel® H81 Express chipset

**Memory<sup>1,4,5</sup>**

4GB (1x 4GB) Up to 16 GB of dual-channel DDR3

**Display<sup>1</sup>**19.5" LED-backlit LCD (None touch) 16:9 aspect ratio 1600 x 900 max resolution 250-nit brightness (cd/m<sup>2</sup>)**Storage<sup>1,6</sup>**

500 GB 2.5-inch 5400 RPM

**Optical drive (optional)**

N/A

**Audio**

Built-in stereo speakers Integrated high-definition sound

**Webcam****Video conferencing:** Integrated 2.0 MP Full HD high-sense webcam**Networking**

Gigabit Ethernet 802.11 a/b/g/n (combo mini-card)

**Input and output****Front/side I/O connectors:** Card reader, two audio jacks, USB 3.0 port **Rear I/O connectors:** VGA port, DisplayPort™ port, serial port on board header (COM2), Ethernet port, combo stereo headphone/mic jack, two USB 2.0 ports, USB 3.0 port**Expansion slots**

One PCIe x1 slot One Mini PCI Express® slot One mSata slot

**Windows Store Apps<sup>7,8</sup>**

<b>Productivity</b>	<b>Utilities</b>
• Evernote®	• Acer Explorer v1.0
• Skitch	

**Windows Desktop Apps<sup>7,10</sup>**

<b>Content</b>	<b>Productivity</b>	<b>Utilities</b>	<b>Web links</b>
• Microsoft Office 2013 <sup>11</sup>	• PowerSaver <sup>9,10</sup>	• McAfee® LiveSafe Internet Security Suite <sup>8,10</sup>	• Acer Touch Tools <sup>8,14</sup>
<b>ISP &amp; Communications</b>	• SmartBoot	• Norton™ Online Backup	• Agoda Weblink <sup>7,8</sup>
• Skype	• Veriton ControlCenter	<b>Utilities</b>	• Hotkey Utility v3.0
<b>Multimedia</b>	• Evernote®	• Acer Identity Card	• Software Assembler
• Cyberlink® PowerDVD™	• NewsXpresso <sup>9</sup>	• Acer Office Manager Agent	• Adobe Flash Player <sup>9</sup>
• Cyberlink® YouCam <sup>12</sup>	<b>Search</b>	• Acer Office Manager Console	• Adobe Reader X <sup>9</sup>
• Nero BackItUp 12 Essentials	• Yahoo Search <sup>8</sup>	• Acer Registration	• Power Management <sup>8</sup>
<b>Operating System</b>	<b>Security</b>	• Acer Live Updater	• Yandex.Disk <sup>7,5</sup>
• Microsoft Windows Virtual PC <sup>13</sup>	• Acer Proshield	• Acer Recovery Management	• Acer Accessory Store <sup>7</sup>
• Microsoft Windows XP Mode <sup>13</sup>	• McAfee® Internet Security Suite <sup>10</sup>	• Acer eSettings Management	
		• Acer Screen Grasp <sup>8,14</sup>	

**Commercial features**Intrusion alert (via BIOS)<sup>1</sup> Hard drive password protection (via BIOS) WOL (Wake On Lan)  
One-button recovery (OBR) PXE (Preboot eXecution Environment)**Accessories**

USB keyboard and mouse

**Power supply/adaptor**

3-pin 90 W AC adaptor

**Dimensions**

330 (W) x 60 (D) x 490 (H) mm (12.99 x 2.36 x 19.29 inches)

**System compliance**

DMI, GS, ENERGY STAR®, PC2001, RoHS

**Certifications**

BSMI, CCC, CE, FCC, CB

1. Specifications vary depending on model.	8. For Windows 8.1 only.
2. 64-bit software is required to enjoy the advantages of 64-bit processing.	9. For Windows 7 only.
3. Only supports 35W CPU.	10. Trial periods vary depending on the geographic region and specifications: 365-day trial for China, Taiwan, Hong Kong and Singapore (Simplified Chinese and Traditional Chinese OS models); 60-day trial for other regions. The trial periods vary depending on the OS language: 365 days for Simple Chinese/Traditional Chinese/T.C. (Hong Kong); 60 days for others.
4. A 64-bit operating system is required to enjoy the ultimate performance of 4 GB or higher memory.	11. Trial version.
5. Memory speed may vary, depending on the CPU, chipset or memory fitted.	12. Optional.
6. 1 GB is 1 billion bytes. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Recovery Management uses a portion of the stated hard disk capacity as dedicated backup space.	13. For Windows 7 Professional only.
7. Bundled software may vary depending on hardware configuration, OS and regional availability.	14. For touch model only.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty. In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region. Microsoft and Windows are registered trademarks of Microsoft Corporation. Intel, Intel Core, Core Inside, Pentium, and Pentium Inside are trademarks of Intel Corporation in the U.S. and other countries.