



LOW VOLTAGE TESTER


USER'S MANUAL



CT102

Please read this manual carefully and thoroughly before using this product.

KEY FEATURES

- Visual indication of AC or DC voltage
- Versatile alligator clip leads with boots
-  approved; safe for CAT I use
- Double insulated housing and leads
- Pocket clip on back

SAFETY INSTRUCTIONS

DANGER
Electric
Shock Risk



Warning



DANGER
Electric
Shock Risk

To avoid possible electric shock or personal injury, and to avoid damaging the tester or the equipment being tested:

- Do not use the CT102 in any way not detailed in this manual or the tester's safety features may be compromised.
- Never use the tester to detect the presence of voltages higher than 50V (AC or DC). Attaching the clip leads across a 110V or 220V line will burn out the bulb, increasing the risk of shock, personal injury and equipment

damage. Use caution when detecting AC voltages above $42\text{VAC}_{\text{RMS}}$.

- Before using the tester, inspect the case. Do not use the CT102 if the case is damaged. Look for cracks or missing plastic. Pay particular attention to the insulation around the connectors.
- Do not operate the tester around explosive gas, vapor, or dust.
- When using the probes, keep your fingers behind the finger guards. Never touch the metal ends of the probes when making a measurement.

OPERATING INSTRUCTIONS

Attach the clip leads across a low-voltage device (a doorbell transformer or relay, for example) or any two points in a low-voltage DC circuit. The bulb will light to indicate the presence of 5 to 50VDC.

Warning: Attaching the clip leads across a 110V or 220V line will burn out the bulb, increasing the risk of shock, personal injury and equipment damage.

SPECIFICATIONS

Voltage Detection Range:

5 to 50V AC/DC

Safety Rating: CAT I

Lead Thickness: 20 AWG

Operating Temperature: 21° to 104°F

(-5° to 40°C) @ <85%RH

(decreasing linearly to

<50%RH at 104°F/40°C)

Weight: 0.6 oz. (17g)

WARRANTY INFORMATION

General Tools & Instruments' (General's) CT102 Low Voltage Tester is warranted to the original purchaser to be free from defects in material and workmanship for a period of one year. Subject to certain restrictions, General will repair

or replace this instrument if, after examination, the company determines it to be defective in material or workmanship. The warranty period begins on the date of purchase. You are encouraged to register your product online. General will extend your warranty an additional 60 days if you register at www.generaltools.com/ProductRegistry. This warranty does not apply to damages that General determines to be from an attempted repair by non-authorized personnel or misuse, alterations, normal wear and tear, or accidental damage. The defective unit must be returned to General Tools & Instruments or to a General-authorized service center, freight prepaid and insured.

Acceptance of the exclusive repair and replacement remedies described herein is a condition of the contract for purchase of this product. In no event shall General be liable for any incidental, special, consequential or punitive damages, or for any cost, attorneys' fees, expenses, or losses alleged to be a consequence of any damage due to failure of, or defect in any product including, but not limited to, any claims for loss of profits.

Register now at www.generaltools.com/ProductRegistry to receive a 60-day extension to your warranty.

RETURN FOR REPAIR POLICY

Every effort has been made to provide you with a reliable product of superior quality. However, in the event your instrument requires repair, please contact our Customer Service to obtain an RGA (Return Goods Authorization) number before forwarding the unit via prepaid freight to the attention of our Service Center at this address:

General Tools & Instruments
80 White Street
New York, NY 10013
212-431-6100

Remember to include a copy of your proof of purchase, your return address, and your phone number and/or e-mail address.



Specialty Tools & Instruments

GENERAL TOOLS & INSTRUMENTS

80 White Street

New York, NY 10013-3567

PHONE (212) 431-6100

FAX (212) 431-6499

TOLL FREE (800) 697-8665

e-mail: sales@generaltools.com

www.generaltools.com

CT102 User's Manual

Specifications subject to change without notice

©2013 GENERAL TOOLS & INSTRUMENTS

NOTICE - WE ARE NOT RESPONSIBLE

FOR TYPOGRAPHICAL ERRORS.

MAN# CT102

12/11/13