Print only HP LaserJet Enterprise M605dn

Accelerate business results with outstanding print quality. Tackle large jobs and equip workgroups for success wherever business leads.² Easily manage and expand this impressively fast, versatile printer—and help reduce environmental impact.







Take productivity to the next level

- Monitor jobs and settings guickly with the 4-line display and use the 10-key pad for PIN printing.
- Meet high-volume demands with automatic two-sided printing and versatile paper trays—up to 3,600 sheets.³
- Improve efficiency. Add paper-handling accessories to presort jobs, print on different media, and more.⁴
- Print uninterrupted for longer periods of time with high-yield Original HP LaserJet cartridges.⁵

Meet business needs in the office and beyond

- Get optional wireless direct printing. Send prints from mobile devices—without accessing the network.⁶
- Add the option to print with a touch of your NFC-enabled mobile device to this printer—no network needed.⁷ •
 - Easily print from a variety of smartphones and tablets—generally no setup or apps required.²
 - Easily print from virtually anywhere in the office with Ethernet and optional wireless connectivity.⁸

Advanced capabilities, easy management

- Easily expand this printer as solutions advance and workgroup needs grow, with add-on, updatable features.
 - Protect sensitive data—at rest or in transit—with a variety of embedded and optional security solutions.⁹
- Easily take command of your printing environment from one central location—with HP Web Jetadmin.¹⁰ •
- Quickly troubleshoot problems using cloud-based help services that are relevant and up to date.¹¹



Care Pack

Less energy, more efficiency and savings

- Save energy—HP Auto-On/Auto-Off Technology turns your printer on when you need it and off when you don't.¹²
- Conserve resources—this efficient printer consumes less total energy than any device in its class.¹³
- Help save time and money with lightweight HP EcoEFFICIENT paper—engineered for clean, trouble-free printing. •
- Help reduce your impact. Count on easy, free cartridge recycling through HP Planet Partners.¹ ٠
- Protect your investment with HP Care Pack. Let our HP certified engineers resolve all your technical issues.¹⁴

Program availability varies. Original HP cartridge return and recycling is currently available in more than 49 countries, territories, and regions in Asia, Europe, and North and South America through the HP Planet Partners program. For more information, visit <u>hp.com/recycle</u>
 Local printing requires mobile device and printer be on the same network or have a direct wireless connection. Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to an HP Web-connected printer. App or software and HP ePrint account registration may also be required. Wireless breadband use requires exparately purchased adservice contract for mobile devices. Check with service provider for coverage and availability in your area. See <u>hp.com/go/mobileprinting</u> for more details. Some features require purchase of additional accessory, available Fall 2015.
 3,600 -sheet input capacity requires purchased adgite emust be purchased separately.
 The optional high-yield Original HP Laserlet cartridge must be purchased separately.
 Requires purchase of optional module, available Fall 2015, for the Laserlet Enterprise M605n and M605dn. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable multi-function printer prior to printer, prior to printer, Dending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the MP or printer. For details, see <u>hp.com/go/mobileprinting</u>
 Requires purchase of additional accessory, available Fall 2015, for the Laserlet Enterprise M605n and M605dn. Mobile device must be uncomercial printer prior to printer, prior to printer, prior more information, see <u>hp.com/go/mobileprinting</u>
 Requires purchase of optional HP Jetfürct 3000w near-Field communications

Technical specifications

Functions Print	Print only
Duplex print options	Yes
Print speed ¹	Black (normal, A4): Up to 55 ppm; Black (normal, letter): Up to 58 ppm
First page out	Black (A4, ready): As fast as 7 sec; Black (letter, ready): As fast as 7 sec
Print resolution	Black (best): Up to 1200 x 1200 dpi; Black (normal): HP ImageREt 3600 (600 x 600 dpi)
Print technology	Laser
Print resolution technologies	HP ImageREt 3600 (600 x 600 dpi), HP ProRes 1200 (1200 x 1200 dpi)
Print cartridges number	2 (black)
Standard print languages	HP PCL 6, HP PCL 5e , HP Postscript Level 3 emulation, native PDF printing (v 1.7)
Printer management	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac)
Connectivity	
Standard connectivity	Hi-Speed USB 2.0 ports (Host and Device); built-in Gigabit Ethernet 10/100/1000T network port; Hardware Integration Pocket (HIP)
Mobile print capability	HP ePrint, Apple AirPrint™
Network ready	Standard (built-in Gigabit Ethernet)
Network capabilities	Via HP Jetdirect Ethernet embedded print server (standard) supports: 10Base-T, 100Base-Tx, 1000Base-T; 802.3az (EEE) support on Fast Ethernet and Gigabit Ethernet; IPsec (standard)
Wireless capability	Optional, enabled with purchase of a pending hardware accessory
Memory	Standard: 512 MB; Maximum: 1.5 GB
Processor speed	1.2 GHz
Duty cycle (monthly) ²	Up to 225,000 pages; Recommended monthly page volume: ² 5,000 to 16,000 pages
Paper handling Input ⁷	100-sheet multipurpose tray 1, 500-sheet input tray 2, Automatic duplexer for two-sided printing; Optional: 500-sheet input tray, Custom media cassette (for tray 2 position only), 1500-sheet High-capacity input tray (add up to 4 additional trays for up 3600-sheet input capacity), Automatic duplexer for two-sided printing, 75-sheet envelope feeder
Output	500-sheet output bin, 100-sheet rear output bin; Optional: 500-sheet stacker, 500-sheet stapler-stacker, optional 500-shee 5-bin mailbox
Media type	Paper (bond, colour, letterhead, plain, preprinted, prepunched, recycled, rough, light), envelopes, labels, cardstock, transparencies, shelf edge labels, user-defined
Media weight	Multipurpose tray 1: 60 to 200 g/m ² ; Tray 2, optional 500-sheet input tray, optional Custom media cassette, optional 1,500-sheet High-capacity input tray: 60 to 120 g/m ² ; Optional Envelope feeder: 75 to 105 g/m ² ; Optional Duplexer: 60 to 120 g/m ²
Media sizes custom	Multipurpose tray 1: 76 x 127 to 216 x 356 mm; Tray 2, optional 500-sheet input tray: 148 x 210 to 216 x 356 mm; Optional Custom media cassette: 102 x 148 to 170 x 282 mm
Dimensions (W x D x H)	425 x 537 x 399 mm (16.7 x 21.1 x 15.7 in)
Weight	25.9 kg (57 lb)
What's in the box	HP LaserJet M605dn Printer; Pre-installed HP Black LaserJet Toner Cartridge (~10,500 pages); Pre-installed HP Duplexer; Installation guide, Support flyer; Printer documentation and software on CD-ROM; Power cord
Warranty features	One-year return to bench [®]
Systems	
	(32-bit) editions (Home Basic, Premium, Professional, etc.), Windows 7 all (32-bit, 64-bit) editions (windows R/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows 10 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows XP (SP3) (32-bit, 64-bit) editions (XP Home, XP Pro, etc.), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows XP (SP3) (32-bit, 64-bit) editions (XP Home, XP Pro, etc.), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows K/8.1 all (32-bit, 64-bit) editions (excluding RT OS for Tablets), Windows
Minimum system requirements	PC Windows XP (SP3) all 32-bit editions (XP Home, XP zo, other 05. of XP and Constructions (Home Basic, Premium, Professional, etc.), Windows 7 all 32-bit and 64-bit editions (excluding RT OS for Tablets), Windows 12 all 32-bit and 64-bit editions (excluding RT OS for Tablets), Windows OS compatible with Universal Print Driver (From H2.com): Windows 7 all 32-bit and 64-bit editions (excluding RT OS for Tablets), Windows OS compatible with Universal Print Driver (From H2.com): Windows 7 all 32-bit and 64-bit editions (excluding RT OS for Tablets), Windows Vista all 32-bit and 64-bit editions (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editions (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS for Tablets), Windows 8/8.1 all 32-bit and 64-bit editors (excluding RT OS fo
Fonts and typefaces	105 internal TrueType fonts scalable in HP PCL, 92 internal scalable fonts in HP postscript Level 3 emulation (Euro symbol buit-in); 1 internal Unicode Fonts (Andale Mono WorldType); 2 Internal Windows Vista 8 Fonts (Calibri, Cambria) additional font soions available via third-party flash memory cards; HP LaserJet Fonts and IPDS Emulation available at hp.com/go/laserjetfonts
Control panel	4-line colour LCD display, 3 LED lights (Ready, Data, Attention), buttons (Information, Stop/Cancel, Return, Home, Folder, Clear 10-key numeric keypad
Power	Power supply type: Internal (Built-in) power supply; Power supply required: 110-volt input voltage: 100 to 127 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R40-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 1 Hz); R20-volt input voltage: 220 to 240 VAC (+/ - 10%), 50/60 Hz (+/ - 10\%), 50/60 Hz (+
Software included	Vort watts (walload off), 0.7 watts (value-off)
Acoustic	Acoustic power emissions: ⁶ 7.1 B(A); Acoustic power emissions (ready): 4.2 B(A); Acoustic pressure emissions bystande (active, printing): 56 dB(A); Acoustic pressure emissions bystander (ready): 27 dB(A)
Environmental ranges	Operating temperature range: 15 to 32° C (59 to 89.6° F); Recommended operating temperature: 15 to 32° C (59 to 89.6° F); Non-operating humidity range: 10 to 90% RH; Operating humidity range: 10 to 80% RH;
Security management	Recommended operating humidity range: 10 to 80% RH Identity management: Kerberos authentication, LDAP authentication, 1000 user PIN codes, optional HP and 3rd party advanced authentication solutions (e.g., badge readers); Network: IPsec/firewall with Certificate, Pre-Shared Key, and Kerbero authentication, Supports WIA-10 IPsec configuration Plug-in, 802.1X authentication (EAP-PEAPE EAP-LS), SMMPv3, HTTPS, Certificates, Access Control List; Data: Storage Encryption, Encrypted PDF & Email (uses FIPS 140 validated cryptographic libraries from Microsoft), Secure Erase, SSL/TLS (HTTPS), Encrypted Credentials; Device: Security lock slot, USB port disablement, hardware integration pocket for security solutions; Security management: Compatible with HP Imaging and Printing Security Center
Safety approvals and requirements	IEC 60950-1:2005 + A1:2009 +A2:2013 (International); EN 60950-1:2006 + A1:2010 + A1:2:2001 + A2:2013 (EL IEC 60825-1; UL/UL Listed (US/Canada); GS License (Europe); EN 60825-1 (Class 1 Laser/LED Device), Low Voltage Directive 2006/9/S/EC with CE Marking (Europe); other safety approvals as required by individual countries
Supported network protocols	IPv4/IPv6: Apple Bonjour Compatible (Mac OS 10.2.4 or highen), SNMPv1/v2c/v3, HTTP, HTTPS, FTP, TETP, Port 9100, LPD, WS Discovery, IPP, Secure-IPP, IPsec/Firewalt; IPv6: DHCPv6, MLDv1, ICMPv6; IPv4: Auto-IP, SLP, Telnet, IGMPv2, BOOTP/DHCP, WIN IP Direct Mode, WS Print; Other: NetWare NDS, Bindery, NDPS, IPrint
¹ Measured using ISO/IEC 24734 exclu	ides first set of test documents. For more information, see hp.com/go/printerclaims. Exact speed varies depending on the

IP Direct Mode, WS Print; Other: NetWare NDS, Bindery, NDPS, iPrint
 Measured using ISO/IEC 24734, excludes first set of test documents. For more information, see <u>hp.com/go/printerclaims</u>. Exact speed varies depending on the
 system configuration, software application, driver, and document complexity.
 Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other
 HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.
 HP recommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies
 replacement intervals and device life over an extended warranty period.
 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the
 product warranty.
 Acoustic values are subject to change. For current information see <u>hp.com/support</u>. Configuration tested: M605x, simplex printing, A4 paper at an average of
 56 ppm.

56 ppm.
6 Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors.
For details see <u>hp.com/go/learnaboutsupplies</u>
7 Paper handling accessories are offered separately and with an additional cost. To insure product stability, it is a requirement to purchase the HP Laserlet Printer Stand (F2G70A) when using M605 Printer with more than three HP Laserlet 500-sheet Input Tray Feeders (CE998A), or with one HP Laserlet 1500-sheet Input Tray (CE398A) and more than one HP Laserlet 500-sheet Input Tray (EC398A).
⁸ Warranty terms vary from country to country.

To learn more, visit hp.com

© Copyright 2015 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Microsoft and Windows are registered trademarks of Microsoft Corporation. AirPrint and the AirPrint logo are trademarks of Apple Inc., registered in the U.S. and other countries. Linux is a U.S. registered trademark of Linus Torvalds. UNIX is a registered trademark of The Open Group. NetWare® is a trademark of Novell, Inc.

Ordering information

Number E6B70A	Description HP LaserJet Enterprise M605dn Printer
Supplies & Ma	intenance Kits
Number CF281A	Description HP 81A Black Original LaserJet Toner Cartridge (~10,500 pages)
CF281X	HP 81X High Yield Black Original LaserJet Toner Cartridge (~25,000 pages)
F2G76A F2G77A	HP LaserJet Printer 110V Maintenance Kit HP LaserJet Printer 220V Maintenance Kit
Accessories ⁶	
Number	Description
F2G68A	HP LaserJet 500-Sheet Input Tray Feeder
F2G69A	HP LaserJet Auto Duplexer Two Side Print
F2G70A	HP LaserJet Printer Stand
F2G71A	HP LaserJet 500-Sheet Stacker
F2G72A	HP LaserJet 500-Sheet Stacker Stapler
F2G73A	HP LaserJet 1,500-Sheet Input Tray
F2G74A	HP LaserJet 75-Sheet Envelope Feeder
F2G81A	HP LaserJet 500-Sheet 5-Bin Mailbox
B5L28A	HP Two Internal USB Ports
B5L29A	HP Secure High Performance Hard Disk Drive
G6W84A	HP 1GB 90-Pin DDR3 Slim DIMM
F5S62A	HP Trusted Platform Module
F2G75A	HP LaserJet Custom Media Cassette Accessory
	The Educitie Caston media cassette necessory
HP Care Pack	
Number	Description
Number U8CR0E	Description HP 3-year Next Business Day + DMR LaserJet M605
	HP 3-year Next Business Day + DMR LaserJet M605
U8CR0E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support
U8CR0E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware
U8CR0E U8CR1E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware
U8CR0E U8CR1E U8CR2E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605
U8CR0E U8CR1E U8CR2E U8CR5E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support H9 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E U8CS5E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Ah 13x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E U8CS5E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E U8CS5E U8CS9E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E U8CS5E U8CS9E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E U8CS5E U8CS9E U8C50E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Ah 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR6E U8CS5E U8CS9E U8C50E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR5E U8CS5E U8CS9E U8CT0E U8CT1E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Mardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year AH 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR5E U8CS5E U8CS9E U8CT0E U8CT1E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Ah 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CR5E U8CS5E U8CS9E U8CT0E U8CT1E U8CT2E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Ah 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 0st Warranty 4h 9x5 + DMR LaserJet M605 Support HP 1-year Post Warranty 4h 13x5 + DMR
U8CR0E U8CR1E U8CR2E U8CR5E U8CR5E U8CS5E U8CS9E U8CT0E U8CT1E U8CT2E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Ah 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Ah Max5 + DMR LaserJet M605 Hardware Support HP 4-year Post Warranty 4h 9x5 + DMR LaserJet M605 Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CS5E U8CS9E U8CS9E U8CT0E U8CT1E U8CT2E U8CT3E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 1-year Post Warranty 4h 13x5 + DMR LaserJet M605 Support HP 1-year Post Warranty Next Business Day + DMR
U8CR0E U8CR1E U8CR2E U8CR5E U8CS5E U8CS9E U8CS9E U8CT0E U8CT1E U8CT2E U8CT3E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 1-year Post Warranty 4h 9x5 + DMR LaserJet M605 Support HP 1-year Post Warranty 4h 13x5 + DMR LaserJet M605 Support
U8CR0E U8CR1E U8CR2E U8CR5E U8CS5E U8CS9E U8CT9E U8CT1E U8CT1E U8CT2E U8CT5E	HP 3-year Next Business Day + DMR LaserJet M605 Hardware Support HP 3-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 3-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 4-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year Next Business Day + DMR LaserJet M605 Hardware Support HP 5-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 5-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 9x5 + DMR LaserJet M605 Hardware Support HP 4-year 4h 13x5 + DMR LaserJet M605 Hardware Support HP 1-year Post Warranty 4h 13x5 + DMR LaserJet M605 Support HP 1-year Post Warranty Next Business Day + DMR

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to <u>hp.com/go/cpc</u>

Supported paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

For more solutions information, please visit hp.com/go/gsc



