**IBC233B Bluetooth Boombox** 

## **IMPORTANT SAFETY INSTRUCTIONS**

## FCC Warnings

Read these Instructions. Keep these Instructions. Heed all Warnings.

- Follow all instructions.
- Do not use this apparatus no Clean only with a dry cloth. tus near water

- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions. Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatu (including amplifiers) that produce heat.
- (including amplifiers) that produce heat. Do not defeat the safety purpose of the polarized or grounding type plug. A polarized plug has two blacks with one wider than the other. A grounding type plug has two blacks and a third grounding proog. The wide black or the third proog are provided for your safety. When the provided plug desen off in into your cutlet, consult an electrician for replacement of the obsolete outlet. 9
- Protect the power cord from being walked on or pinched particularly at plugs, convenience recept and the point where they exit from the apparatus
- Only use attachments/accessor specified by the manufacturer essories
- specified by the manufacturer. 12. Use only with a cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/paratus combination to avoid inju-from tip-over. Upplug this apparatus during lightning storms or when unused for long periods of time.
- storms or when unused for long Refer all servicing to qualified is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped. 13.

# Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment responsible for compliance could void the user's authority to operate the equipment. NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiater radio frequency energy and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occu in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment of and on, the is encouraged to try to correct the interference by one or more of the following measure

- Reorient or relocate the receiving antenna. Increase the separation between the equipment and rece
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician for help.

#### Additional Warnings

- The apparatus shall not be exposed to dripping or splashing and that no objects filled with liquids, such as vases, shall be placed on apparatus. *L'appareil ne doit pas être exposé aux écoulements ou aux éclaboussures et aucun* objet ne contenant de liquide, tel qui un vases, ne doit ere placé sur *l'objet*. Main plug is used as disconnect device and it should remain readily operable during intended use. In order to disconnect the apparatus from the mains completely, the mains plug should be disconnected form the mains socked outlet completely.
- name ping snout de disconnecteu n'un un main societ d'une compret La prise du secteur ne doit pas être obstruée ou doit être facilement accessible pendant son utilisation. Pour être complétement déconnecté de l'alimentation d'entrée, la prise doit être débranchée du secteur. Battery shall not be exposed to excessive heat such as sunshine, fire or the like
- Les piles ne doivent pas être exposées à de forte chaleur, tel qu'à la lumière du soleil, au feu ou autres choses de semblable. Caution marking is located at the rear or bottom of the apparatus
- Cautom marking is recard at the real of bottom of the apparatus. Attention marquage est situé sur le paneau arrière ou inférieur de l'unité. The marking information is located at the rear or bottom of apparatus. Le marquage est situé sur le paneau arrière ou inférieur de l'unité.

Volume

Press to adjust the

volume.

## WARNINGS AND PRECAUTIONS

- CAUTION: TO PREVENT ELECTRIC SHOCK, MATCH WIDE BLADE OF PLUG TO WIDE SLOT. FULLY INSERT.
- WARNING: To reduce the risk of fire or electric shock, do not expose this apparatus to rain or moisture.
- AVERTISSEMENT: Pour réduire le risque d'incendie ou de choo électrique, ne pas exposer cet appareil sous la pluie et l'humidité. .
- CAUTION: Use of controls or adjustments or performance of procedures other than those specified may result in hazardous radiation exposure.
- WARNING: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
- responsible for compliance could void the user's authority to operate the equipment. WARNING: Do not place this unit diredly onto furniture surfaces with any type of soft, porous or sensitive finish. As with any nubber compound made with oils, the fest could cause marks or staining where the fest reside. We recommend using a protective barrier such as a clob at on a piece of glass between the unit and the surface to reduce the risk of damage and/or staining. WARNING: Use of this unit near fluorescent lighting may cause interference regarding use of the renote. If the unit is displaying erratio behavior move away from any fluorescent lighting, as it may be the cause. CALTEDIN: Dueme of candonica if there is in the cause.
- CAUTION: Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type.
- PRÉCAUTION: Danger d'explosion si les piles sont remplacées de façon incorrect. Remplacer les piles seulement par le même type de pile ou l'équivalent. WARNING: There is a danger of explosion if you attempt to charge standard Alkaline batteries in the unit. Only use rechargeable NiMH batteries.
- WARNING: The remote control's button cell battery contains mercury. Do not put in the trash, instead recycle or dispose of as hazardous waste
- nue pui nue trans, mistead recycle or dispose of as hazardous waste WARNING: Lithuin batterics, like all crechargaells batteries are recycladele and should be recycled or disposed of in normal household waste. Contact your local government for disp or recycling practices in your area. They should never be incimental since they might expl WARNING: Shock hazard. Do Not Open. AVIS: RESQUE DE CHOC ÉLECTROUE NE PAS OUTRIR Minis puis in tone ali concound charge and it should never incimental since they areaches a since they are aligned to the since and it should never inciments and an and a since they area discoursed whereas and it should never inciments are an and a since they area discoursed whereas and it should never inciments are an and a since they area discoursed whereas and its hourd never the since they area the since they area discoursed whereas and its hourd never the since they area the since they area discoursed whereas and its hourd never the since they area the since they area the since the since they area they area they area they area the since they area the since they area discoursed whereas and its hourd never the since the since they area the since the since they area they area they area they area the since t
- Mains plug is used as disconnect device and it should remain readily operable du intended use. In order to disconnect the apparatus from the mains completely, th mains plug should be disconnected form the mains socket outlet completely. during manis ping snouto ce usconnected rolm ne manis societ outer . La prise du secteur est utilisé pour déconnect re système. La prise du secteur ne doit pas être obstruée ou doit être facileme accessible pendant son utilisation. Pour être complètement déco l'alimentation d'entrée, la prise doit être débranchée du secteur.

#### Do not mix old and new batteries Do not mix alkaline, standard (carbon-zinc), or rechargeable (ni-cad, ni-mh, etc) batteries

**Telescopic FM** 

Antenna

No mezcle baterías viejas y nuevas. No mezcle baterías alcalinas, estándar (carbono-zinc) o recargables (ni-cad, ni-mh, etc.) ELECTRIC SHOCK, DO NOT REMOVE COVER (OR BACK). NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE SERVICING

ATTENTION

WARNING: TO REDUCE THE RISK OF ELECTRIC SHOCK. DO NOT REMOVE







is symbol indicates that this product orporates double insulation between hazardous mains voltage and user accessible parts

## Source

Press to switch between CD. Bluetooth, Line In, and FM Radio modes.

## Tun/Skip/Search

In FM Radio mode, press to tune the radio. Press and hold to search for the next available station. In CD mode, press to skip to the next track. Press and hold to search. In Bluetooth mode, press to skip to the next track.

In CD Mode, press to program tracks to play in a specific order. In FM Radio mode, press to begin saving a station as a preset.

Customer Service: 1-888-999-4215

## OR UP Requires 6 C batteries 0 Prog/Mem ٢ $\square$ Line In 250 Preset-/Repeat Preset+/Stop Power Pair/Play/Pause Press and hold In FM Radio mode, In FM Radio mode, Press to turn the unit press to cycle though press to cycle though on or off. to begin pairing a preset stations. Bluetooth device. preset stations. Press to stop the current In CD Mode, press Press to play or pause to repeat the current track. the current track. track. Press twice Ο to repeat the entire album.

For Warranty Information and the most up-to-date version of this User's Guide, go to www.iLiveElectronics.com

Email Support: prodinfo@dpiinc.com, Email Parts: partsinfo@dpiinc.com


Copyright © 2012 Digital Products International (DPI, Inc.) All other trademarks appearing herein are the property of their respective owners. Specifications are subject to change without notice.


## Introduction and Setup

## Power

AC power input: requires an AC power cable (included)







## **Bluetooth Setup**

- Pairing a Bluetooth Device for the First Time 1. Power on the unit by pressing the **Power** button.
- Press the Source button to switch to Bluetooth Mode.

The display will show the flashing letters "bt".

3. "BT" will flash quickly on the display.

When pairing, remain within 3 feet of the unit.

If the unit does not automatically begin to pair, press and hold the **Pair** button.

 Using the native controls on your Bluetooth device, select the "IBC233" in your Bluetooth settings to pair.

If your device requests a password, enter the default password "0000".

Refer to the user's manual for your specific device for instructions on pairing and connecting Bluetooth devices.

5. When successfully paired, the display will stop flashing.

After initial pairing, the unit will stay paired unless unpaired manually by the user or erased due to a reset of the device.

If your device should become unpaired, follow the above steps again.

If any pairing issues should occur, un-pair the unit on your Bluetooth device and follow the above steps again.

#### Playing Audio Wirelessly

- 1. Follow the instructions for <u>Pairing a</u> <u>Bluetooth Device.</u>
- 2. Use the native controls on the connected Bluetooth Device to select a track.
- To play, pause or skip the selected track, use the native controls on the connected Bluetooth Device or press the Pair/Play/ Pause or Tun/Skip/Search buttons.
- 4. Audio played through the connected Bluetooth device will now be heard through the speakers.

## Radio

## Tuning the FM Radio

- 1. Press the **Source** button to switch to FM Radio mode.
- 2. Press the **Tun/Skip/Search** buttons to tune the radio manually, press and hold to search for the next available station.

#### Saving a Station as a Preset

- 1. Follow the instructions for <u>Playing the</u> <u>Radio</u>.
- 2. Press the Prog/Mem button.
- 3. Press the **Tun/Skip/Search** to select a preset number.
  - Up to 20 stations may be preset.
- 4. Press the **Mem** button to save the current station to the selected preset.

## Tuning to a Preset Radio Station

 In FM Radio mode, press the Preset-/ Repeat and Preset+/Stop buttons to cycle through saved presets.

## Radio Reception

Adjust the position of the **Telescopic FM Antenna** to improve FM radio reception.

## Line In

## Using the Line In

Requires a 3.5mm audio cable (not included)

- Connect the 3.5mm audio cable to the Line In on the unit and an audio output on an MP3 player or other audio source.
- 2. Press the **Source** button to switch to Line In mode.
- Use the native controls on the connected MP3 player or other audio source to play and control audio played through the clock radio.

## CD

Note: This unit is not compatible with MP3 CDs.

## Loading a CD

- 1. Open the Disc Door.
- Place a CD into the unit, label side facing up.
- 3. Close the Disc Door.

#### Playing a CD

- 1. Follow the instructions for Loading a CD.
- 2. Press the **Source** button to switch to CD mode.
- Press the Pair/Play/Pause button to begin playing the loaded CD.

## **Programming a CD**

- 1. Follow the instructions for <u>Loading a CD</u> and <u>Playing a CD</u>.
- 2. Press the Prog/Mem button.
- Press the Tun/Skip/Search buttons to select a track.
- Press the Prog/Mem button to save the track to the program.
- 5. Repeat step 3 and 4 until the desired number of CD tracks are programmed.
- 6. Press the **Play** button to begin playing the program.



## International Support

To download this User's Guide in English, Spanish, or French, or to get answers to frequently asked questions, visit the support section at: www.iLiveElectronics.com Para descargar este Manual del Usuario en inglés, español y francés, o para obtener respuestas a preguntas frecuentes, visite la sección de apoyo en www.iLiveElectronics. com

Pour télécharger ce guide de l'utilisateur en anglais, espagnol ou français, ou pour obtenir des réponses à des questions fréquemment posées, consultez la rubrique d'assistance sur www.iLiveElectronics.com

For Warranty Information and the most up-to-date version of this User's Guide, go to www.iLiveElectronics.com Email Support: prodinfo@dpiinc.com, Email Parts: partsinfo@dpiinc.com Customer Service: 1-888-999-4215

Copyright © 2012 Digital Products International (DPI, Inc.) All other trademarks appearing herein are the property of their respective owners. Specifications are subject to change without notice.