

LaserJet Pro 500 MFP M521dn

Finish jobs faster, produce high-quality documents, and make scanning and sharing simple. Get set up and connected quickly.^{3,7} Send quick commands from an intuitive color touchscreen. Easily conserve resources and recycle used cartridges.¹¹

Print speed:9 Up to 42 ppm black (letter), Up to 40 ppm black (A4)

First page out (black): As fast as 8.0 sec

Scan speed (letter):10 Up to 19 ppm (black & white), Up to 15 ppm (color)

Copy resolution: Up to 600 x 600 dpi black graphics and text, Up to 600 x 600 dpi color

graphics and text

Fax speed: 11 33.6 kbps, 3 sec per page (letter)

Paper handling: 100-sheet multipurpose tray, 500-sheet input tray 2, 50-sheet Automatic

Document Feeder (ADF), 250-sheet output bin, 100-sheet rear output bin

Standard connectivity: 1 Hi-Speed USB 2.0 Device; 1 Hi-Speed USB 2.0 Host; 1 Gigabit

Ethernet 10/100/1000Base-TX; 1 Telecom; 1 Phone

Duty cycle (monthly):12 Up to 75,000 pages



HP LaserJet Pro 500 MFP M521dn

Quickly create, capture, and deliver documents

- Finish faster—with less standing around—using singlepass, dual-head scanning.
- Stay on schedule—print up to 42 pages per minute.¹
 Handle high-volume printing without worries.
- Scan documents and send digital files in one easy step—to email, the cloud, network folders, or a USB drive.
- Efficiently handle large jobs, with an input capacity up to 1,100 sheets and automatic two-sided printing.

Increase efficiency with an easy-to-manage MFP

- Work smarter—access, store, and print business content quickly from the 8.89 cm color touchscreen.²
- Control access to walkup features and easily look up network email addresses, using LDAP connectivity.
- Save time with an easy-to-install Original HP cartridge.
 Save more, using a high-capacity cartridge.³
- Efficiently manage this MFP, using HP Web Jetadmin to remotely monitor office printing and device status.⁸

Set up fast and stay connected

- Get this MFP up and running fast with HP Smart Install—no CD required.⁴
- Easily print from your smartphone, tablet, or notebook at home, work, or on the go.⁵
- Use resources more efficiently with 100/1000 Base –TX Ethernet networking—easily print and share.
- Pull print jobs from your pocket—walk up and print right from a memory device via the USB port.

Improve your energy costs and save resources

- Help save energy with HP Auto-On/Auto-Off Technology, Instant-on Copy, and Instant-on Technology.⁶
- Conserve resources and save paper—use automatic two-sided printing.
- Get centralized, easy access to custom energy-saving options and printer settings with HP EcoSMART Console.
- Reduce your impact—easily recycle Original HP LaserJet toner cartridges through HP Planet Partners.⁷

HP EcoSolutions

- Reduce paper use by up to 50% using automatic two-sided printing.
- Reduce energy use with HP Instant-on Technology and HP Instant-on Copy.¹
- Save energy—HP Auto-On/Auto-Off Technology turns your printer on when you need it and off when you don't.²



Join HP in more sustainable printing hp.com/ecosolutions

¹ Compared with products that use traditional fusing and cold cathode fluorescent lamp (CCFL) copying.

² HP Auto-On and Auto-Off Technology subject to printer and settings.

Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. First page out exact speed varies depending on the system configuration, software program, document complexity, network, media width, media weight, environment, and job size. Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see hpconnected.com. He LaserJet 255X Black Toner Cartridge not included; please purchase separately. He Psmart Install works with Microsoft Windows only. Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to the printer. Wireless performance is dependent on physical environment and distance from access point. Wireless so perations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to an HP web-connected printer. App or software and HP ePrint account registration may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and availability in your area. See hp.com/go/mobileprinting for more details. HP Auto-On and Auto-Off Technology are subject to printer and settings. Instant-on Technology claim based on comparison with products that use traditional fusing. Instant-on Copy claim based on comparison with fluorescent tubes. Program availability varies. Original HP cartridge return and recycling is currently available in more than 50 countries, territories and regions in Asia, Europe, and North and South America through the HP Planet Partners program. For more information, visit: hp.com/go/weither 4 HP Web Jetadmin is free and can be downloaded at hp.com/go/webjetadmin. Measured using ISO/IEC 24734, excludes first set of test documents. For more in


Product walk around

- 1 Intuitive 8.9 cm (3.5-in) color touchscreen control panel with business apps
- 2 50-sheet automatic document feeder (ADF) with automatic two-sided scanning
- 3 Plate glass scanner handles up to A4/letter size
- 4 250-sheet output bin with extension for long paper
- 5 100-sheet rear output bin
- 6 100-sheet multipurpose tray 1handles heavy custom media up to 199 g/m^2 (53 lb bond)
- 7 500-sheet input tray 2
- 8 Tray fill indicator
- 9 On/Off button
- 10 Built-in automatic two-sided printing
- 11 Front door release button allows convenient access to HP all-in-one toner cartridge
- 12 Easy access USB port to save and print files directly
- 13 Access port for optional Kensington style lock
- 14 Ethernet network port for easy sharing
- 15 Hi-Speed USB 2.0 printing port
- 16 Telephone "line out" port
- 17 800 MHz processor, 256 MB RAM
- 18 Power connection

HP LaserJet Pro 500 MFP M521dn shown



Front view



Side I/O panel close-up

Series at a glance



M855dn

Model	M521dn
Part number	A8P79A
100-sheet multipurpose tray 1	✓
500-sheet input tray 2	✓
Duplex Printing / Copying	✓
3,500-sheet HCI	Not available

Top features

Speed your business with fast printing, powerful scanning, cloud access, and touchscreen simplicity.

Maintain peak performance with fast print speeds. Scan both sides of a page in one pass, and easily turn paper documents into digital files. Save paper with two-sided printing, and use the 50-sheet automatic document feeder to heighten productivity.

Access, store, and print web content from the touchscreen, using business apps. 1 Easily complete a range of print, copy, scan, and fax tasks. Use LDAP to manage device-level access and network email look up.

Install this MFP and start working in minutes.² Print from your smartphone, tablet, or notebook at home, work, or on the go.3 Easily access the MFP, print, and share files with convenient networking. Walk up and print from your USB drive.

Help reduce energy use through Instant-on Copy and HP Auto-On/Auto-Off Technology.4 Conserve resources with automatic two-sided printing. Centrally control printer settings to help save energy, and easily recycle used cartridges.5

HP LaserJet Pro 500 MFP M521dn

Get the most out of your printer with HP accessories, supplies, and services.

HP services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs. Choose from:

Optimized Care (optimum performance and stability): 4-hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

Standard Care (high level of uptime): Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

Basic Care (minimum recommended support): Next Business Day Onsite Support

4-hour Onsite Support: Onsite support within four hours after a service call received within the coverage window

Next Business Day Onsite Support: Onsite service the next business day after the service call is received

Maintenance Kit Replacement Service: Onsite replacement of your printer's maintenance kit including parts, materials, and labor

Installation with Network Configuration Service: Assembly, network configuration, and basic administrator familiarization

For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit hp.com/go/printservices

HP LaserJet Print Cartridges⁶ HP LaserJet Black Cartridge (~6,000 pages based on ISO/IEC 19752) CE255A HP LaserJet Black Cartridge (~12,500 pages based on ISO/IEC 19752) CE255X HP 55X Black Dual Pack LaserJet Toner Cartridges (~12,500 pages based on ISO/IEC 19752) CF255XD

A8P79A

Accessories

HP LaserJet 500-sheet Feeder/Tray CE530A HP LaserJet MFP M525 Cabinet CF338A

HP service and support

HP 3-year Next Business Day LaserJet Pro M521 MFP Hardware Support U6Z59E HP 3-year 4h 9X5 LaserJet Pro M521MFP Hardware Support U6Z61E HP 1-year Post Warranty 4h 9x5 LaserJet Pro M521 MFP Support U6Z68PE HP 1-year Post Warranty Next Business Day LaserJet Pro M521 MFP Hardware Support U6Z70PE

To know what HP Care Pack services exist for your product, please visit Care Pack Central at hp.com/go/cpc

hp.com/go/paper

Software

HP Web Jetadmin: hp.com/go/wja HP Easy Printer Care: hp.com/go/easyprintercare

HP Universal Print Driver: hp.com/go/upd

HP Install Network Printer Wizard: hp.com/go/inpw_sw

¹ Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see hpconnected.com. ² HP Smart Install works with Microsoft Windows only. ³ Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to the printer. Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to an HP web-connected printer. App or software and HP ePrint account registration may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and availability in your area. See hp.com/go/mobileprinting for more details. 4 HP Auto-On and Auto-Off Technology are subject to printer and settings. Instant-on Technology claim based on comparison with products that use traditional fusing. Instant-on Copy claim based on comparison with fluorescent tubes. Program availability varies. Original HP cartridge return and recycling is currently available in more than 50 countries, territories and regions in Asia, Europe, and North and South America through the HP Planet Partners program. For more information, visit: hp.com/recycle

HP LaserJet Pro 500 MFP M521dn

AIO functions	Driet converge faw Aid multitacking comparted Voc
Duplex print options	Print, copy, scan, fax; AiO multitasking supported: Yes Automatic (standard)
Print speed ¹	The control of the co
First page out ²	Top to 4c ppin tolers, retern, up to 4c ppin tolers, ret
Print technology	As its its source.
Print resolution	Black (best): Up to 1200 x 1200 dpi; Black (normal): HP FastRes 1200 (1200 dpi quality), 600 x 600 dpi with HP Resolution Enhancement technology
Print resolution Technologies	HP sat Res 1 200 (600 x 600 dpi), HP prokes 1 200 (1200 x 1 200 dpi), 600 x 600 dpi
Print cartridges number	1 (black)
Printer smart software features	H9 ePrint, Apple AirPrint™, Smart Install, HP Auto-On/Auto-Off technology
Mobile printing capability	HP ePrint, Apple AirPrint™, Mobile Apps
Standard print languages	HP PCL 6; HP PCL 5; HP postscript level 3 emulation, PCLm
Printer management	Windows: HP Device Toolbox, Status Alerts (default install), SNP Alerts (minimum network install), HP Web Jetadmin (download); Mac: HP Utility
Scan type	Flatbed, ADF
Scan speed ³	Letter: Up to 19 ppm (black & white), Up to 14 ppm (color)
Scan resolution	Hardware: Up to 300 x 300 dpi (color, grayscale and mono, ADF); Up to 1200 x 1200 dpi (color, grayscale and mono, flatbed);
	Optical: Up to 300, 600, 1200 dpi
Scan technology	Contact Image Sensor (CIS)
Scan file format	Windows Scan SW supports file format: JPG, RAW(BMP), PDF, TIFF, PNG; Mac Scan SW supports file format: TIFF, PNG, JPEG, JPEG-2000, PDF, PDF-Searchable, RTF, TXT
Scan input modes	From PC: Solution Center Lite (Windows Vista, Windows XP) or Device Stage (Windows 7, 8); TWAIN-compliant or WIA-compliant software
Scan size maximum	216 x 297 mm (8.5 x 11.7 in)
Scanner advanced features	Duplex scanning from ADF Scan to USB flash drive; Scan to network folder; Scan to email; Scan to cloud; Optimize text/picture; Selectable scan resolution 75 to 300 dpi
Twain version	Version 1.9
Bit depth/Grayscale levels	24 bit (8 bit for greyscale duplex jobs)/256
Copy speed4	Up to 42 ppm (black, letter) Up to 40 ppm (black, A4)
Copy resolution	Black (text and graphics): Up to 600 x 600 dpi; Color (text and graphics): Up to 600 x 600 dpi Up to 90 cropic
Max number of copies	Up to 99 copies
Copier resize	25 to 400% Number of conject Poduco/Solarce: Ligher/Darker: Detimize: Dance: Multi-page const Collation: Transplort: True cided: Draft mode: Image adjustment: Set as now defaults: Decimal of the collaboration of the co
Copier settings Fax speed ⁵	Number of copies Reduce/Enlarge; Ligher/Darker; Optimize; Paper; Multi-page copy; Collation; Tray select; Two-sided; Draft mode; Image adjustment; Set as new defaults; Restore defaults Up to 33.6 kbps; 3 sec per page
Fax resolution	Up to 33.6 kpb; 3 set per page Black (best): Up to 300 x 300 dp; Black (standard): Up to 203 x 98 dpi; Black and White (fine): 203 x 196 dpi, 256 levels of gray; Black Photo Grayscale: 300 x 300 dpi (halftone)
Fax resolution Fax smart software features	stack (best): Up to 300 x 300 dp; stack (standard): Up to 203 x 98 dp; stack and writer (me); 203 x 196 dpt, 256 levels of gray; stack wrote Graystate: 300 x 300 dp (natrone) Permanent fax memory backup; Fax forwarding; Fax address book; TAM interface, Speed-dial; Group dis, Juto redial; Block junk faxes; Polling; Send a fax with confirmation; Private fax receive
Fax memory	Up to 250 pages
Fax features	Auto fax reduction supported: Yes; Auto-redialing: Yes; Fax delayed sending: No; Distinctive ring detection supported: Yes; Fax forwarding supported: Yes; Fax phone TAM interface supported: Yes;
rax reatures	Fax polling supported: (ve.), nutrier supported: (ve.), requires Caller ID; PC interface supported: (ve.), returned apported: (ve.), returned apported: (ve.), requires caller ID; PC interface supported: (ve.), returned included; Telephone handset supported: (ve.), requires caller ID; PC interface supported: (ve.), returned included; Telephone handset supported: (ve.), requires caller ID; PC interface supported: (ve.), returned included; Telephone handset supported: (ve.), requires caller ID; PC interface supported: (ve.), returned included; Telephone handset supported included; Telephone hands
Standard connectivity	1 Hi-Speed USB 2.0 Device; 1 Hi-Speed USB 2.0 Host; 1 Gigabit Ethernet 10/100/1000Base-TX; 1 Telecom; 1 Phone
Network capabilities	Via built-in 100/1000Base-TX networking
Modem	33.6kbps
Memory	256 MB
Processor speed	800 MHz
Duty cycle (monthly, A4) ⁶	Up to 75,000 pages
Recommended monthly page volume ⁷	2,000 to 6,000 pages
Paper handing	100-sheet multipurpose tray, 500-sheet input tray 2, 50-sheet Automatic Document Feeder (ADF), 250-sheet output bin, 100-sheet rear output bin
Media type	Paper (bond, color, letterhead, plain, pre-printed, prepunched, recycled, rough); envelopes, labels, cardstock, transparencies, user-defined
Media weight	Tray 1: 14 to 53 lb; Tray 2, 3: 14 to 32 lb
Supported media sizes	A4, RA4, Oficio 216 x 343 mm, Oficio 216 x 347 mm, 10 x 15 cm, B5(JIS), B6(JIS), Postcard(JIS), Double Postcard(JIS), A5, A6, 16K 195 x 270 mm, 16K 184 x 260 mm, 16K 197 x 273 mm
Auto document feeder capacity	Standard, 50 sheets
Dimensions (W x D x H)	465 x 465 x 508 mm (18.3 x 18.3 x 20 in) Maximum: 465 x 900 x 750 mm (18.3 x 35.4 x 29.5 in)
Weight	22.3kg (52.7 lb)
What's in the box ^e	HP LaserJet Pro MFP M521dn; HP LaserJet Black introductory cartridge (~6000 pages); Printer documentation and software on CDs (Windows/Mac OS installation CD); Installation guide, Support flyer, Warranty Card; power cord; USB cable (AP & Brazil only); Fax Cable
Warranty features	One-year limited warranty, Onsite
Compatible operating systems	Full software installs supported on: Windows 8 32-bit and 64-bit, Windows 7 32-bit and 64-bit, Windows Vista 32-bit and 64-bit, Windows XP 32-bit (SP2 or higher); Driver only installs supported on: Windows 2012; Windows Server 2008 32-bit, Windows Server 2008 32-bit (SP3 or higher); Mac 05 X v 10.6.8 and later; Linpus Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package); SUSE Linux (10.3, 11.0, 11, 11.1, 11.2), Fedora (9, 9.0, 10, 10.0, 11.0, 11, 12, 12.0), Ubuntu (8.04, 8.04.1, 8.04.2, 8.10, 9.04, 9.10, 10.04), Debian (5.0, 5.0.1, 5.0.2, 5.0.3) (supported by the automatic installer); HPUX 11 and Solaris 8/9
Minimum system requirements	PC: Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit): 1 GHz 32-bit (x86) or 64-bit (x86) processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or
	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port
Fonts and typefaces	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port
Fonts and typefaces Control panel	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port
	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts.
Control panel	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, 65, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply
Control panel Display	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC 64, 65, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at the common gof laserjetfonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply Power supply type: Built-in power supply Powers upply required: Input voltage: 110 to 127 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) and 220V-240 VAC (+/- 10%), 50/60Hz (+/- 2 Hz)
Control panel Display	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, 65, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply Power supply type: Built-in power supply Power supply required: Input voltage: 110 to 127 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) and 220V-240 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) Power consumption: 760 watts (Printing), 520 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) Windows: HP Installer/Uninistaller, HP PCL 6 print driver, HP WIA Scan Driver, HP TWAN Scan Driver, HP Scan, HP Fax Setup Wizard, HP Send Fax, HP Fax Print Driver, Status Alerts, HP Update, DXP;
Control panel Display Power ³ Software included	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC 64, 65, or Intel® Core® Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at the comy go/laser/effonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply Power supply type: Built-in power supply Power supply required: input voltage: 110 to 127 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) and 220V-240 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) Power consumption: 760 watts (Printting), 520 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) Windows: HP Installer/Uninstaller, HP PCL 6 print driver, HP WIA Scan Driver, HP TWAN Scan Driver, HP Scan, HP Fax Print Driver, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP PCL 6 print driver, HP Scan, HP Sex Print Driver, HP Utility, HP Alerts, HP Firmware Updater
Control panel Display Power ^a	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply Power supply type: Built-in power supply Power supply type: Built-in power supply Power consumption: 750 watts (Printing), 520 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) Windows: HP Installer/Uninstaller, HP PCL & print driver, HP WIA Scan Driver, HP TWAIN Scan Driver, HP Scan, HP Fax Setup Wizard, HP Send Fax, HP Fax Print Driver, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP Postscript driver, HP Scan, HP Setup Assistant, HP Fax Print Driver, HP Utility, HP Alerts, HP Firmware Updater Acoustic power emissions (Fady): Inaudible Acoustic power emissions (ready): Inaudible Acoustic power emissions bystander (active, copy): 54 dB(A) Acoustic powere emissions bystander (active, copy): 54 dB(A) Acoustic powere emissions bystander (active, copy): 54 dB(A)
Control panel Display Power ³ Software included	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port Mac: Mac OSX v 10.6; PowerPC 64, 65, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 8.4 Scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply Power supply type: Built-in power supply Power supply type: Built-in power supply Power consumption: 760 watts (Printing), S20 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) Windows: HP Installer/Uninstaller, HP PCL 6 print driver, HP WA Scan Driver, HP Twan Scan Driver, HP Twan Scan Driver, HP Fax Print Driver, HP Fax Print Driver, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP Postscript driver, HP Scan, HP Setup Assistant, HP Fax Print Driver, HP Utility, HP Alerts, HP Firmware Updater Acoustic power emissions (active, copy): 6.8 B(A) Acoustic power emissions (active, copy): 6.8 B(A) Acoustic pressure emissions bystander (active, copy): 5.4 dB(A) Acoustic pressure emissions bystander (active, copy): 5.4 dB(A) Acoustic pressure emissions bystander (active, copy): 6.4 B(A) Acoustic pressure emissions bystander (active, copy): 6.4 B(A) Acoustic pressure emissions bystander (active, printing): 5.4 dB(A) Acoustic pressure emissions bystander (active, printing): 5.4 dB(A) Acoustic pressure emissions bystander (active, printing): 5.4 dB(A) Acoustic pressure emissions bystander (active, printing): 5.7 CB(A) Recommended operating humidity range: 10 to 90% RH Recommended operating humidity range: 30 to 70% RH Operating temperature range: 50 to 90.5° F (10 to 32.5° C)
Control panel Display Power ³ Software included Acoustic ¹⁰	Network port; Windows XP (32-bit) SP2: Pentium® 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet; USB or Network port Mac: Mac OSX v 10.6; PowerPC G4, 65, or Intel® Core™ Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port 84 scalable TrueType fonts. Additional Font Solutions available at the p.com/go/laserjetfonts. 8.89 cm (3.5-in) intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error) 8.89 cm (3.5-in) touchscreen, LCD (color graphics) Power supply type: Built-in power supply Power supply type: Built-in power supply Power supply required: Input voltage: 110 to 127 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) and 220V-240 VAC (+/- 10%), 50/60Hz (+/- 2 Hz) Power consumption: 760 watts (Printing), 520 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) Windows: HP Installer/Uninstaller, HP PCL 6 print driver, HP WIA Scan Driver, HP TWAN Scan, HP Fax Setup Wizard, HP Send Fax, HP Fax Print Driver, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP Postscript driver, HP Sean, HP Setup Assistant, HP Fax Print Driver, HP Utility, HP Alerts, HP Firmware Updater Acoustic power emissions (active, copy): 6.8 B(A) Acoustic power emissions (ready): Inaudible Acoustic pressure emissions bystander (active, copy): 54 dB(A) Acoustic pressure emissions bystander (active, printing): 54 dB(A) Acoustic pressure emissions bystander (ready): Inaudible Operating humidity range: 10 to 80% RH Non-operating humidity range: 10 to 90% RH Operating temperature range: 50 to 90.5° F (10 to 32.5° C)

¹ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see **bp.com/go/printerclaims**. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ² Exact speed varies depending on the system configuration, software application, driver and document complexity. ³ Scan speeds of up to 21 ppm measured at 200 dpi (b&w) and up to 15 ppm at 200 dpi (color) from automatic document feeder when scanning to digital file. Actual speeds may vary depending on scan resolution, network conditions, computer performance and application software. ⁴ First Corp Out and Coopy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application of work or speed varies to the standard resolution. More complicated pages or higher resolution will take longer and use more memory. ⁶ Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other IPL LaserJet or IPC Color LaserJet documents. For more information will take longer and use more memory. ⁶ Duty cycle is defined as the maximum number of pages per month of imaged output be within the stated range for optimization do other IPL LaserJet or IPC Color LaserJet documents. ⁶ Performance has been provided output be within the stated range for optimization do other IPL LaserJet or IPC Color LaserJet documents. ⁶ Performance has been provided output be within the stated range for optimization do other IPL LaserJet or IPC Color LaserJet documents. ⁶ Performance has been provided output be within the stated range for optimization do other IPL LaserJet or IPC Color Lase















© 2013 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries. Linux is a U.S. registered trademark of Linus Torvalds. Celeron are trademarks of Intel Corporation in the U.S. and/or other countries.

