HP LaserJet Pro M521dn Multifunction Printer



Finish jobs faster, produce high-quality documents, and make scanning and sharing simple. Get set up and connected quickly. Send quick commands from an intuitive color touchscreen. Easily conserve resources and recycle used cartridges.



Print speedUp to 42 ppm black (letter), Up to 40 ppm black (A4)

First page out (black)As fast as 13.4 sec. **Scan speed (letter)**Up to 21 ppm (b&w), up to 15 ppm (color)

Copy resolution Up to 600×600 dpi graphics and text, Up to 600×600 dpi color graphics and text.

Fax speedUp to 33.6 kbps; 3 sec per page.

Paper handling00-sheet multipurpose tray, 500-sheet input tray 2, 50-sheet automatic document feeder, 250-sheet output bin, 100-sheet rear output bin

Standard connectivityHP Jetdirect ew2500 802.11b/g Wireless Print Server J8021A; HP

Jetdirect 2700w USB Wireless Print Server J8026A.

Duty cycle (monthly)Up to 75,000 pages













Quickly create, capture, and deliver documents

- Finish faster—with less standing around—using single-pass, dual-head scanning.
- Stay on schedule—print up to 42 pages per minute. Handle high-volume printing without worries.
- Scan documents and send digital files in one easy step—to email, the cloud, network folders, or a USB drive.
- Efficiently handle large jobs, with an input capacity up to 1,100 sheets and automatic two-sided printing.

Increase efficiency with an easy-to-manage MFP

- Work smarter—access, store, and print business content quickly from the 3.5-inch color touchscreen.5
- Control access to walkup features and easily look up network email addresses, using LDAP connectivity.²
- Save time with an easy-to-install Original HP cartridge. Save more, using a high-capacity cartridge.
- Efficiently manage this MFP, using HP Web Jetadmin to remotely monitor office printing and device status.12

Set up fast and stay connected

- Get this MFP up and running fast with HP Smart Install—no CD required.7
- Easily print from your smartphone, tablet, or notebook at home, work, or on the go.8
- Use resources more efficiently with 100/1000 Base –TX Ethernet networking—easily print and share.
- Pull print jobs from your pocket—walk up and print right from a memory device via the USB port.

Improve your energy costs and save resources

- Help save energy with HP Auto-On/Auto-Off Technology, Instant-on Copy, and Instant-on Technology.¹⁰
- Conserve resources and save paper—use automatic two-sided printing.
- Get centralized, easy access to custom energy-saving options and printer settings with HP EcoSMART Console.
- Reduce your impact—easily recycle Original HP LaserJet toner cartridges through HP Planet Partners.¹¹

⁴ Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. First page out exact speed varies depending on the system configuration, software program, document complexity, network, media width, media weight, environment, and job size. ⁵ Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see hpconnected.com ⁶ HP Laser let 255X Black Toner Cartridge not included; please purchase separately. ⁷ HP Smart Install works with Microsoft Windows only. ⁸ Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to the printer. Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to an HP web-connected printer. App or software and HP ePrint account registration may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and adiability in your area. See hp.com/go/mobileprinting for more details ¹⁰ HP Auto-On and Auto-Off Technology are subject to printer and settings. Instant-on Technology claim based on comparison with fluorescent tubes. ¹¹ Program availability varies. Original HP cartridge return and recycling is currently available in more than 50 countries, territories and regions in Asia, Europe, and North and South America through the HP Planet Partners program. For more information, visit: hp.com/recycle ¹² HP Web Jetadmin is free and can be downloaded at hp.com/glowebjetadmin ¹³ An FCC Class A device cannot be marketed for use in a residential environment and an FCC class A device cannot be marketed for use in a

HP LaserJet Pro M521dn Multifunction Printer Specifications Table

Functions / Multitasking Supported	Print, copy, scan, fax / Yes
Print Speed	Letter: Up to 42 ppm black; ⁵ First Page Out: As fast as 8.0 sec black; ⁶
Print Resolution	Black (best) : Up to 1200 x 1200 dpi
Print Technology	Laser
Print Resolution Technologies	HP FastRes 1200 (600 x 600 dpi), HP ProRes 1200 (1200 x 1200 dpi), 600 x 600 dpi
rint Cartridges Number	1 (black)
itandard Print languages	HP PCL 6, HP PCL 5, HP postscript level 3 emulation, PCLm
rinter Smart Software Features	HP ePrint, Apple AirPrint™, Mopria-certified, Smart Install, HP Auto-On/Auto-Off technology
rinter Management	Windows: HP Device Toolbox, Status Alerts (default install), SNP Alerts (minimum network install), HP Web Jetadmin (download); Mac: HP Utility
can Type / Technology	Flatbed, ADF / Contact Image Sensor (CIS)
can Resolution	Hardware : Up to 300×300 dpi (color, grayscale and mono, ADF); Up to 1200×1200 dpi (color, grayscale and mono, flatbed); Optical : Up to 300 , 600 , 1200 dpi
can File Format	Windows Scan SW supports file format: JPG, RAW(BMP), PDF, TIFF, PNG; Mac Scan SW supports file format: TIFF, PNG, JPEG, JPEG-2000, PDF, PDF-Searchable, RTF, TXT
ican Input Modes	From PC: Solution Center Lite (Windows Vista, Windows XP) or Device Stage (Windows 7, 8); TWAIN-compliant or WIA-compliant software
can Size	ADF : 8.5 x 14 in Maximum; 5 x 7 in Minimum; Flatbed : 8.5 x 11.7 in
can Speed	Up to 19 ppm (black & white), up to 15 ppm (color) 7 Duplex : Up to 36 ipm (black & white), up to 14 ipm (color)
canner Advanced Features	Duplex scanning from ADF; Scan to USB flash drive; Scan to network folder; Scan to email; Scan to cloud; Optimize text/picture; Selectable scan resolution 75 to 300 dpi
it depth / Grayscale levels	24 bit (8 bit for grayscale duplex jobs) / 256
opy Speed	Black (letter): Up to 42 ppm
opy Resolution	Black (text and graphics): Up to 600×600 dpi; Up to 600×600 dpi; Color (text and graphics): Up to 600×600 dpi
laximum Number Of Copies	Up to 99 copies
opier Resize	25 to 400%
opier Settings	Number of copies; Reduce/Enlarge; Ligher/Darker; Optimize; Paper; Multi-page copy; Collation; Tray select; Two-sided; Draft mode; Image adjustment; Set as new defaults; Restore defaults
ax Speed	Up to : 33.6 kbps; Letter : 3 sec per page ⁴
ax Resolution	Black (best) : Up to 300×300 dpi; Black (standard) : 203×98 dpi
ax Smart Software Features	Permanent fax memory backup; Fax forwarding; Fax address book; TAM interface, Speed-dial; Group dial; Auto redial; Block junk faxes; Polling; Send a fax with confirmation; Private fax receive
ax Features	Fax Memory: Up to 250 pages; Auto Fax Reduction Supported: Yes; Auto-Redialing: Yes; Fax Delayed Sending: Yes; Distinctive Ring Detection Supported: Yes; Fax Forwarding Supported: Yes Fax Poling Supported: Yes; Fax Telphone Mode Supported: Yes; Fax Telphone Mode Supported: Yes; Junk Barrier Supported: Yes, requires Caller ID; Maximum Speed Dialing Numbers Up to 100 numbers (each can contain 100 numbers). PC Interface Supported: Yes, Software not included; Remode Retrieval Capability Supported: No. Telephone Handset Supported: No.
Standard Connectivity	1 Hi-Speed USB 2.0 Device; 1 Hi-Speed USB 2.0 Host; 1 Gigabit Ethernet 10/100/1000Base-TX; 1 Telecom; 1 Phone
etwork Capabilities	Via built-in 100/1000Base-TX networking
letwork Ready	Standard (built-in Gigabit Ethernet)
lobile Printing Capability	HP ePrint, Apple AirPrint™, Mopria-certified, Mobile Apps
lemory	Standard: 256 MB; Maximum: 256 MB
rocessor Speed	800 MHz / Hard disk: None
uty Cycle	Monthly, letter: 75000
tecommended Monthly Page Volume	2000 to 6000
ledia Types Supported	Paper (bond, color, letterhead, plain, preprinted, prepunched, recycled, rough); envelopes, labels, cardstock, transparencies, user-defined
ledia Weight Supported	Tray 1: 14 to 53 lb; Tray 2, 3: 14 to 32 lb
ledia Sizes Supported	Letter, Legal, Statement, 3×5 in, 4×6 in, 5×7 in , 5×8 in , Executive, 8.5×13 in, Envelope (#9, #10, Monarch, C5, DL, B5, C6); Discrete Custom Sizes: Minimum size 3×5 in, Maximum size 8.5×14 in
ledia Sizes Custom	Tray 1: 3×5 to 8.5×14 in; tray 2, optional 500-sheet tray (3): 4.1×5.8 to 8.5×14 in
aper Handling	100-sheet multipurpose tray, 500-sheet input tray 2, 50-sheet Automatic Oocument Feeder (ADF); 250-sheet output bin, 100-sheet rear output bin, 20plex Options : Automatic (standard); Auto Document Feeder (Spacity: Standard, 50 sheets, Envelope Feeder : No, Standard Paper Trays : 2; Input Capacities : Up to 600 sheets; Output Capacities : Up to 250 sheets; Up to 10 envelopes; Up to 75 sheets
What's in the box	ABP79A HP Laser Jet Pro MFP M521dn; HP Laser Jet Black cartridge (~6000 pages); Printer documentation and software on CDs (Windows/Mac OS installation CD); Installation guide; Support flyer; warranty card; Power cord; Fax Cable ¹
Replacement Cartridges	HP Laser Jet Black Cartridge CE255A (~6000 pages based on ISO/JEC 19752); HP Laser Jet Black Cartridge CE255X (~12,500 pages based on ISO/JEC 19752) ³

Product Dimensions	W x D x H : 18.3 x 18.3 x 20 in; Maximum : 18.3 x 35.4 x 29.5 in
Product Weight	52.7 lb
Warranty Features	One-year limited warranty, Onsite
Energy Efficiency Compliance	ENERGY STAR® qualified; EPEAT ® Silver
Control Panel	3.5-in intuitive touchscreen control panel with color graphic display; Buttons (Home, Cancel, Help, Right/Left Arrows, Back); LED indicator lights (Ready, Error)
Display Description	3.5" (8.89 cm) touchscreen, LCD (color graphics)
Software Included	Windows: HP Installer/Uninstaller, HP PCL 6 print driver, HP WIA Scan Driver, HP TWAIN Scan Driver, HP Scan, HP Fax Setup Wizard, HP Send Fax, HP Fax Print Driver, Status Alerts, HP Update, DXP; Mac: HP Installer, HP Postscript driver, HP Scan, HP Setup Assistant, HP Fax Print Driver, HP Utility, HP Alerts, HP Firmware Updater
Fonts and Typefaces	84 scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts.
Compatible Operating Systems	Full software installs supported on: Windows 8.32-bit and 64-bit, Windows, 7.32-bit and 64-bit, Windows Vista 32-bit and 64-bit, Windows Skra 32-bit and 64-bit, Windows Skra 32-bit shad 64-bit, Windows Skraver 2003 32-bit (SP3 or higher); Driver only installs supported on: Windows 2012; Windows Server 2003 32-bit (SP3 or higher); Mac 05 X v 10.6.8 and later; Linpus Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package); SUSE Linux (10.3, 11.0, 11, 11.1, 11.2), Fedora (9.9, 0.1, 10.0, 11.0, 11.2, 11.2), Ubuntu (8.04, 8.04.1, 8.04.2, 8.10, 9.04, 9.10, 10.04), Debian (5.0, 5.01, 5.0.2, 5.0.3) (supported by the automatic installer); HPUX II and Solaris 80?
Minimum System Requirements	PC: Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit): 1 GHz 32-bit (x86) or 64-bit (x64) processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit); 400 MB free hard disk space, (D/DVD-ROM or Internet, US8 or Network port, Windows XP (32-bit) SP2: Pentime* 233 MHz processor, 512 MB RAM 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port; MAC: Mac OSX v 10.6; PowerPC 64, 65, or Intel® Core® Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network port.
Power	Power Supply Type: Built-in power supply; Power Requirements: Input voltage: 110 to 127 VAC (+/- 10%), 50/60Hz (+/- 3 Hz) and 220V-240 VAC (+/- 10%), 50/60Hz (+/- 3 Hz); Power Consumption: 760
	watts (Printing), 520 watts (Copying from ADF), 18.2 watts (Ready), 4.3 watts (Sleep), 0.3 watts (Off) ²
Acoustics	Acoustic Power Emissions: 6.7 B(A); Acoustic Pressure Emissions: 54 dB(A)
Operating Environment	Operating Temperature Range: 50 to 90.5%; Recommended Operating Temperature: 59 to 90.5%; Storage Temperature Range: -4 to 10.4%; Non-Operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 10 to 80% RH; Recommended Humidity Operating Range: 30 to 70% RH
Security Management	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPNI community password change, SNMPN3, 802.1 x, Firewall, Access Control List; HP ePrint: HTTPS with certificate validation, HTTP Basic Access authentication, SASL authentication
Accessories	HP LaserJet 500-sheet Feeder/Tray CE530A, HP LaserJet MFP M525 Cabinet CF338A
HP Service and Support Options	U6Z65E - HP 3 year Next business day + Defective Media retention LJ Pro M521/435 Multifunction printer Support U6Z61E - HP 3 year 4 hour 3x5 LJ Pro M521/435 Multifunction printer Hardware Support U6Z62E - HP 3 year 4 hour 13X5 LJ Pro M521/435 Multifunction printer Hardware Support U6Z67E - HP 1 year 4 hour 13X5 LJ Pro M521/435 Multifunction printer Hardware Support U6Z67E - HP 1 year Post Warranty Next business day + Defective Media retention LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 9X5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/435 Multifunction printer Support U6Z69PE - HP 1 year Post Warranty 4 hour 13x5 LJ Pro M521/43

Learn more at

hp.com

¹ One CE255A cartridge included and its declared yield is 6000 pages basing on ISO/IEC 19752. Actual yield vary considerably based on images printed and other factors. For details please see http://www.hp.com/go/learnaboutsupplies.Pages may vary based on customer printing conditions and usage. And users can also purchase CE255X cartridge for this printer, which declared yield is 12500 pages basing on ISO/IEC 19752. Values subject to change. Power numbers are the highest values measured using all standard voltages. See hp.com/support for current information. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. ³ Approximate average yield based on ISO/IEC 19752. Actual yield varies considerably based on printer platform, content of printed pages and other factors. For details see http://www.hp.com/go/learnaboutsupplies ⁴ Based on standard ITU-T test image #1 at standard resolution. More complicated pages or higher resolution will take longer and use more memory. ⁵ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ⁶ Exact speed varies depending on the system configuration, software application, driver, and document complexity. ⁷ Sexact speed varies depending on the system configuration, software application, driver, and document complexity. ⁷ Sexact speed varies depending on on the system configuration, software application, driver and document complexity. ⁷ Sexact speed varies depending on on the system configuration, software application, driver and document complexity. ⁷ Sexact speed varies depending on scan resolution, network conditions, computer performance and application software.

