



swift



smart



tough

**MH-C801D**

## **EIGHT CELL 1 HOUR CHARGER**

### **SPECIFICATIONS**

<b>Charge Time</b>	1 hr. (normal charge) / 2 hr. (soft charge)
<b>Charge Current</b>	2000mA (AA), 700mA (AAA)
<b>Power Source</b>	100-240 VAC, 50/60Hz
<b>Conditioning Discharge Current</b>	250mA
<b>Supported Batteries</b>	1 to 8 AA/AAA NiMH or NiCD rechargeables

### **FEATURES AND BENEFITS**

#### **Eight Independent Charging Circuits**

Charge 1 to 8 batteries.  
Mix rechargeable AA / AAA batteries.

#### **LCD Display**

Displays charging and conditioning status.  
Status is described in English.

#### **Built-in Deep Battery Conditioning System**

Cycle charges, discharges and recharges batteries.  
Restores batteries to their optimal performance level.  
Reduces memory effect.

#### **Selectable Soft and Rapid Charge Modes**

Soft charge option for highest battery life.  
Rapid charge option for shortest charge time.

#### **Precision Microprocessor Controlled**

0.001V voltage detection.  
No under-charge.  
No over-charge.  
Just the right charge every time.  
Maximum battery longevity.

#### **Heavy Duty International AC Adapter**

Worldwide compatibility:  
Universal auto-ranging switching adapter.  
Made to last even in rough environments:  
Uses a rugged DIN connector.  
For home and travel.

#### **Integrated Safety Protection Device**

Charger will not apply charging current in abnormal situations:  
Battery polarity reversal  
Alkaline batteries  
Short circuits

100% Factory Tested.  
Manufactured to the world's highest quality standards in ISO-9001 facilities.

### **ORDERING INFORMATION**



**BROUGHT TO YOU BY**  
**MAHA®**  
Maha Energy Corporation  
[www.mahaenergy.com](http://www.mahaenergy.com)

All brand names are registered trademarks of their perspective owners.